TS3A27518E-Q1 具有集成 IEC L-4 ESD 及 1.8V 逻辑兼容控制输入的 6 位、2 选 1 多路复用器或多路信号分离器

1 特性

- 符合汽车应用要求
- 具有符合 AEC-Q100 标准的下列特性：
  - 器件温度等级 2：-40°C 至 105°C 环境工作温度范围
  - 器件 HBM ESD 分类等级 H2
  - 器件 CDM ESD 分类等级 C3B
- 提供功能安全型
  - 有助于进行功能安全系统设计的文档
- 1.65V 至 3.6V 单电源运行
- 关断保护（在处于断电模式时提供隔离，在 V_+ = 0 时处于高阻抗状态）
- 低电容开关，21.5pF（典型值）
- 可为高速轨到轨信号处理提供高达 240MHz 的带宽
- 串扰及断开隔离为 -62dB
- 用于控制输入的 1.8V 逻辑阈值兼容性
- 可耐受 3.6V 电压的控制输入
- ESD 性能：NC/NO 端口
  - ±6kV 接触放电 (IEC 61000-4-2)
- 24 引脚 TSSOP (7.80mm × 4.40mm) 和 24 引脚 QFN (4.00mm × 4.00mm) 封装

2 应用

- SD/SDIO 和 MMC 两端口多路复用器
- PC VGA 视频多路复用器/视频系统
- 音频和视频信号路由

3 说明

TS3A27518E-Q1 是一款 6 位、2 选 1 多路复用器/多路解复用器，其设计工作电压为 1.65V 至 3.6V。此器件可以处理数字信号和模拟信号，并允许向任意方向传输高达 V_+ 的信号。TS3A27518E-Q1 有两个控制引脚，每个引脚可同时控制三个 2 选 1 复用器，并且一个使能引脚可用于将所有输出置于高阻抗模式。这个控制引脚与 1.8V 逻辑阈值兼容并且也与 2.5V 和 3.3V 阈值向后兼容。

由于 SDIO 接口包含 6 位信号，即 CMD、CLK 和 Data[0:3] 信号，TS3A27518E-Q1 允许 SD、SDIO 和多媒体卡主机控制器扩展至多个卡或者外设。TS3A27518E-Q1 有两个控制引脚，这两个引脚可为用户提供附加灵活性，例如复用两个设备中不同的音视频信号（诸如 LCD 电视、LCD 监视器、或者笔记本扩展坞）的功能。

封装信息(1)

器件型号	封装	封装尺寸（标称值）
TS3A27518E-Q1	RTW (WQFN, 24)	4.00mm × 4.00mm
	PW (TSSOP, 24)	7.80mm × 4.40mm

(1) 如需了解所有可用封装，请参阅数据表末尾的可订购产品附录。



Copyright © 2016, Texas Instruments Incorporated

功能方框图

本文档旨在为方便起见，提供有关 TI 产品中文版本的信息，以确认产品的概要。有关适用的官方英文版本的最新信息，请访问 www.ti.com，其内容始终优先。TI 不保证翻译的准确性和有效性。在实际设计之前，请务必参考最新版本的英文版本。

Table of Contents

1 特性 1
2 应用 1
3 说明 1
4 Revision History 2
5 Pin Configuration and Functions 3
6 Specifications 4
6.1 Absolute Maximum Ratings 4
6.2 ESD Ratings 4
6.3 Recommended Operating Conditions 4
6.4 Thermal Information 5
6.5 Electrical Characteristics for 3.3-V Supply 5
6.6 Electrical Characteristics for 2.5-V Supply 7
6.7 Electrical Characteristics for 1.8-V Supply 9
6.8 Typical Characteristics 11
7 Parameter Measurement Information 14
8 Detailed Description 19
8.1 Overview 19
8.2 Functional Block Diagram 19
8.3 Feature Description 19
8.4 Device Functional Modes 19
9 Application and Implementation 20
9.1 Application Information 20
9.2 Typical Application 20
10 Power Supply Recommendations 21
11 Layout 22
11.1 Layout Guidelines 22
11.2 Layout Example 22
12 Device and Documentation Support 23
12.1 Documentation Support 23
12.2 接收文档更新通知 23
12.3 支持资源 23
12.4 Trademarks 23
12.5 Electrostatic Discharge Caution 23
12.6 术语表 23
13 Mechanical, Packaging, and Orderable Information 23

4 Revision History

注：以前版本的页码可能与当前版本的页码不同

Changes from Revision C (January 2019) to Revision D (November 2022) — **Page**

- 更新了整个文档中的表格、图和交叉参考的编号格式 1
- 向 *特性* 部分添加了“提供功能安全”信息 1

Changes from Revision B (May 2012) to Revision C (January 2019) — **Page**

- 添加了 *器件信息* 表、*ESD 等级* 表、*建议运行条件* 表、*特性说明* 部分、*器件功能模式*、*应用和实施* 部分、*电源相关建议* 部分、*布局* 部分、*器件和文档支持* 部分以及 *机械、封装和可订购信息* 部分 1
- 更新了整个文档中的表格、图和交叉参考的编号格式 1

Changes from Revision A (March 2012) to Revision B (May 2012) — **Page**

- 将器件的温度等级从 1 更改为 2，删除了最大耐受电压信息，将 C3B2 更改为 C3B 1
- 在订购信息表中添加了额外一行 1
- Changed T_A = –40°C to 85°C to T_A = –40°C to 105°C 5
- Changed Full to –40°C to 85°C and added extra row with 85°C to 105°C and limits -7.5 to 7.5 5
- Changed Full to –40°C to 85°C and added extra row with 85°C to 105°C with limits 68 5
- Changed Full to –40°C to 85°C and added extra row with 85°C to 105°C with limits 70 5
- Changed Full to –40°C to 85°C and added extra row with 85°C to 105°C with limits 5 µA 5
- Changed T_A = –40°C to 85°C to T_A = –40°C to 105°C 7
- Changed Full to –40°C to 85°C and added extra row with 85°C to 105°C with limits 38.4 7
- Changed Full to –40°C to 85°C and added extra row with 85°C to 105°C with limits 3 7
- Changed T_A = –40°C to 85°C to T_A = –40°C to 105°C 9
- Changed Full to –40°C to 85°C and added extra row with 85°C to 105°C and limits –5.8 to 5.8 9
- Changed Full to –40°C to 85°C and added extra row with 85°C to 105°C with limits 35.2 9
- Changed Full to –40°C to 85°C and added extra row with 85°C to 105°C with limits 2.5 9

Copyright © 2022 Texas Instruments Incorporated

5 Pin Configuration and Functions



图 5-1. RTW Package, 24-Pin WQFN (Top View)



图 5-2. PW Package, 24-Pin TSSOP (Top View)

表 5-1. Pin Functions

PIN			TYPE(1)	DESCRIPTION
NAME	RTW	PW		
COM1	1	4	I/O	Common-signal path
COM2	3	6	I/O	Common-signal path
COM3	4	7	I/O	Common-signal path
COM4	6	9	I/O	Common-signal path
COM5	7	10	I/O	Common-signal path
COM6	9	12	I/O	Common-signal path
$\overline{EN}$	17	20	I	Digital control to enable or disable all signal paths
GND	2	5	—	Ground.
IN1	21	24	I	Digital control to connect COM to NC or NO
IN2	11	14	I	Digital control to connect COM to NC or NO
N.C.	24	3	—	Not connected
NC1	23	2	I/O	Normally closed-signal path
NC2	22	1	I/O	Normally closed-signal path
NC3	20	23	I/O	Normally closed-signal path
NC4	18	21	I/O	Normally closed-signal path
NC5	16	19	I/O	Normally closed-signal path
NC6	19	22	I/O	Normally closed-signal path
NO1	8	11	I/O	Normally open-signal path
NO2	10	13	I/O	Normally open-signal path
NO3	12	15	I/O	Normally open-signal path
NO4	14	17	I/O	Normally open-signal path
NO5	15	18	I/O	Normally open-signal path
NO6	13	16	I/O	Normally open-signal path
V_{CC}	5	8	—	Voltage supply

(1) I = input, O = output

Copyright © 2022 Texas Instruments Incorporated

6 Specifications

6.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)(1)

			MIN	MAX	UNIT
V_+	Supply voltage range(2)		–0.5	4.6	V
V_{NC} V_{NO} V_{COM}	Analog voltage range(2) (3) (4)		–0.5	4.6	V
I_K	Analog port diode current(5)	$V_+ < V_{NC}$, V_{NO}, $V_{COM} < 0$	–50		mA
I_{NC} I_{NO} I_{COM}	ON-state switch current(6)	V_{NC}, V_{NO}, V_{COM} = 0 to V_+	–50	50	mA
V_I	Digital input voltage range(2) (3)		–0.5	4.6	V
I_{IK}	Digital input clamp current(2) (3)	$V_{IO} < V_I < 0$	–50		mA
I_+	Continuous current through V_+			100	mA
I_{GND}	Continuous current through GND		–100		mA
T_{stg}	Storage temperature range		–65	150	°C

(1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions*. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
(2) All voltages are with respect to ground, unless otherwise specified.
(3) The input and output voltage ratings may be exceeded if the input and output clamp-current ratings are observed.
(4) This value is limited to 5.5 V maximum.
(5) Requires clamp diodes on analog port to V_+.
(6) Pulse at 1-ms duration <10% duty cycle

6.2 ESD Ratings

			VALUE	UNIT
$V_{(ESD)}$	Electrostatic discharge	Human-body model (HBM), per ANSI/ESDA/JEDEC JS-001(1) AEC-Q100 Classification Level H2	±2000	V
		Charged-device model (CDM), per JEDEC specification JESD22-C101(2) AEC-Q100 Classification Level C3B	±750	

(1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process..
(2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

6.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

		MIN	MAX	UNIT
Supply voltage	V_{CC}	1.65	3.6	V
Analog signal voltage	V_{NC}	0	V_{CC}	V
	V_{NO}			
	V_{COM}			
Digital input voltage	V_I	0	V_{CC}	V

Copyright © 2022 Texas Instruments Incorporated

6.4 Thermal Information

THERMAL METRIC (1)		TS3A27518E		UNIT
		PW (TSSOP)	RTW (WQFN)	
		24 PINS	24 PINS	
$R_{\theta JA}$	Junction-to-ambient thermal resistance	104	40.7	°C/W
$R_{\theta JC(top)}$	Junction-to-case (top) thermal resistance	51.6	42.9	°C/W
$R_{\theta JB}$	Junction-to-board thermal resistance	57.5	19.2	°C/W
ψ_{JT}	Junction-to-top characterization parameter	9.9	1	°C/W
ψ_{JB}	Junction-to-board characterization parameter	57.1	19.3	°C/W
$R_{\theta JC(bot)}$	Junction-to-case (bottom) thermal resistance	—	8	°C/W

(1) For more information about traditional and new thermal metrics, see the *Semiconductor and IC Package Thermal Metrics* application report.

6.5 Electrical Characteristics for 3.3-V Supply

V_+ = 3 V to 3.6 V, T_A = –40°C to 105°C (unless otherwise noted)

PARAMETER	SYMBOL	TEST CONDITIONS		T_A	V_+	MIN	TYP	MAX	UNIT
Analog Switch									
ON-state resistance	r_{on}	0 ≤ (V_{NC} or V_{NO}) ≤ V_+, I_{COM} = –32 mA,	Switch ON, See 图 7-1	25°C	3 V		4.4	6.2	Ω
				Full				7.6	
ON-state resistance match between channels	Δr_{on}	V_{NC} or V_{NO} = 2.1 V, I_{COM} = –32 mA,	Switch ON, See 图 7-1	25°C	3 V		0.3	0.7	Ω
				Full				0.8	
ON-state resistance flatness	$r_{on(flat)}$	0 ≤ (V_{NC} or V_{NO}) ≤ V_+, I_{COM} = –32 mA,	Switch ON, See 图 7-2	25°C	3 V		0.95	2.1	Ω
				Full				2.3	
NC, NO OFF leakage current	$I_{NC(OFF)}$, $I_{NO(OFF)}$	V_{NC} or V_{NO} = 1 V, V_{COM} = 3 V, or V_{NC} or V_{NO} = 3 V, V_{COM} = 1 V,	Switch OFF, See 图 7-2	25°C	3.6 V	–0.5	0.05	0.5	µA
				Full		–7		7	
	$I_{NC(PWROFF)}$, $I_{NO(PWROFF)}$	V_{NC} or V_{NO} = 0 to 3.6 V, V_{COM} = 3.6 V to 0, or V_{NC} or V_{NO} = 3.6 V to 0, V_{COM} = 0 to 3.6 V,		25°C	0 V	–1	0.05	1	
				Full		–12		12	
COM OFF leakage current	$I_{COM(OFF)}$	V_{NC} or V_{NO} = 3 V, V_{COM} = 1 V, or V_{NC} or V_{NO} = 1 V, V_{COM} = 3 V,	Switch OFF, See 图 7-2	25°C	3.6 V	–1	0.01	1	µA
				Full		–2		2	
	$I_{COM(PWROFF)}$	V_{NC} or V_{NO} = 3.6 V to 0, V_{COM} = 0 to 3.6 V, or V_{NC} or V_{NO} = 0 to 3.6 V, V_{COM} = 3.6 V to 0,		25°C	0 V	–1	0.02	1	
				Full		–12		12	
NC, NO ON leakage current	$I_{NO(ON)}$, $I_{NC(ON)}$	V_{NC} or V_{NO} = 1 V, V_{COM} = Open, or V_{NC} or V_{NO} = 3 V, V_{COM} = Open,	Switch ON, See 图 7-3	25°C	3.6 V	–2.5	0.04	2.2	µA
				–40°C to 85°C		–7		7	
				85°C to 105°C		–7.5		7.5	
COM ON leakage current	$I_{COM(ON)}$	V_{NC} or V_{NO} = Open, V_{COM} = 1 V, or V_{NC} or V_{NO} = Open, V_{COM} = 3 V,	Switch ON, See 图 7-3	25°C	3.6 V	–2	0.03	2	µA
				Full		–7		7	
Digital Control Inputs (IN1, IN2, $\overline{EN}$) (1)									
Input logic high	V_{IH}			Full	3.6 V	1.2		3.6	V
Input logic low	V_{IL}			Full	3.6 V	0		0.65	V

6.5 Electrical Characteristics for 3.3-V Supply (continued)

V_+ = 3 V to 3.6 V, T_A = –40°C to 105°C (unless otherwise noted)

PARAMETER	SYMBOL	TEST CONDITIONS		T_A	V_+	MIN	TYP	MAX	UNIT
Input leakage current	I_{IH}, I_{IL}	V_I = V_+ or 0		25°C	3.6 V	–0.1	0.05	0.1	µA
				Full		–2.5		2.5	
Dynamic									
Turn-on time	t_{ON}	V_{COM} = V_+, R_L = 50 Ω,	C_L = 35 pF, See 图 7-5	25°C	3.3 V		18.1	59	ns
				–40°C to 85°C	3 V to 3.6 V			60	
				85°C to 105°C				68	
Turn-off time	t_{OFF}	V_{COM} = V_+, R_L = 50 Ω,	C_L = 35 pF, See 图 7-5	25°C	3.3 V		25.4	60.6	ns
				–40°C to 85°C	3 V to 3.6 V			61	
				85°C to 105°C				70	
Break-before-make time	t_{BBM}	V_{NC} = V_{NO} = V_+/2, R_L = 50 Ω,	C_L = 35 pF, See 图 7-6	25°C	3.3 V	4	11.1	22.7	ns
				Full	3 V to 3.6 V			28	
Charge injection	Q_C	V_{GEN} = 0, R_{GEN} = 0,	C_L = 0.1 nF, See 图 7-10	25°C	3.3 V		0.81		pC
NC, NO OFF capacitance	$C_{NC(OFF)}$, $C_{NO(OFF)}$	V_{NC} or V_{NO} = V_+ or GND, Switch OFF,	See 图 7-4	25°C	3.3 V		13		pF
COM OFF capacitance	$C_{COM(OFF)}$	V_{NC} or V_{NO} = V_+ or GND, Switch OFF,	See 图 7-4		3.3 V		8.5		pF
NC, NO ON capacitance	$C_{NC(ON)}$, $C_{NO(ON)}$	V_{NC} or V_{NO} = V_+ or GND, Switch OFF,	See 图 7-4	25°C	3.3 V		21.5		pF
COM ON capacitance	$C_{COM(ON)}$	V_{COM} = V_+ or GND, Switch ON,	See 图 7-4	25°C	3.3 V		21.5		pF
Digital input capacitance	C_I	V_I = V_+ or GND	See 图 7-4	25°C	3.3 V		2		pF
Bandwidth	BW	R_L = 50 Ω,	Switch ON, See 图 7-6	25°C	3.3 V		240		MHz
OFF isolation	O_{ISO}	R_L = 50 Ω, f = 10 MHz,	Switch OFF, See 图 7-8	25°C	3.3 V		–62		dB
Crosstalk	X_{TALK}	R_L = 50 Ω, f = 10 MHz,	Switch ON, See 图 7-9	25°C	3.3 V		–62		dB
Crosstalk adjacent	$X_{TALK(ADJ)}$	R_L = 50 Ω, f = 10 MHz,	Switch ON, See 图 7-9	25°C	3.3 V		–71		dB
Total harmonic distortion	THD	R_L = 600 Ω, C_L = 50 pF,	f = 20 Hz to 20 kHz, See 图 7-11	25°C	3.3 V		0.05		%
Supply									
Positive supply current	I_+	V_I = V_+ or GND,	Switch ON or OFF	25°C	3.6 V		0.04	0.3	µA
				–40°C to 85°C				3	
				85°C to 105°C				5	

(1) All unused digital inputs of the device must be held at V_+ or GND to ensure proper device operation. Refer to the TI application report, *Implications of Slow or Floating CMOS Inputs*, literature number SCBA004.

Copyright © 2022 Texas Instruments Incorporated

6.6 Electrical Characteristics for 2.5-V Supply

V_+ = 2.3 V to 2.7 V, T_A = –40°C to 105°C (unless otherwise noted)

PARAMETER	SYMBOL	TEST CONDITIONS		T_A	V_+	MIN	TYP	MAX	UNIT
Analog Switch									
ON-state resistance	r_{on}	0 ≤ (V_{NC} or V_{NO}) ≤ V_+, I_{COM} = –32 mA,	Switch ON, See 图 7-1	25°C	2.3 V		5.5	9.6	Ω
				Full				11.5	
ON-state resistance match between channels	Δr_{on}	V_{NC} or V_{NO} = 1.6 V, I_{COM} = –32 mA,	Switch ON, See 图 7-1	25°C	2.3 V		0.3	0.8	Ω
				Full				0.9	
ON-state resistance flatness	$r_{on(flat)}$	0 ≤ (V_{NC} or V_{NO}) ≤ V_+, I_{COM} = –32 mA,	Switch ON, See 图 7-2	25°C	2.3 V		0.91	2.2	Ω
				Full				2.3	
NC, NO OFF leakage current	$I_{NC(OFF)}$, $I_{NO(OFF)}$	V_{NC} or V_{NO} = 0.5 V, V_{COM} = 2.3 V, or V_{NC} or V_{NO} = 2.3 V, V_{COM} = 0.5 V,	Switch OFF, See 图 7-2	25°C	2.7 V	–0.3	0.04	0.3	µA
				Full		–6		6	
	$I_{NC(PWROFF)}$, $I_{NO(PWROFF)}$	V_{NC} or V_{NO} = 0 to 2.7 V, V_{COM} =2.7 V to 0, or V_{NC} or V_{NO} = 2.7 V to 0, V_{COM} = 0 to 2.7 V,		25°C	0 V	–0.6	0.02	0.6	
				Full		–10		10	
COM OFF leakage current	$I_{COM(OFF)}$	V_{NC} or V_{NO} = 0.5 V, V_{COM} = 2.3 V, or V_{NC} or V_{NO} = 2.3 V, V_{COM} = 0.5 V,	Switch OFF, See 图 7-2	25°C	2.7 V	–0.7	0.02	0.7	µA
				Full		–1		1	
	$I_{COM(PWROFF)}$	V_{NC} or V_{NO} = 2.7 V to 0, V_{COM} = 0 to 2.7 V, or V_{NC} or V_{NO} = 0 to 2.7 V, V_{COM} = 2.7 V to 0,		25°C	0 V	–0.7	0.02	0.7	
				Full		–7.2		7.2	
NC, NO ON leakage current	$I_{NO(ON)}$, $I_{NC(ON)}$	V_{NC} or V_{NO} = 0.5 V or 2.3 V, V_{COM} = Open,	Switch ON, See 图 7-3	25°C	2.7 V	–2.1	0.03	2.1	µA
				Full		–6		6	
COM ON leakage current	$I_{COM(ON)}$	V_{NC} or V_{NO} = Open, V_{COM} = 0.5 V, or V_{NC} or V_{NO} = Open, V_{COM} = 2.3 V,	Switch ON, See 图 7-3	25°C	2.7 V	–2	0.02	2	µA
				Full		–5.7		5.7	
Digital Control Inputs (IN1, IN2, $\overline{EN}$)(1)									
Input logic high	V_{IH}	V_I = V_+ or GND		Full	2.7 V	1.15		3.6	V
Input logic low	V_{IL}			Full	2.7 V	0		0.55	V
Input leakage current	I_{IH}, I_{IL}	V_I = V_+ or 0		25°C	2.7 V	-0.1	0.01	0.1	µA
				Full		–2.1		2.1	
Dynamic									
Turn-on time	t_{ON}	V_{COM} = V+, R_L = 50 Ω,	C_L = 35 pF, See 图 7-5	25°C	2.5 V		17.2	36.8	ns
				Full	2.3 V to 2.7 V			42.5	
Turn-off time	t_{OFF}	V_{COM} = V+, R_L = 50 Ω,	C_L = 35 pF, See 图 7-5	25°C	2.5 V		17.1	29.8	ns
				–40°C to 85°C	2.3 V to 2.7 V			34.4	
				85°C to 105°C				38.4	
Break-before-make time	t_{BBM}	V_{NC} = V_{NO} = V_+/2, R_L = 50 Ω,	C_L = 35 pF, See 图 7-6	25°C	2.5 V	4.5	13	30	ns
				Full	2.3 V to 2.7 V			33.3	
Charge injection	Q_C	V_{GEN} = 0, R_{GEN} = 0,	C_L = 0.1 nF, See 图 7-10	25°C	2.5 V		0.47		pC
NC, NO OFF capacitance	$C_{NC(OFF)}$, $C_{NO(OFF)}$	V_{NC} or V_{NO} = V_+ or GND, Switch OFF,	See 图 7-4	25°C	2.5 V		13.5		pF
COM OFF capacitance	$C_{COM(OFF)}$	V_{NC} or V_{NO} = V_+ or GND, Switch OFF,	See 图 7-4		2.5 V		9		pF

Copyright © 2022 Texas Instruments Incorporated

6.6 Electrical Characteristics for 2.5-V Supply (continued)

V_+ = 2.3 V to 2.7 V, T_A = –40°C to 105°C (unless otherwise noted)

PARAMETER	SYMBOL	TEST CONDITIONS		T_A	V_+	MIN	TYP	MAX	UNIT
NC, NO ON capacitance	$C_{NC(ON)}$, $C_{NO(ON)}$	V_{NC} or V_{NO} = V_+ or GND, Switch OFF,	See 图 7-4	25°C	2.5 V		22		pF
COM ON capacitance	$C_{COM(ON)}$	V_{COM} = V_+ or GND, Switch ON,	See 图 7-4	25°C	2.5 V		22		pF
Digital input capacitance	C_I	V_I = V_+ or GND	See 图 7-4	25°C	2.5 V		2		pF
Bandwidth	BW	R_L = 50 Ω,	Switch ON, See 图 7-6	25°C	2.5 V		240		MHz
OFF isolation	O_{ISO}	R_L = 50 Ω, f = 10 MHz,	Switch OFF, See 图 7-8	25°C	2.5 V		–62		dB
Crosstalk	X_{TALK}	R_L = 50 Ω, f = 10 MHz,	Switch ON, See 图 7-9	25°C	2.5 V		–62		dB
Crosstalk adjacent	$X_{TALK(ADJ)}$	R_L = 50 Ω, f = 10 MHz,	Switch ON, See 图 7-9	25°C	2.5 V		–71		dB
Total harmonic distortion	THD	R_L = 600 Ω, C_L = 50 pF,	f = 20 Hz to 20 kHz, See 图 7-11	25°C	2.5 V		0.06		%
Supply									
Positive supply current	I_+	V_I = V_+ or GND,	Switch ON or OFF	25°C	2.7 V		0.01	0.1	µA
				–40°C to 85°C				2	
				85°C to 105°C				3	

(1) All unused digital inputs of the device must be held at V_+ or GND to ensure proper device operation. Refer to the TI application report, *Implications of Slow or Floating CMOS Inputs*, literature number SCBA004.

Copyright © 2022 Texas Instruments Incorporated

6.7 Electrical Characteristics for 1.8-V Supply

V_+ = 1.65 V to 1.95 V, T_A = –40°C to 105°C (unless otherwise noted)

PARAMETER	SYMBOL	TEST CONDITIONS		T_A	V_+	MIN	TYP	MAX	UNIT
Analog Switch									
ON-state resistance	r_{on}	0 ≤ (V_{NC} or V_{NO}) ≤ V_+, I_{COM} = –32 mA,	Switch ON, See 图 7-1	25°C	1.65 V		7.1	14.4	Ω
				Full				16.3	
ON-state resistance match between channels	Δr_{on}	V_{NC} or V_{NO} = 1.5 V, I_{COM} = –32 mA,	Switch ON, See 图 7-1	25°C	1.65 V		0.3	1	Ω
				Full				1.2	
ON-state resistance flatness	$r_{on(flat)}$	0 ≤ (V_{NC} or V_{NO}) ≤ V_+, I_{COM} = –32 mA,	Switch ON, See 图 7-2	25°C	1.65 V		2.7	5.5	Ω
				Full				7.3	
NC, NO OFF leakage current	$I_{NC(OFF)}$, $I_{NO(OFF)}$	V_{NC} or V_{NO} = 0.3 V, V_{COM} = 1.65 V, or V_{NC} or V_{NO} = 1.65 V, V_{COM} = 0.3 V	Switch OFF, See 图 7-2	25°C	1.95 V	–0.25	0.03	0.25	µA
				Full		–5		5	
	$I_{NC(PWROFF)}$, $I_{NO(PWROFF)}$	V_{NC} or V_{NO} = 1.95 V to 0, V_{COM} = 0 to 1.95 V, or V_{NC} or V_{NO} = 0 to 1.95 V, V_{COM} = 1.95 V to 0,		25°C	0 V	–0.4	0.01	0.4	µA
				Full		–7.2		7.2	
COM OFF leakage current	$I_{COM(OFF)}$, $I_{COM(OFF)}$	V_{NC} or V_{NO} = 0.3 V, V_{COM} = 1.65 V, or V_{NC} or V_{NO} = 1.65 V, V_{COM} = 0.3 V	Switch OFF, See 图 7-2	25°C	1.95 V	–0.4	0.02	0.4	µA
				Full		–0.9		0.9	
	$I_{COM(PWROFF)}$, $I_{COM(PWROFF)}$	V_{NC} or V_{NO} = 1.95 V to 0, V_{COM} = 0 to 1.95 V, or V_{NC} or V_{NO} = 0 to 1.95 V, V_{COM} = 1.95 V to 0,		25°C	0 V	–0.4	0.02	0.4	µA
				–40°C to 85°C		–5		5	
				85°C to 105°C		–5.8		5.8	
NC, NO ON leakage current	$I_{NO(ON)}$, $I_{NC(ON)}$	V_{NC} or V_{NO} = 0.3 V, V_{COM} = Open, or V_{NC} or V_{NO} = 1.65 V, V_{COM} = Open,	Switch ON, See 图 7-3	25°C	1.95 V	–2	0.02	2	µA
				Full		–5.2		5.2	
COM ON leakage current	$I_{COM(ON)}$	V_{NC} or V_{NO} = Open, V_{COM} = 0.3 V, or V_{NC} or V_{NO} = Open, V_{COM} = 1.65 V,	Switch ON, See 图 7-3	25°C	1.95 V	–2	0.02	2	µA
				Full		–5.2		5.2	
Digital Control Inputs (IN1, IN2, $\overline{EN}$)(1)									
Input logic high	V_{IH}	V_I = V_+ or GND		Full	1.95 V	1		3.6	V
Input logic low	V_{IL}			Full	1.95 V	0		0.4	V
Input leakage current	I_{IH}, I_{IL}	V_I = V_+ or 0		25°C	1.95 V	-0.1	0.01	0.1	µA
				Full		-2.1		2.1	
Dynamic									
Turn-on time	t_{ON}	V_{COM} = V_+, R_L = 50 Ω,	C_L = 35 pF, See 图 7-5	25°C	1.8 V		14.1	49.3	ns
				Full	1.65 V to 1.95 V			56.7	
Turn-off time	t_{OFF}	V_{COM} = V_+, R_L = 50 Ω,	C_L = 35 pF, See 图 7-5	25°C	1.8 V		16.1	26.5	ns
				–40°C to 85°C	1.65 V to 1.95 V			31.2	
				85°C to 105°C				35.2	
Break-before-make time	t_{BBM}	V_{NC} = V_{NO} = V_+/2, R_L = 50 Ω,	C_L = 35 pF, See 图 7-6	25°C	1.8 V	5.3	18.4	58	ns
				Full	1.65 V to 1.95 V			58	
Charge injection	Q_C	V_{GEN} = 0, R_{GEN} = 0,	C_L = 1 nF, See 图 7-10	25°C	1.8 V		0.21		pC

Copyright © 2022 Texas Instruments Incorporated

6.7 Electrical Characteristics for 1.8-V Supply (continued)

V_+ = 1.65 V to 1.95 V, T_A = –40°C to 105°C (unless otherwise noted)

PARAMETER	SYMBOL	TEST CONDITIONS		T_A	V_+	MIN	TYP	MAX	UNIT
NC, NO OFF capacitance	$C_{NC(OFF)}$, $C_{NO(OFF)}$	V_{NC} or V_{NO} = V_+ or GND, Switch OFF,	See 图 7-4	25°C	1.8 V		9		pF
NC, NO ON capacitance	$C_{NC(ON)}$, $C_{NO(ON)}$	V_{NC} or V_{NO} = V_+ or GND, Switch OFF,	See 图 7-4	25°C	1.8 V		22		pF
COM ON capacitance	$C_{COM(ON)}$	V_{COM} = V_+ or GND, Switch ON,	See 图 7-4	25°C	1.8 V		22		pF
Digital input capacitance	C_I	V_I = V_+ or GND	See 图 7-4	25°C	1.8 V		2		pF
Bandwidth	BW	R_L = 50 Ω,	Switch ON, See 图 7-6	25°C	1.8 V		240		MHz
OFF isolation	O_{ISO}	R_L = 50 Ω, f = 10 MHz,	Switch OFF, See 图 7-8	25°C	1.8 V		-60		dB
Crosstalk	X_{TALK}	R_L = 50 Ω, f = 10 MHz,	Switch ON, See 图 7-9	25°C	1.8 V		-60		dB
Crosstalk adjacent	$X_{TALK(ADJ)}$	R_L = 50 Ω, f = 10 MHz,	Switch ON, See 图 7-9	25°C	1.8 V		-71		dB
Total harmonic distortion	THD	R_L = 600 Ω, C_L = 50 pF,	f = 20 Hz to 20 kHz, See 图 7-11	25°C	1.8 V		0.1		%
Supply									
Positive supply current	I_+	V_I = V_+ or GND,	Switch ON or OFF	25°C	1.95 V		0.01	0.1	μA
				–40°C to 85°C				1.5	
				85°C to 105°C				2.5	

(1) All unused digital inputs of the device must be held at V_+ or GND to ensure proper device operation. Refer to the TI application report, *Implications of Slow or Floating CMOS Inputs*, literature number SCBA004.

Copyright © 2022 Texas Instruments Incorporated

6.8 Typical Characteristics



图 6-1. ON-State Resistance vs COM Voltage (V_{CC} = 3 V)



图 6-2. ON-State Resistance vs COM Voltage (V_{CC} = 2.3 V)



图 6-3. ON-State Resistance vs COM Voltage (V_{CC} = 1.65 V)



图 6-4. Leakage Current vs Temperature (V_{CC} = 3.3 V)



图 6-5. Supply Current vs Supply Voltage



图 6-6. Control Input Thresholds (IN1, T_A = 25°C)

Copyright © 2022 Texas Instruments Incorporated

6.8 Typical Characteristics (continued)



图 6-7. Crosstalk Adjacent



图 6-8. Crosstalk



图 6-9. Total Harmonic Distortion vs Frequency



图 6-10. OFF Isolation



图 6-11. Insertion Loss



图 6-12. Charge Injection vs Bias Voltage (1.8 V)

Copyright © 2022 Texas Instruments Incorporated

6.8 Typical Characteristics (continued)



图 6-13. Charge Injection vs Bias Voltage (2.5 V)



图 6-14. Charge Injection vs Bias Voltage (3.3 V)

Copyright © 2022 Texas Instruments Incorporated

7 Parameter Measurement Information

表 7-1. Parameter Description

SYMBOL	DESCRIPTION
V_{COM}	Voltage at COM
V_{NC}	Voltage at NC
V_{NO}	Voltage at NO
r_{on}	Resistance between COM and NC or NO ports when the channel is ON
Δr_{on}	Difference of r_{on} between channels in a specific device
$r_{on(flat)}$	Difference between the maximum and minimum value of r_{on} in a channel over the specified range of conditions
$I_{NC(OFF)}$	Leakage current measured at the NC port, with the corresponding channel (NC to COM) in the OFF state
$I_{NC(ON)}$	Leakage current measured at the NC port, with the corresponding channel (NC to COM) in the ON state and the output (COM) open
$I_{NO(OFF)}$	Leakage current measured at the NO port, with the corresponding channel (NO to COM) in the OFF state
$I_{NO(ON)}$	Leakage current measured at the NO port, with the corresponding channel (NO to COM) in the ON state and the output (COM) open
$I_{COM(OFF)}$	Leakage current measured at the COM port, with the corresponding channel (COM to NC or NO) in the OFF state
$I_{COM(ON)}$	Leakage current measured at the COM port, with the corresponding channel (COM to NC or NO) in the ON state and the output (NC or NO) open
V_{IH}	Minimum input voltage for logic high for the control input (IN, $\overline{EN}$)
V_{IL}	Maximum input voltage for logic low for the control input (IN, $\overline{EN}$)
V_I	Voltage at the control input (IN, $\overline{EN}$)
I_{IH}, I_{IL}	Leakage current measured at the control input (IN, $\overline{EN}$)
t_{ON}	Turn-on time for the switch. This parameter is measured under the specified range of conditions and by the propagation delay between the digital control (IN) signal and analog output NC or NO) signal when the switch is turning ON.
t_{OFF}	Turn-off time for the switch. This parameter is measured under the specified range of conditions and by the propagation delay between the digital control (IN) signal and analog output (NC or NO) signal when the switch is turning OFF.
Q_C	Charge injection is a measurement of unwanted signal coupling from the control (IN) input to the analog (NC or NO) output. This is measured in coulomb (C) and measured by the total charge induced due to switching of the control input. Charge injection, $Q_C = C_L \times \Delta V_{COM}$, C_L is the load capacitance and ΔV_{COM} is the change in analog output voltage.
$C_{NC(OFF)}$	Capacitance at the NC port when the corresponding channel (NC to COM) is OFF
$C_{NC(ON)}$	Capacitance at the NC port when the corresponding channel (NC to COM) is ON
$C_{NO(OFF)}$	Capacitance at the NC port when the corresponding channel (NO to COM) is OFF
$C_{NO(ON)}$	Capacitance at the NC port when the corresponding channel (NO to COM) is ON
$C_{COM(OFF)}$	Capacitance at the COM port when the corresponding channel (COM to NC) is OFF
$C_{COM(ON)}$	Capacitance at the COM port when the corresponding channel (COM to NC) is ON
C_I	Capacitance of control input (IN, $\overline{EN}$)
O_{ISO}	OFF isolation of the switch is a measurement of OFF-state switch impedance. This is measured in dB in a specific frequency, with the corresponding channel (NC to COM) in the OFF state.
X_{TALK}	Crosstalk is a measurement of unwanted signal coupling from an ON channel to an OFF channel (NC1 to NO1). Adjacent crosstalk is a measure of unwanted signal coupling from an ON channel to an adjacent ON channel (NC1 to NC2) .This is measured in a specific frequency and in dB.
BW	Bandwidth of the switch. This is the frequency in which the gain of an ON channel is –3 dB below the DC gain.
THD	Total harmonic distortion describes the signal distortion caused by the analog switch. This is defined as the ratio of root mean square (RMS) value of the second, third, and higher harmonic to the absolute magnitude of the fundamental harmonic.
I_+	Static power-supply current with the control (IN) pin at V_+ or GND

Copyright © 2022 Texas Instruments Incorporated



图 7-1. ON-state Resistance (r_{ON})



图 7-2. OFF-State Leakage Current ($I_{COM(OFF)}$, $I_{NC(OFF)}$, $I_{COM(PWROFF)}$, $I_{NC(PWROFF)}$)



图 7-3. ON-State Leakage Current ($I_{COM(ON)}$, $I_{NC(ON)}$)



图 7-4. Capacitance (C_I, $C_{COM(OFF)}$, $C_{COM(ON)}$, $C_{NC(OFF)}$, $C_{NC(ON)}$)



A. All input pulses are supplied by generators having the following characteristics: PRR ≤ 10 MHz, Z_O = 50 Ω, t_r < 5 ns, t_f < 5 ns.
B. C_L includes probe and jig capacitance.

图 7-5. Turn-On (t_{ON}) and Turn-Off Time (t_{OFF})



A. C_L includes probe and jig capacitance.
B. All input pulses are supplied by generators having the following characteristics: PRR ≤ 10 MHz, Z_O = 50 Ω, t_r < 5 ns, t_f < 5 ns.

图 7-6. Break-Before-Make Time (t_{BBM})

Copyright © 2022 Texas Instruments Incorporated



图 7-7. Bandwidth (BW)



图 7-8. OFF Isolation (O_{ISO})



图 7-9. Crosstalk (X_{TALK})



A. All input pulses are supplied by generators having the following characteristics: PRR ⩽ 10 MHz, Z_O = 50 Ω, t_r < 5 ns, t_f < 5 ns.
B. C_L includes probe and jig capacitance.

图 7-10. Charge Injection (Q_C)

Channel ON: COM to NO	V_I = V_{IH} or V_{IL}	R_L = 600 Ω
V_{SOURCE} = V_{CC} P-P	f_{SOURCE} = 20 Hz to 20 kHz	C_L = 50 pF



A. C_L includes probe and jig capacitance.

图 7-11. Total Harmonic Distortion (THD)

Copyright © 2022 Texas Instruments Incorporated

8 Detailed Description

8.1 Overview

The TS3A27518E-Q1 is a bidirectional, 6-channel, 1:2 multiplexer-demultiplexer designed to operate from 1.65 V to 3.6 V. This device can handle both digital and analog signals, and can transmit signals up to V_{CC} in either direction. The TS3A27518E-Q1 has two control pins, each controlling three 1:2 muxes at the same time, and an enable pin that puts all outputs in high-impedance mode. The control pins are compatible with 1.8-V logic thresholds and are backward compatible with 2.5-V and 3.3-V logic thresholds.

8.2 Functional Block Diagram



Copyright © 2016, Texas Instruments Incorporated

8.3 Feature Description

The isolation in power-down mode, V_{CC} = 0 feature places all switch paths in high-impedance state (High-Z) when the supply voltage equals 0 V.

8.4 Device Functional Modes

The TS3A27518E-Q1 is a bidirectional device that has two sets of three single-pole double-throw switches. Two digital signals control the 6 channels of the switch; one digital control for each set of three single-pole, double-throw switches. Digital input pin IN1 controls switches 1, 2, and 3, while pin IN2 controls switches 4, 5, and 6.

The TS3A27518E-Q1 has an $\overline{EN}$ pin that when set to logic high, it places all channels into a high-impedance or HIGH-Z state. 表 8-1 lists the functions of TS3A27518E-Q1.

表 8-1. Function Table

$\overline{EN}$	IN1	IN2	NC1/2/3 TO COM1/2/3, COM1/2/3 TO NC1/2/3	NC4/5/6 TO COM4/5/6, COM4/5/6 TO NC4/5/6	NO1/2/3 TO COM1/2/3, COM1/2/3 TO NO1/2/3	NO4/5/6 TO COM4/5/6, COM4/5/6 TO NO4/5/6
H	X	X	OFF	OFF	OFF	OFF
L	L	L	ON	ON	OFF	OFF
L	H	L	OFF	ON	ON	OFF
L	L	H	ON	OFF	OFF	ON
L	H	H	OFF	OFF	ON	ON

9 Application and Implementation

备注

以下应用部分中的信息不属于 TI 器件规格的范围，TI 不担保其准确性和完整性。TI 的客 户应负责确定器件是否适用于其应用。客户应验证并测试其设计，以确保系统功能。

9.1 Application Information

The switches are bidirectional, so the NO, NC, and COM pins can be used as either inputs or outputs.

9.2 Typical Application



图 9-1. SDIO Expander Application Block Diagram

9.2.1 Design Requirement

Ensure that all of the signals passing through the switch are within the recommended operating ranges to ensure proper performance. For more information, see *节 6.3*.

Copyright © 2022 Texas Instruments Incorporated

9.2.2 Detailed Design Procedure

The TS3A27518E-Q1 can operate properly without any external components. However, TI recommends connecting unused pins to the ground through a 50-Ω resistor to prevent signal reflections back into the device. TI also recommends that the digital control pins (INX) be pulled up to V_{CC} or down to GND to avoid undesired switch positions that could result from the floating pin.

For the RTW package connect the thermal pad to ground.

9.2.3 Application Curves



图 9-2. ON-State Resistance vs COM Voltage (V_{CC} = 3 V)

10 Power Supply Recommendations

TI recommends proper power-supply sequencing for all CMOS devices. Do not exceed the absolute maximum ratings, because stresses beyond the listed ratings can cause permanent damage to the device. Always sequence V_{CC} on first, followed by NO, NC, or COM. Although it is not required, power-supply bypassing improves noise margin and prevents switching noise propagation from the V_{CC} supply to other components. A 0.1-μF capacitor is adequate for most applications, if connected from V_{CC} to GND.

Copyright © 2022 Texas Instruments Incorporated

11 Layout

11.1 Layout Guidelines

To ensure reliability of the device, TI recommends following these common printed-circuit board layout guidelines:

- Bypass capacitors should be used on power supplies, and should be placed as close as possible to the V_{CC} pin
- Short trace-lengths should be used to avoid excessive loading
- For the RTW package, connect the thermal pad to ground

11.2 Layout Example



图 11-1. WQFN Layout Recommendation

Copyright © 2022 Texas Instruments Incorporated

12 Device and Documentation Support

12.1 Documentation Support

12.1.1 Related Documentation

For related documentation, see the following:

- Texas Instruments, *TS3A27518E-Q1 Functional Safety FIT Rate, FMD and Pin FMA* report

12.2 接收文档更新通知

要接收文档更新通知，请导航至 ti.com 上的器件产品文件夹。点击 *订阅更新* 进行注册，即可每周接收产品信息更改摘要。有关更改的详细信息，请查看任何已修订文档中包含的修订历史记录。

12.3 支持资源

TI E2E™ 支持论坛是工程师的重要参考资料，可直接从专家获得快速、经过验证的解答和设计帮助。搜索现有解答或提出自己的问题可获得所需的快速设计帮助。

链接的内容由各个贡献者“按原样”提供。这些内容并不构成 TI 技术规范，并且不一定反映 TI 的观点；请参阅 TI 的《使用条款》。

12.4 Trademarks

TI E2E™ is a trademark of Texas Instruments.
所有商标均为其各自所有者的财产。

12.5 Electrostatic Discharge Caution

This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

12.6 术语表

TI 术语表　　本术语表列出并解释了术语、首字母缩略词和定义。

13 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

Copyright © 2022 Texas Instruments Incorporated

重要声明和免责声明

TI 提供技术和可靠性数据（包括数据表）、设计资源（包括参考设计）、应用或其他设计建议、网络工具、安全信息和其他资源，不保证没有瑕疵且不做出任何明示或暗示的担保，包括但不限于对适销性、某特定用途方面的适用性或不侵犯任何第三方知识产权的暗示担保。

这些资源可供使用 TI 产品进行设计的熟练开发人员使用。您将自行承担以下全部责任：(1) 针对您的应用选择合适的 TI 产品，(2) 设计、验证并测试您的应用，(3) 确保您的应用满足相应标准以及任何其他安全、安保或其他要求。这些资源如有变更，恕不另行通知。TI 授权您仅可将这些资源用于研发本资源所述的 TI 产品的应用。严禁对这些资源进行其他复制或展示。您无权使用任何其他 TI 知识产权或任何第三方知识产权。您应全额赔偿因在这些资源的使用中对 TI 及其代表造成的任何索赔、损害、成本、损失和债务，TI 对此概不负责。

TI 提供的产品受 TI 的销售条款 (https:www.ti.com/legal/termsofsale.html) 或 ti.com 上其他适用条款/TI 产品随附的其他适用条款的约束。TI 提供这些资源并不会扩展或以其他方式更改 TI 针对 TI 产品发布的适用的担保或担保免责声明。

邮寄地址：Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2021，德州仪器 (TI) 公司

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead finish/ Ball material (6)	MSL Peak Temp (3)	Op Temp (°C)	Device Marking (4/5)	Samples
TS3A27518EIPWRQ1	ACTIVE	TSSOP	PW	24	2000	RoHS & Green	NIPDAU	Level-3-260C-168 HR	-40 to 85	YL518EQ1	Samples
TS3A27518EIRTWRQ1	ACTIVE	WQFN	RTW	24	3000	RoHS & Green	NIPDAU	Level-3-260C-168 HR	-40 to 85	27518EI	Samples
TS3A27518ETRTWRQ1	ACTIVE	WQFN	RTW	24	3000	RoHS & Green	NIPDAU	Level-3-260C-168 HR	-40 to 105	27518ET	Samples

(1) The marketing status values are defined as follows:
ACTIVE: Product device recommended for new designs.
LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.
NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.
PREVIEW: Device has been announced but is not in production. Samples may or may not be available.
OBSOLETE: TI has discontinued the production of the device.

(2) **RoHS:** TI defines "RoHS" to mean semiconductor products that are compliant with the current EU RoHS requirements for all 10 RoHS substances, including the requirement that RoHS substance do not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, "RoHS" products are suitable for use in specified lead-free processes. TI may reference these types of products as "Pb-Free".
RoHS Exempt: TI defines "RoHS Exempt" to mean products that contain lead but are compliant with EU RoHS pursuant to a specific EU RoHS exemption.
Green: TI defines "Green" to mean the content of Chlorine (Cl) and Bromine (Br) based flame retardants meet JS709B low halogen requirements of <=1000ppm threshold. Antimony trioxide based flame retardants must also meet the <=1000ppm threshold requirement.

(3) MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

(6) Lead finish/Ball material - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

OTHER QUALIFIED VERSIONS OF TS3A27518E-Q1 :

- Catalog : TS3A27518E

NOTE: Qualified Version Definitions:

- Catalog - TI's standard catalog product

TAPE AND REEL INFORMATION

REEL DIMENSIONS



TAPE DIMENSIONS



A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
TS3A27518EIPWRQ1	TSSOP	PW	24	2000	330.0	16.4	6.95	8.3	1.6	8.0	16.0	Q1
TS3A27518EIRTWRQ1	WQFN	RTW	24	3000	330.0	12.4	4.25	4.25	1.15	8.0	12.0	Q2
TS3A27518ETRTWRQ1	WQFN	RTW	24	3000	330.0	12.4	4.25	4.25	1.15	8.0	12.0	Q2

TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
TS3A27518EIPWRQ1	TSSOP	PW	24	2000	356.0	356.0	35.0
TS3A27518EIRTWRQ1	WQFN	RTW	24	3000	356.0	356.0	35.0
TS3A27518ETRTWRQ1	WQFN	RTW	24	3000	356.0	356.0	35.0

GENERIC PACKAGE VIEW

RTW 24

WQFN - 0.8 mm max height

4 x 4, 0.5 mm pitch

PLASTIC QUAD FLATPACK - NO LEAD

This image is a representation of the package family, actual package may vary.
Refer to the product data sheet for package details.



4224801/A

PACKAGE OUTLINE

RTW0024B

WQFN - 0.8 mm max height

PLASTIC QUAD FLATPACK-NO LEAD



NOTES:

1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.



LAND PATTERN EXAMPLE
SCALE: 20X



SOLDER MASK DETAILS

4219135/B 11/2016

NOTES: (continued)

3. For more information, see Texas Instruments literature number SLUA271 (www.ti.com/lit/slua271).



SOLDER PASTE EXAMPLE
BASED ON 0.125 mm THICK STENCIL

EXPOSED PAD 25:
78% PRINTED COVERAGE BY AREA UNDER PACKAGE
SCALE: 20X

4219135/B 11/2016

NOTES: (continued)

4. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.

PACKAGE OUTLINE

PW0024A

TSSOP - 1.2 mm max height

SMALL OUTLINE PACKAGE



NOTES:

1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.15 mm per side.
4. This dimension does not include interlead flash. Interlead flash shall not exceed 0.25 mm per side.
5. Reference JEDEC registration MO-153.



LAND PATTERN EXAMPLE
EXPOSED METAL SHOWN
SCALE: 10X



SOLDER MASK DETAILS

4220208/A 02/2017

NOTES: (continued)

6. Publication IPC-7351 may have alternate designs.
7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



SOLDER PASTE EXAMPLE
BASED ON 0.125 mm THICK STENCIL
SCALE: 10X

4220208/A 02/2017

NOTES: (continued)

8. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
9. Board assembly site may have different recommendations for stencil design.

重要声明和免责声明

TI“按原样”提供技术和可靠性数据（包括数据表）、设计资源（包括参考设计）、应用或其他设计建议、网络工具、安全信息和其他资源，不保证没有瑕疵且不做出任何明示或暗示的担保，包括但不限于对适销性、某特定用途方面的适用性或不侵犯任何第三方知识产权的暗示担保。

这些资源可供使用 TI 产品进行设计的熟练开发人员使用。您将自行承担以下全部责任：(1) 针对您的应用选择合适的 TI 产品，(2) 设计、验证并测试您的应用，(3) 确保您的应用满足相应标准以及任何其他功能安全、信息安全、监管或其他要求。

这些资源如有变更，恕不另行通知。TI 授权您仅可将这些资源用于研发本资源所述的 TI 产品的应用。严禁对这些资源进行其他复制或展示。您无权使用任何其他 TI 知识产权或任何第三方知识产权。您应全额赔偿因在这些资源的使用中对 TI 及其代表造成的任何索赔、损害、成本、损失和债务，TI 对此概不负责。

TI 提供的产品受 TI 的销售条款或 ti.com 上其他适用条款/TI 产品随附的其他适用条款的约束。TI 提供这些资源并不会扩展或以其他方式更改 TI 针对 TI 产品发布的适用的担保或担保免责声明。

TI 反对并拒绝您可能提出的任何其他或不同的条款。

邮寄地址：Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2022，德州仪器 (TI) 公司