
NPN
MJL3281A*
PNP
MJL1302A*

*Motorola Preferred Device

Designer's™ Data Sheet
Complementary NPN-PNP Silicon Power Bipolar Transistor

- The MJL3281A and MJL1302A are PowerBase power transistors for high power audio, disk head positioners and other linear applications.
- Designed for 100 W Audio Frequency
- Gain Complementary:
  - — Gain Linearity from 100 mA to 7 A
  - — High Gain — 60 to 175
  - — h_{FE} = 45 (Min) @ I_C = 8 A
- Low Harmonic Distortion
- High Safe Operation Area — 1 A/100 V @ 1 sec
- High f_T — 30 MHz Typical

15 AMPERE COMPLEMENTARY SILICON POWER TRANSISTORS 200 VOLTS 200 WATTS



CASE 340G–02, STYLE 2 TO–264

MAXIMUM RATINGS (T_J = 25°C unless otherwise noted)

Rating	Symbol	Value	Unit
Collector–Emitter Voltage	V_{CEO}	200	Vdc
Collector–Base Voltage	V_{CBO}	200	Vdc
Emitter–Base Voltage	V_{EBO}	7	Vdc
Collector–Emitter Voltage — 1.5 V	V_{CEX}	200	Vdc
Collector Current — Continuous — Peak (1)	I_C	15 25	Adc
Base Current — Continuous	I_B	1.5	Adc
Total Power Dissipation @ T_C = 25°C Derate Above 25°C	P_D	200 1.43	Watts W/°C
Operating and Storage Junction Temperature Range	T_J, T_{stg}	–65 to +150	°C

THERMAL CHARACTERISTICS

Characteristic	Symbol	Max	Unit
Thermal Resistance, Junction to Case	$R_{\theta JC}$	0.7	°C/W

(1) Pulse Test: Pulse Width = 5 ms, Duty Cycle <10%.

Designer's Data for "Worst Case" Conditions — The Designer's Data Sheet permits the design of most circuits entirely from the information presented. SOA Limit curves — representing boundaries on device characteristics — are given to facilitate "worst case" design.

Designer's is a trademark of Motorola, Inc.

Preferred devices are Motorola recommended choices for future use and best overall value.

© Motorola, Inc. 1995

ELECTRICAL CHARACTERISTICS (T_C = 25°C unless otherwise noted)

Characteristic	Symbol	Min	Typ	Max	Unit
OFF CHARACTERISTICS					
Collector–Emitter Sustaining Voltage (I_C = 100 mAdc, I_B = 0)	$V_{CEO(sus)}$	200	—	—	Vdc
Emitter–Base Voltage (I_E = 100 μAdc, I_C = 0)	V_{EBO}	7	—	—	Vdc
Collector Cutoff Current (V_{CB} = 200 Vdc, I_E = 0)	I_{CBO}	—	—	50	μAdc
Emitter Cutoff Current (V_{EB} = 5 Vdc, I_C = 0)	I_{EBO}	—	—	5	μAdc
Emitter Cutoff Current (V_{EB} = 7 Vdc, I_C = 0)	I_{EBO}	—	—	25	μAdc
SECOND BREAKDOWN					
Second Breakdown Collector with Base Forward Biased	$I_{S/b}$				Adc
(V_{CE} = 50 Vdc, t = 1 s (non–repetitive)		4	—	—	
(V_{CE} = 100 Vdc, t = 1 s (non–repetitive)		1	—	—	
ON CHARACTERISTICS					
DC Current Gain	h_{FE}				
(I_C = 100 mAdc, V_{CE} = 5 Vdc)		60	125	175	
(I_C = 1 Adc, V_{CE} = 5 Vdc)		60	—	175	
(I_C = 3 Adc, V_{CE} = 5 Vdc)		60	—	175	
(I_C = 5 Adc, V_{CE} = 5 Vdc)		60	—	175	
(I_C = 7 Adc, V_{CE} = 5 Vdc)		60	115	175	
(I_C = 8 Adc, V_{CE} = 5 Vdc)		45	—	—	
(I_C = 15 Adc, V_{CE} = 5 Vdc)		12	35	—	
Collector–Emitter Saturation Voltage (I_C = 10 Adc, I_B = 1 Adc)	$V_{CE(sat)}$	—	—	3	Vdc
DYNAMIC CHARACTERISTICS					
Current–Gain — Bandwidth Product (I_C = 1 Adc, V_{CE} = 5 Vdc, f_{test} = 1 MHz)	f_T	—	30	—	MHz
Output Capacitance (V_{CB} = 10 Vdc, I_E = 0, f_{test} = 1 MHz)	C_{ob}	—	—	600	pF

(1) Pulse Test: Pulse Width = 300 μs, Duty Cycle ≤ 2%.

TYPICAL CHARACTERISTICS

PNP MJL1302A




Figure 1. Current–Gain — Bandwidth Product

NPN MJL3281A




Figure 2. Current–Gain — Bandwidth Product

PNP MJL1302A




Figure 3. DC Current Gain

NPN MJL3281A




Figure 4. DC Current Gain

PNP MJL1302A




Figure 5. DC Current Gain, V_{CE} = 5 V

NPN MJL3281A




Figure 6. DC Current Gain, V_{CE} = 5 V

TYPICAL CHARACTERISTICS

PNP MJL1302A




Figure 7. Typical Base–Emitter Voltage

NPN MJL3281A




Figure 8. Typical Base–Emitter Voltage

PNP MJL1302A




Figure 9. Typical Output Characteristics

NPN MJL3281A




Figure 10. Typical Output Characteristics





Figure 11. Forward Bias Safe Operating Area (FBSOA)

There are two limitations on the power handling ability of a transistor; average junction temperature and secondary breakdown. Safe operating area curves indicate $I_C - V_{CE}$ limits of the transistor that must be observed for reliable operation; i.e., the transistor must not be subjected to greater dissipation than the curves indicate.

The data of Figure 11 is based on $T_{J(pk)}$ = 200°C; T_C is variable depending on conditions. At high case temperatures, thermal limitations will reduce the power than can be handled to values less than the limitations imposed by second breakdown.

PACKAGE DIMENSIONS



NOTES:
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
2. CONTROLLING DIMENSION: MILLIMETER.

	MILLIMETERS		INCHES	
DIM	MIN	MAX	MIN	MAX
A	2.8	2.9	1.102	1.142
B	19.3	20.3	0.760	0.800
C	4.7	5.3	0.185	0.209
D	0.93	1.48	0.037	0.058
E	1.9	2.1	0.075	0.083
F	2.2	2.4	0.087	0.102
G	5.45 BSC		0.215 BSC	
H	2.6	3.0	0.102	0.118
J	0.43	0.78	0.017	0.031
K	17.6	18.8	0.693	0.740
L	11.0	11.4	0.433	0.449
N	3.95	4.75	0.156	0.187
P	2.2	2.6	0.087	0.102
Q	3.1	3.5	0.122	0.137
R	2.15	2.35	0.085	0.093
U	6.1	6.5	0.240	0.256
W	2.8	3.2	0.110	0.125

STYLE 2:
PIN 1. BASE
2. COLLECTOR
3. EMITTER

CASE 340G–02
TO–264
ISSUE E

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. “Typical” parameters can and do vary in different applications. All operating parameters, including “Typicals” must be validated for each customer application by customer’s technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and Ⓜ are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

How to reach us:
USA / EUROPE: Motorola Literature Distribution;
P.O. Box 20912; Phoenix, Arizona 85036. 1–800–441–2447

MFAX: RMFAX0@email.sps.mot.com – TOUCHTONE (602) 244–6609
INTERNET: http://Design–NET.com

JAPAN: Nippon Motorola Ltd.; Tatsumi–SPD–JLDC, Toshikatsu Otsuki,
6F Seibu–Butsuryu–Center, 3–14–2 Tatsumi Koto–Ku, Tokyo 135, Japan. 03–3521–8315

HONG KONG: Motorola Semiconductors H.K. Ltd.; 8B Tai Ping Industrial Park,
51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852–26629298