



JEWEL HILL ELECTRONIC CO.,LTD.

SPECIFICATIONS FOR LCD MODULE

Module No. GG2014

Office Address: Rm. 518,5/F., 101 Shangbu Industrial District,
HuaqiangNorthRoad, Shenzhen, China

TEL : (86)-755-83362489 83617492

FAX: (86)-755-83286396 83365871

E-mail: sales@jewelhillelectronic.com
jhlcd@21cn.com


Website: www.jewelhillelectronic.com



TABLE OF CONTENTS

| | |
|--|-----------|
| LCM NUMBER SYSTEM | 2 |
| 1. GENERAL DESCRIPTION | 3 |
| 2. FEATURES..... | 3 |
| 3. MECHANICAL SPECIFICATION | 3 |
| 4. MECHANICAL DIMENSION | 4 |
| 5. MAXIMUM RATINGS | 5 |
| 6. ELECTRICAL CHARACTERISTICS | 5 |
| 7. MODULE FUNCTION DESCRIPTION | 6 |
| 8. ELECTRO-OPTICAL CHARACTERISTICS | 13 |
| 9. RELIABILITY..... | 16 |
| 10. PRECAUTIONS FOR USING LCD MODULES | 17 |
| 11. USING LCD MODULES..... | 19 |
| 12. REVISION HISTORY | 21 |
| SAMPLE APPROVED REPORT | 22 |

LCM Number System



1. GENERAL DESCRIPTION

The GG2014 is a 128 x 64 Dots+Icon Graphic LCD module. It has a FSTN panel composed of 128 segments and 65 commons. The LCM can be easily accessed by microcontroller via parallel or series interface.


2. FEATURES

| | |
|--------------------|---|
| Display Mode | Transflective and positive |
| | FSTN module |
| Display Format | Graphic 128x64 dots+Icon |
| Input Data | 8 bit parallel data input from MPU(8080 Timing) |
| Multiplexing Ratio | 1/65 Duty |
| Bias | 1/9 Bias |
| Viewing Direction | 6 O'clock |
| Controller LSI | S6B1713 |
| Backlight | None |

3. MECHANICAL SPECIFICATION

| Item | Specifications | Unit |
|---------------------|-------------------------------|------|
| Dimensional outline | 34.6 x (35.7+15.9) x 2.0(max) | mm |
| Resolution | 128segs x 64coms+Icon | dots |
| Active area | 26.885(W) x 21.02(H) | mm |
| Dots pitch | 0.21(W)×0.27(H) | mm |
| Dots size | 0.185(W)×0.245(H) | mm |

4. MECHANICAL DIMENSION



5. MAXIMUM RATINGS

| Item | Symbol | Min | Max | Unit | Note |
|-----------------------|-------------------|------|--------------|------|------|
| Supply voltage | $V_{DD} - V_{SS}$ | -0.3 | 4.0 | V | |
| | V_{LCD} | -0.3 | 18.0 | V | |
| Input Voltage | V_{IN} | -0.3 | $V_{DD}+0.3$ | V | |
| Operating temperature | T_{OPR} | -20 | +70 | °C | |
| Storage temperature | T_{STR} | -30 | +80 | °C | |
| Humidity | --- | --- | 90 | %RH | |

6. ELECTRICAL CHARACTERISTICS

| Item | | Symbol | Condition | Min. | Typ. | Max. | Unit |
|-------------------------------------|---------|-----------|---|-------------|------|-------------|------|
| Supply Voltage | Logic | V_{DD} | --- | --- | 3.0 | --- | V |
| Input Voltage | H level | V_{IH} | --- | $0.8V_{DD}$ | --- | V_{DD} | V |
| | L level | V_{IL} | | V_{SS} | --- | $0.2V_{DD}$ | |
| Current Consumption (LCD DRIVER) | | I_{DD} | $V_{DD}=3.0V$; $V_{LCD}=10.8V, T_{amb}=25^{\circ}C$; | --- | --- | 1.2 | mA |
| LCD Driving Voltage | | V_{LCD} | Bias=1/9 $V_{LCD}=V_0-V_{SS}$ | --- | 10.8 | --- | V |

7. MODULE FUNCTION DESCRIPTION

7.1. PIN DESCRIPTION

| Pin No. | Symbol | Description |
|---------|--------|--|
| 1,2 | NC | No Connect |
| 3 | INTRS | Internal Resistor Selection Terminal |
| 4-8 | V4-V0 | This is multi-level power supply for liquid crystal driver, and must maintain the relative magnitudes shown below: $V0 \geq V1 \geq V2 \geq V3 \geq V4 \geq V_{ss}$ |
| 9 | VR | External Resistor Regulation Terminal |
| 10 | CAP2- | DC/DC Voltage Converter, Connect a Capacitor Together |
| 11 | CAP2+ | |
| 12 | CAP1+ | DC/DC Voltage Converter, Connect a Capacitor Together |
| 13 | CAP1- | |
| 14 | CAP3- | DC/DC Voltage Converter, Connect a Capacitor Together |
| 15 | CAP3+ | |
| 16 | VOUT | DC/DC Voltage Converter Output |
| 17 | VDD | Power Supply for Positive |
| 18 | VSS | Power Supply for Ground |
| 19-26 | D7-D0 | 8-bit bi-directional Data bus. When "P/S=L", D0-D5 fixed to "H". D6 is serial clock input (SCL), D7 is serial data input (SDA). |
| 27 | /RD | Read Signal |
| 28 | /WR | Write Signal |
| 29 | RS | Command/Data Register Selection |
| 30 | /RES | Reset Signal Input Terminal |
| 31 | /CS | Chip Selection Terminal |
| 32,33 | NC | No Connect |

7.2 TIMING CHARACTERISTICS

1.SYSTEM BUS READ/WRITE CHARACTERISTIC

Read / Write Characteristics (8080-series MPU)




Figure 34. Read / Write Characteristics (8080-series MPU)

(VDD = 2.4 to 3.6V, Ta = -40 to +85°C)

| Item | Signal | Symbol | Min. | Typ. | Max. | Unit | Remark |
|---------------------|------------|----------|------|------|------|------|-------------|
| Address setup time | RS | tAS80 | 13 | - | - | ns | |
| Address hold time | RS | tAH80 | 17 | - | - | ns | |
| System cycle time | RS | tCY80 | 400 | - | - | ns | |
| Pulse width (WR) | RW_WR | tPW80(W) | 55 | - | - | ns | |
| Pulse width (RD) | E_RD | tPW80(R) | 125 | - | - | ns | |
| Data setup time | DB7 to DB0 | tDS80 | 35 | - | - | ns | |
| Data hold time | | tDH80 | 13 | - | - | ns | |
| Read access time | | tACC80 | - | - | 125 | ns | CL = 100 pF |
| Output disable time | | tOD80 | 10 | - | 90 | ns | |

2. RESET TIMING




Figure 37. Reset Input Timing

(VDD = 2.4 to 3.6V, Ta = -40 to +85°C)

| Item | Signal | Symbol | Min. | Typ. | Max. | Unit | Remark |
|-----------------------|--------|--------|------|------|------|------|--------|
| Reset low pulse width | RESETB | trw | 900 | - | - | ns | |

3. DISPLAY CONTROL TIMING




Figure 38. Display Control Output Timing

(VDD = 2.4 to 3.6V, Ta = -40 to +85°C)

| Item | Signal | Symbol | Min. | Typ. | Max. | Unit | Remark |
|--------------|--------|--------|------|------|------|------|--------|
| M delay time | M | tDM | - | 13 | 70 | ns | |

7.3 APPLICATION OF LCM

In Case of Interfacing with 8080-series (PS = "H", MI = "L")




Figure 40. Interfacing with 8080-series (PS = "H", MI = "L")

Reference circuit




Figure 18. When Using all LCD Power Circuits (4-Time V/C: ON, V/R: ON, V/F: ON)




Figure 19. When Using some LCD Power Circuits (V/C: OFF, V/R: ON, V/F: ON)

Voltage Converter Circuits

These circuits boost up the electric potential between VDD and VSS to 2, 3, 4 or 5 times toward positive side and boosted voltage is outputted from VOUT pin.

[C1 = 1.0 to 4.7 μ F]




Figure 12. Two Times Boosting Circuit

Figure 13. Three Times Boosting Circuit




Figure 14. Four Times Boosting Circuit

Figure 15. Five Times Boosting Circuit



7.4 TABLE OF COMMAND

× : Don't care

| Instruction | RS | RW | DB7 | DB6 | DB5 | DB4 | DB3 | DB2 | DB1 | DB0 | Description |
|--------------------------------|----|----|------------|-----|-------|--------|-----|-----|-----|------|--|
| Read display data | 1 | 1 | Read data | | | | | | | | Read data from DDRAM |
| Write display data | 1 | 0 | Write data | | | | | | | | Write data into DDRAM |
| Read status | 0 | 1 | BUSY | ADC | ONOFF | RESETB | 0 | 0 | 0 | 0 | Read the internal status |
| Display ON / OFF | 0 | 0 | 1 | 0 | 1 | 0 | 1 | 1 | 1 | DON | Turn on/off LCD panel When DON = 0: display OFF When DON = 1: display ON |
| Initial display line | 0 | 0 | 0 | 1 | ST5 | ST4 | ST3 | ST2 | ST1 | ST0 | Specify DDRAM line for COM1 |
| Set reference voltage mode | 0 | 0 | 1 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | Set reference voltage Mode |
| Set reference voltage register | 0 | 0 | × | × | SV5 | SV4 | SV3 | SV2 | SV1 | SV0 | Set reference voltage register |
| Set page address | 0 | 0 | 1 | 0 | 1 | 1 | P3 | P2 | P1 | P0 | Set page address |
| Set column address MSB | 0 | 0 | 0 | 0 | 0 | 1 | Y7 | Y6 | Y5 | Y4 | Set column address MSB |
| Set column address LSB | 0 | 0 | 0 | 0 | 0 | 0 | Y3 | Y2 | Y1 | Y0 | Set column address LSB |
| ADC select | 0 | 0 | 1 | 0 | 1 | 0 | 0 | 0 | 0 | ADC | Select SEG output direction When ADC = 0: normal direction (SEG1→SEG132) When ADC = 1: reverse direction (SEG132→SEG1) |
| Reverse display ON / OFF | 0 | 0 | 1 | 0 | 1 | 0 | 0 | 1 | 1 | REV | Select normal / reverse display When REV = 0: normal display When REV = 1: reverse display |
| Entire display ON / OFF | 0 | 0 | 1 | 0 | 1 | 0 | 0 | 1 | 0 | EON | Select normal / entire display ON When EON = 0: normal display. When EON = 1: entire display ON |
| LCD bias select | 0 | 0 | 1 | 0 | 1 | 0 | 0 | 0 | 1 | BIAS | Select LCD bias |
| Set modify-read | 0 | 0 | 1 | 1 | 1 | 0 | 0 | 0 | 0 | 0 | Set modify-read mode |
| Reset modify-read | 0 | 0 | 1 | 1 | 1 | 0 | 1 | 1 | 1 | 0 | Release modify-read mode |
| Reset | 0 | 0 | 1 | 1 | 1 | 0 | 0 | 0 | 1 | 0 | Initialize the internal functions |
| SHL select | 0 | 0 | 1 | 1 | 0 | 0 | SHL | × | × | × | Select COM output direction When SHL = 0: normal direction (COM1→COM64) When SHL = 1: reverse direction (COM64→COM1) |
| Power control | 0 | 0 | 0 | 0 | 1 | 0 | 1 | VC | VR | VF | Control power circuit operation |
| Regulator resistor select | 0 | 0 | 0 | 0 | 1 | 0 | 0 | R2 | R1 | R0 | Select internal resistance ratio of the regulator resistor |
| Set static indicator mode | 0 | 0 | 1 | 0 | 1 | 0 | 1 | 1 | 0 | SM | Set static indicator mode |
| Set static indicator register | 0 | 0 | × | × | × | × | × | × | S1 | S0 | Set static indicator register |
| Power save | - | - | - | - | - | - | - | - | - | - | Compound instruction of display OFF and entire display ON |
| Test instruction | 0 | 0 | 1 | 1 | 1 | 1 | × | × | × | × | <u>Don't use this instruction.</u> |

8. ELECTRO-OPTICAL CHARACTERISTICS


| Item | Symbol | Condition | Temp | Min | Typ. | Max | Units | Note |
|---------------------|-----------------|---------------------|------|------|------|------|-------|-------|
| LCD driving voltage | V_{LCD} | $\theta = \phi = 0$ | 0°C | 10.7 | 11.0 | 11.3 | V | NOTE1 |
| | | | 25°C | 10.5 | 10.8 | 11.1 | | |
| | | | 50°C | 10.3 | 10.6 | 10.9 | | |
| Response Time | Rise Time (Tr) | $\theta = \phi = 0$ | 0°C | --- | --- | -- | msec | NOTE2 |
| | Decay Time (Tf) | | | --- | ---- | --- | | |
| | Rise Time (Tr) | | 25°C | --- | 225 | 340 | | |
| | Decay Time (Tf) | | | --- | 240 | 360 | | |
| | Rise Time (Tr) | | 50°C | --- | --- | -- | | |
| | Decay Time (Tf) | | | --- | --- | -- | | |
| Contrast Ratio | Cr | $\theta = \phi = 0$ | 25°C | 5 | 10 | --- | --- | NOTE4 |

| Viewing Angle Range | $\theta (\phi = 0^\circ)$ (6'') | $\phi = 90^\circ$ (3'') | $\phi = 180^\circ$ (12'') | $\phi = 270^\circ$ (9'') | 備註 |
|--|------------------------------------|----------------------------|------------------------------|-----------------------------|--------------|
| $\theta (25^\circ\text{C})$ CR \geq 2 | 45 | 35 | 15 | 30 | Deg NOTE3 |


● For panel only




• **Electro-Optical Characteristics Measuring Equipment(DMS501)**




• **Note 1. Definition of Driving Voltage(V_{lcd}) :**



• **Note 2. Definition of Optical Response Time :**




• **Note 3. Definition of Viewing Angle θ and ϕ :**



• **Note 4. Definition of Contrast ratio(CR) :**

$$CR = \frac{\text{Brightness of Non-selected Segment (B2)}}{\text{Brightness of Selected Segment (B1)}}$$



9. RELIABILITY

9.1. MTBF

The LCD module shall be designed to meet a minimum MTBF value of 50000 hours with normal. (25°C in the room without sunlight)

9.2. TESTS

| NO. | ITEM | CONDITION | CRITERION |
|-----|---|--|---|
| 1 | High Temperature Operating | 50°C 120Hrs | <ul style="list-style-type: none"> ◦ No Defect Of Operational Function In Room Temperature Are Allowable. ◦ IDD of LCM in Pre-and post-test should follow specification |
| 2 | Low Temperature Operating | -5°C 120Hrs | |
| 3 | High Temperature/ Humidity Non-Operating | 50°C ,90%RH ,120 Hrs | |
| 4 | High Temperature Non-Operating | 70°C 120Hrs | |
| 5 | Low Temperature Non-Operating | -20°C 120Hrs | |
| 6 | Temperature Cycling Non-Operating | -5°C (30Min)↔ 50°C (30Min) 10 CYCLES | |

Notes: Judgments should be made after exposure in room temperature for two hours.



10. PRECAUTIONS FOR USING LCD MODULES

10.1. HANDLING PRECAUTIONS

- (1) The display panel is made of glass. Do not subject it to a mechanical shock or impact by dropping it.
- (2) If the display panel is damaged and the liquid crystal substance leaks out, be sure not to get any in your mouth. If the substance contacts your skin or clothes, wash it off using soap and water.
- (3) Do not apply excessive force to the display surface or the adjoining areas since this may cause the color tone to vary.
- (4) The polarizer covering the display surface of the LCD module is soft and easily scratched. Handle this polarizer carefully.
- (5) If the display surface becomes contaminated, breathe on the surface and gently wipe it with a soft dry cloth. If it is heavily contaminated, moisten a cloth with one of the following solvents:
 - Isopropyl alcohol
 - Ethyl alcohol
- (6) Solvents other than those above mentioned may damage the polarizer.
Especially, do not use the following:
 - Water
 - Ketone
 - Aromatic solvents
- (7) Extra care to minimize corrosion of the electrode. Water droplets, moisture condensation or a current flow in a high-humidity environment accelerates corrosion of the electrode.
- (8) Install the LCD Module by using the mounting holes. When mounting the LCD Module, make sure it is free of twisting, warping and distortion. In particular, do not forcibly pull or bend the I/O cable or the backlight cable.
- (9) Do not attempt to disassemble or process the LCD Module.
- (10) NC terminal should be open. Do not connect anything.
- (11) If the logic circuit power is off, do not apply the input signals.
- (12) To prevent destruction of the elements by static electricity, be careful to maintain an optimum work environment.
 - Be sure to ground the body when handling the LCD Module.
 - Tools required for assembling, such as soldering irons, must be properly grounded.
 - To reduce the amount of static electricity generated, do not conduct assembling and other work under dry conditions.

-The LCD Module is coated with a film to protect the display surface. Exercise care when peeling off this protective film since static electricity may be generated.

10.2. STORAGE CONDITIONS

When storing, avoid the LCD module to be exposed to direct sunlight of fluorescent lamps. For stability, to keep it away from high temperature and high humidity environment (The best condition is : $23\pm5^{\circ}\text{C}$, $45\pm20\%\text{RH}$). ESD protection is necessary for long-term storage also.

10.3. OTHERS

Liquid crystals solidify under low temperature (below the storage temperature range) leading to defective orientation or the generation of air bubbles (black or white). Air bubbles may also be generated if the module is subject to a low temperature.

If the LCD Module have been operating for a long time showing the same display patterns the display patterns may remain on the screen as ghost images and a slight contrast irregularity may also appear. A normal operating status can be recovered by suspending use for some time. It should be noted that this phenomenon does not adversely affect performance reliability.

To minimize the performance degradation of the LCD Module resulting from destruction caused by static electricity etc. exercise care to avoid holding the following sections when handling the modules.

- Exposed area of the printed circuit board.
- Terminal electrode sections.

11. Using LCD modules

11.1 LIQUID CRYSTAL DISPLAY MODULES

LCD is composed of glass and polarizer. Pay attention to the following items when handling.

- (1) Please keep the temperature within specified range for use and storage. Polarization degradation, bubble generation or polarizer peel-off may occur with high temperature and high humidity.
- (2) Do not touch, push or rub the exposed polarizers with anything harder than a HB pencil lead (glass, tweezers, etc).
- (3) N-hexane is recommended for cleaning the adhesives used to attach front/rear polarizers and reflectors made of organic substances, which will be damaged by chemicals such as acetone, toluene, ethanol and isopropyl alcohol.
- (4) When the display surface becomes dusty, wipe gently with absorbent cotton or other soft material like chamois soaked in petroleum ether. Do not scrub hard to avoid damaging the display surface.
- (5) Wipe off saliva or water drops immediately, contact with water over a long period of time may cause deformation or color fading.
- (6) Avoid contacting oil and fats.
- (7) Condensation on the surface and contact with terminals due to cold will damage, stain or polarizers. After products are tested at low temperature they must be warmed up in a container before coming in contact with room temperature air.
- (8) Do not put or attach anything on the display area to avoid leaving marks on.
- (9) Do not touch the display with bare hands. This will stain the display area and degrade insulation between terminals (some cosmetics are determinate to the polarizers).
- (10) As glass is fragile, it tends to become chipped during handling especially on the edges. Please avoid dropping or jarring.

11.2 INSTALLING LCD MODULE

Attend to the following items when installing the LCM.

- (1) Cover the surface with a transparent protective plate to protect the polarizer and LC cell.
- (2) When assembling the LCM into other equipment, the spacer to the bit between the LCM and the fitting plate should have enough height to avoid causing stress to the module surface, refer to the individual specifications for measurements. The measurement tolerance should be $\pm 0.1\text{mm}$.

11.3 ELECTRO-STATIC DISCHARGE CONTROL

Since this module uses a CMOS LSI, the same careful attention should be paid for electrostatic discharge as for an ordinary CMOS IC.

- (1) Make certain that you are grounded when handing LCM.
- (2) Before removing LCM from its packing case or incorporating it into a set, be sure the module and your body have the same electric potential.
- (3) When soldering the terminal of LCM, make certain the AC power source for the soldering iron does not leak.
- (4) When using an electric screwdriver to attach LCM, the screwdriver should be of ground potentiality to minimize as much as possible any transmission of electromagnetic waves produced sparks coming from the commutator of the motor.
- (5) As far as possible, make the electric potential of your work clothes and that of the workbenches to the ground potential.
- (6) To reduce the generation of electro-static discharge, be careful that the air in the work is not too dried. A relative humidity of 50%-60% is recommended.

11.4 PRECAUTIONS FOR OPERATION

- (1) Viewing angle varies with the change of liquid crystal driving voltage (V_o). Adjust V_o to show the best contrast.
- (2) Driving the LCD in the voltage above the limit will shorten its lifetime.
- (3) Response time is greatly delayed at temperature below the operating temperature range. However, this does not mean the LCD will be out of the order. It will recover when it returns to the specified temperature range.
- (4) If the display area is pushed hard during operation, the display will become abnormal. However, it will return to normal if it is turned off and then on.
- (5) Condensation on terminals can cause an electrochemical reaction disrupting the terminal circuit. Therefore, this product must be used and stored within the specified condition of $23\pm5^{\circ}\text{C}$, $45\pm20\%\text{RH}$.
- (6) When turning the power on, input each signal after the positive/negative voltage becomes stable.

11.5 SAFETY

- (1) It is recommended to crush damaged or unnecessary LCDs into pieces and wash them off with solvents such as acetone and ethanol, which should later be burned.
- (2) If any liquid leaks out of a damaged glass cell and comes in contact with the hands, wash off thoroughly with soap and water.

12. REVISION HISTORY

| Version | Revise record | Date |
|---------|-----------------------------|----------|
| 1.0 | Original version | 05-01-01 |
| 2.0 | Change specification format | 05-11-21 |
| | | |
| | | |
| | | |
| | | |
| | | |
| | | |
| | | |
| | | |
| | | |
| | | |
| | | |
| | | |
| | | |
| | | |

SAMPLE APPROVED REPORT

(样品确认单)

| | |
|--|-------------------|
| SAMPLE MODEL NO. (样品型号) | GG2014 |
| SAMPLE SERIES NUMBER NO. (样品序号) | |
| SAMPLE QUANTITY (样品数量) | |
| COLOR/TYPE (底色/类型) | FSTN/POSITIVE |
| VIEWING DIRECTION (视角) | 6:00 |
| DRIVING METHOD (驱动参数) | 1/65Duty, 1/9Bias |
| LOGIC VOLTAGE (IC 工作电压) | 3.0V |
| LCD VOP (LCD 驱动电压) | 10.8V |
| OPERATING TEMP. (操作温度) | -5~50 |
| STORAGE TEMP. (储存温度) | -20~70 |
| POLARIZER----FRONT (首偏光片) | TRANSMISSIVE |
| POLARIZER----BACK (后偏光片) | TRANSFLECTIVE |
| CONTROLLER/DRIVER IC(控制/驱动 IC) | S6B1713 |
| BACKLIGHT COLOR/TYPE (背光源类型/颜色) | NONE |
| DRAWING REV/NO./QUANTITY (图纸版本/数量) | |
| SPECIFICATION (规格书 份数) | |
| REMARKS : (备注) | |
| WRIT BY : _____ DATE : _____ APROV BY : _____ DATE : _____ | |
| CUSTOMER'S APPROVAL (客户确认) : | |
| 1) FUNCTION (功能) : <input type="checkbox"/> OK <input type="checkbox"/> N.G. | |
| 2) DRIVER CONDITION (驱动条件) : <input type="checkbox"/> OK <input type="checkbox"/> N.G. | |
| 3) DISPLAY MODE (显示模式) : <input type="checkbox"/> OK <input type="checkbox"/> N.G. | |
| 4) VIEWING ANGLE (视角) : <input type="checkbox"/> OK <input type="checkbox"/> N.G. | |
| 5) BACKLIGHT (背光源) : <input type="checkbox"/> OK <input type="checkbox"/> N.G. | |
| 6) DISPLAYING PATTERN (显示效果) : <input type="checkbox"/> OK <input type="checkbox"/> N.G. | |
| CUSTOMER'S CONCLUSIONS (客户意见) : _____ | |
| _____ | |
| _____ | |
| CUSTOMER'S SIGNATURE (客户签名) : _____ DATE (日期) : _____ | |