

**SPECIFICATION SHEET**

**JFW MODEL 50T-142**

**TERMINATION**

JFW Industries, Inc.  
Phone: 317-887-1340  
sales@jfwindustries.com  
www.jfwindustries.com

Description Termination with Optional Bead Chain

Frequency Range DC-8000 MHz

Impedance 50 Ohms nominal

VSWR 1.1:1 maximum DC-1000 MHz  
1.2:1 maximum 1000-4000 MHz  
1.35:1 maximum 4000-8000 MHz

RF Input Power 2 Watts average

RF Connector N male

Available Model Numbers 50T-142 N M (with bead chain)  
50T-142 N M NB (without bead chain)

Physical Size See outline drawings:  
092-1832 (with bead chain)  
092-4208 (without bead chain)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
1079	05/19/1998	A		23840	03/10/2014	D	TRS 03/10/2014
2894	02/18/2002	B		27936	07/11/2017	E	CLK 07/11/2017
9999	02/14/2003	C	SL 04/30/2003				