



### Main

Product or component type	Energy meter kit
---------------------------	------------------

### Complementary

Poles description	3P + N 1P + N 3P
Type of measurement	Active and reactive energy Active and reactive power Current Voltage
Metering type	Active, reactive, apparent energy (signed, four quadrant)
Device application	Sub billing Multi-tariff Partial meter
Rated voltage	100...277 V +/- 20 % 173...480 V +/- 20 %
Network frequency	60 Hz 50 Hz
Technology type	Electronic
Display type	LCD display
Current transformer type	Split core balance
Line Rated Current	200 A
Measurement accuracy	1 % 10...100 %
Enclosure mounting	Wall mounted
Communication port protocol	Modbus RTU 9.6, 19.2 and 38.4 kbauds even/odd or none
Communication port support	Screw terminal block RS485
Local signalling	Green indicator light power ON Yellow flashing LED accuracy checking alarm overload Yellow indicator light communications are active on the Modbus port (Modbus)
Mounting mode	Clip-on
Mounting support	DIN rail
Connections - terminals	Current circuit screw terminals 0.01 in <sup>2</sup> (6 mm <sup>2</sup> ) Voltage circuit screw terminals 0.00 in <sup>2</sup> (2.5 mm <sup>2</sup> ) Input/output circuit screw terminals 0.00 in <sup>2</sup> (1.5 mm <sup>2</sup> ) Communication screw terminals 0.00 in <sup>2</sup> (2.5 mm <sup>2</sup> )

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Tightening torque	Input/output circuit 4.43 lbf.in (0.5 N.m) Philips Voltage circuit 4.43 lbf.in (0.5 N.m) Philips Current circuit 7.08 lbf.in (0.8 N.m) pozidriv Communication 4.43 lbf.in (0.5 N.m) Philips
Provided equipment	1 energy meter 3 x 200 A current transformer 1 enclosure
Product certifications	ANSI UL CSA

## Environment

NEMA degree of protection	NEMA 4X
Ambient air temperature for operation	-13...158 °F (-25...70 °C)