



## FCC-6512-5

### TECHNICAL DATA



## Optical Fiber Checker

### Introduction

This high-quality optical fiber checker incorporates the latest technology in red laser optics and microelectronics. Use this tool to check any connector with  $\varnothing$  2.5 mm ferrule.

### Features

- Portable pen style design
- A Main Power Switch at the rear is a safety function to prevent for impropriety use.
- Function Button supplies both "CW (Continuous)" or "Pulse" mode for extra clear noticeable results.
- option: adaptor for 1.25 mm (FC-M2F1-U1)

### Specifications

Laser Class	Class IIIa
Wavelength	650 nm
Output Power	> -4 dBm @ 25 °C into 9 $\mu$ m Fiber
Spectral Width	< 20 nm
Operation Mode	continuous or 3 Hz pulsed signal
Range	Visibility to 3 km
Power source	2x AAA batteries
Operating Temperatur	0 ... +50 °C
Storage Temperatur	0 ... +70 °C
Connector Style	universal (accept any connector with $\varnothing$ 2.5mm ferrule)
Dimension	$\varnothing$ 13.5 x 146 mm
Weight	79 g (incl. batteries)
Colour	black





**ROITHNER LASERTECHNIK GmbH**

WIEDNER HAUPTSTRASSE 76

1040 VIENNA

AUSTRIA

TEL. +43 1 586 52 43 -0, FAX. -44, OFFICE@ROITHNER-LASER.COM



### ***Operation***

- Make sure the fiber connection is in place.
- Press Main Power Switch which is at the rear of the checker; it will make the power “On”. Then press Function Button, which is at the middle of checker into the mode “CW” or “Pulse” for your preference.
- Press Function Button or Main Power Switch to “Off” position, and the laser light will shut off.



### **User Safety Precautions**

Direct eye contact with laser beam may cause eye injury and should be avoided at all cost. Caution – use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous radiation exposure.