SPECIFICATION SHEET

JFW MODEL 50BA-012-95

BENCHTOP PROGRAMMABLE ATTENUATOR ASSEMBLY

JFW Industries, Inc. Phone: 317-887-1340 sales@jfwindustries.com www.jfwindustries.com

Frequency Range 30-3000 MHz

Configuration Four individually controlled solid-state

programmable attenuators

Enclosure Type Mini-benchtop

50 Ohms nominal Impedance

0-95 dB in 1 dB steps Attenuation Range

Startup/Default States

Maximum attenuation (see ATTEN STARTUP command)

DHCP enabled (see NET command) (configurable)

4 Ethernet users (see NET USERS command)

Prompts off (see PROMPT command) Jog speed 5 (see JOG SPEED command)

2.0:1 maximum **VSWR** 30-700 MHz

1.6:1 maximum 700-3000 MHz

 \pm 0.50 dB 1-7 dB Attenuation Accuracy ± 1.00 dB (guaranteed monotonic) 8-11 dB

± 1.25 dB or 3% 12-95 dB (whichever is greater)

5.5 dB maximum Insertion Loss

5.0 dB typical

RF Input Power +27 dBm average

+33 dBm (no damage)

Switching Speed 4 microseconds typical

> (after command is received and processed) (3 milliseconds typical processing time)

DC Supply +12 Vdc

(100-240 VAC AC/DC transformer included)

Manual Control Four Momentary Lever Actuator Switches with

> 7-Segment LED Displays (tap to step, hold to jog) (jog speed range is 0-10)

(jog speed set to 0 will disable all levers)

Remote Control Ethernet (DHCP, TCP/IP, 10/100, up to 12 users)

RS-232 (up to 115200 Baud)

--CONTINUED--

Page 1 of 2 JFW FORM E-7-F REV F

SPECIFICATION SHEET

JFW MODEL 50BA-012-95

BENCHTOP PROGRAMMABLE ATTENUATOR ASSEMBLY

JFW Industries, Inc. Phone: 317-887-1340 sales@jfwindustries.com www.jfwindustries.com

Remote Commands

Attenuator Control Commands:

Atten, Set Attenuator, Read Attenuator, Set All Attenuators, Read All Attenuators, Read All Extended, Fade Attenuator, Variable Attenuator Handover, Block, Set Block, Read Block, Read All Blocks, Fade Block, Variable Block Handover

System Commands:

Help, Identification, Store, Recall, Pause, Net, Serial, Close, Disconnect, MOTD, Date, Message, Restrict, IDENT, Name, Show Users,

Reboot, Uptime, Prompt, Jog Speed

RF Connector

SMA female

Operating Temperature Range

 $0^{\circ}C$ to $+50^{\circ}C$

Physical Size

See outline drawing 092-8150

ECR/ECN	# DATE	REV	APPR / DATE	ECR/ECN	# DATE	REV	APPR / DATE
	03/04/2013		CLK 03/04/2013	28159	10/05/2017	С	CLK 10/05/2017
23463	11/19/2013	A	CLK 11/19/2013				
24239	11/14/2014	В	TRS 11/14/2014				

Page 2 of 2 JFW FORM E-7-F REV F