

## Data sheet | Item number: 706-4756/500-300

System cable; for Rockwell Control Logix; 4 analog outputs (current); Length: 3 m; Conductor cross-section: 0.25 mm<sup>2</sup>



[www.wago.com/706-4756/500-300](http://www.wago.com/706-4756/500-300)



### Data Notes

Note	When using more than 10 wires, the maximum current per wire must be reduced to 1 A.
------	---

### Electrical data

Inputs/outputs	4 analog outputs; current
Operating voltage	≤ AC/DC 35 V
Current per wire (max.)	2 A

### Connection data

Compatible PLC Modules	Rockwell Control Logix
Compatible PLC I/O Card Types	1756 - OF4
Connection type (1)	System
Pole number 1	15
Pluggable connectors	D-sub female connector
Connection type 2	System
Pole number 2	20
Connector 2	Allen Bradley 1756-TBSH
Cable type	LiYCY
Wire cross-section	0.25 mm <sup>2</sup>
Color code	per DIN VDE 47100

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG  
Hansastr. 27  
32423 Minden  
Phone: +49571 887-0 | Fax: +49571 887-169  
Email: [info.de@wago.com](mailto:info.de@wago.com) | Web: [www.wago.com](http://www.wago.com)

Do you have any questions about our products?  
We are always happy to take your call at +49 (571) 887-44222.



## Physical data

Cable length	3 m
--------------	-----

---

## Material data

Weight	1.1 g
--------	-------

---

## Environmental requirements

Surrounding air temperature (operation)	-20 ... 50 °C
---	---------------

---

## Commercial data

PU (SPU)	1 Stück
Packaging type	box
GTIN	4055143046657

---

## Downloads

### Documentation

#### System Description

WAGO System Wiring, Selection Guide This guide will help you select the appropriate interface modules and system cables for the controller you are using.	pdf 545.9 kB	Download
--	-----------------	----------

---

## Environmental Product Compliance

### Compliance Search

Environmental Product Compliance 706-4756/500-300 System cable; for Rockwell Control Logix; 4 analog outputs (current); Length: 3 m; Conductor cross-section: 0.25 mm <sup>2</sup>	URL	Download
--	-----	----------

---

## Installation Notes

Subject to changes. Please also observe the further product documentation!