Ordering number : ENA1250A

SANYO Semiconductors
DATA SHEET

An ON Semiconductor Company

Bi-CMOS LSI

LV8411GR — For DSC, and Cell Phone Camera Modules 4-channel Single-chip Motor Driver IC

Overview

The LV8411GR is an H bridge motor driver IC and is able to control 4 modes of forward, reverse, brake, and standby. This IC housed in a miniature package is optimum for use in a stepping motor driving system for DSC or a camera module of cell phones.

Features

- Saturation drive H bridge: 4 channels
- Built-in thermal protection circuit
- Built-in low voltage malfunction prevention circuit
- Incorporates a transistor for driving photosensors

Specifications

Absolute Maximum Ratings at Ta = 25°C

Parameter	Symbol	Conditions	Ratings	Unit
Power supply voltage 1	V_M max		6.0	V
Power supply voltage 2	V_{CC} max		6.0	V
Output peak current	I_O peak	Channels 1 to 4, t ≤ 10msec, ON-duty ≤ 20%	600	mA
Output continuous current 1	I_O max1	Channels 1 to 4	400	mA
Output continuous current 2	I_O max2	PI1	30	mA
Allowable power dissipation	Pd max	Mounted on a circuit board*	1.05	W
Operating temperature	Topr		-40 to +85	°C
Storage temperature	Tstg		-55 to +150	°C

* Specified circuit board : 40mm×50mm×0.8mm : glass epoxy four-layer board

Caution 1) Absolute maximum ratings represent the value which cannot be exceeded for any length of time.

Caution 2) Even when the device is used within the range of absolute maximum ratings, as a result of continuous usage under high temperature, high current, high voltage, or drastic temperature change, the reliability of the IC may be degraded. Please contact us for the further details.

■ Any and all SANYO Semiconductor Co.,Ltd. products described or contained herein are, with regard to "standard application", intended for the use as general electronics equipment. The products mentioned herein shall not be intended for use for any "special application" (medical equipment whose purpose is to sustain life, aerospace instrument, nuclear control device, burning appliances, transportation machine, traffic signal system, safety equipment etc.) that shall require extremely high level of reliability and can directly threaten human lives in case of failure or malfunction of the product or may cause harm to human bodies, nor shall they grant any guarantee thereof. If you should intend to use our products for new introduction or other application different from current conditions on the usage of automotive device, communication device, office equipment, industrial equipment etc. , please consult with us about usage condition (temperature, operation time etc.) prior to the intended use. If there is no consultation or inquiry before the intended use, our customer shall be solely responsible for the use.

■ Specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.

Recommended Operating Conditions at Ta = 25°C

Parameter	Symbol	Conditions	Ratings	Unit
Power supply voltage range 1	V_M		2.5 to 5.5	V
Power supply voltage range 2	V_{CC}		2.5 to 5.5	V
Logic input voltage range	V_{IN}		0 to V_{CC}+0.3	V
Input frequency	f_{IN}	IN1 to 8, INA	to 100	kHz


Electrical Characteristics at Ta = 25°C, V_M = 5V, V_{CC} = 3.3V, unless otherwise specified.


Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Standby mode current drain	Istn	IN1 to 8 = "L"			1.0	μA
VM current drain	IM	IN1 = "H", IM1 + IM2, with no load	50	100	200	μA
V_{CC} current drain	I_{CC}	IN1 = "H"	0.3	0.6	1.2	mA
V_{CC} low-voltage cutoff voltage	VthV_{CC}		2.0	2.25	2.5	V
Low-voltage hysteresis voltage	VthHIS		100	150	200	mV
Thermal shutdown temperature	TSD	Design guarantee value *	160	180	200	°C
Thermal hysteresis width	ΔTSD	Design guarantee value *	10	30	50	°C
OUT1 to 8						
Logic pin internal pull-down resistance	Rin	IN1 to 8	50	100	200	kΩ
Logic pin input current	IinL	V_{IN} = 0V, IN1 to 8			1.0	μA
	IinH	V_{IN} = 3.3V, IN1 to 8	16.5	33	60	μA
Logic input high-level voltage	Vinh	IN1 to 8	2.5			V
Logic input low-level voltage	Vinl	IN1 to 8			1.0	V
Output on-resistance	Ronu	I_O = 400mA, upper ON resistance		0.75	0.9	Ω
	Rond	I_O = 400mA, lower ON resistance		0.45	0.6	Ω
Output leakage current	$I_O$leak				1.0	μA
Diode forward voltage	VD	ID = -400mA	0.7	0.9	1.2	V
PI1						
Logic pin internal pull-down resistance	Rin	INA	50	100	200	kΩ
Logic pin input current	IinL	V_{IN} = 0V, INA			1.0	μA
	IinH	V_{IN} = 3.3V, INA	16.5	33	60	μA
Logic input high-level voltage	Vinh	INA	2.5			V
Logic input low-level voltage	Vinl	INA			1.0	V
Output on-resistance	Ron	I_O = 10mA		3.0	6.0	Ω
Output leakage current	$I_O$leak				1.0	μA

Package Dimensions


unit : mm (typ)

3366









Pin Assignment



Block Diagram



Pin Functions


Pin No.	Pin name	Pin Function	Equivalent Circuit
1	INA	Control signal input pin (Photo sensor driving transistor)	
2	IN1	Control signal input pin	
3	IN2	Control signal input pin	
4	IN3	Control signal input pin	
5	IN4	Control signal input pin	
6	IN5	Control signal input pin	
7	IN6	Control signal input pin	
8	IN7	Control signal input pin	
9	IN8	Control signal input pin	
11	OUT8	Outpin	
13	OUT7	Outpin	
14	OUT6	Outpin	
15	OUT5	Outpin	
16	OUT4	Outpin	
17	OUT3	Outpin	
18	OUT2	Outpin	
20	OUT1	Outpin	
24	PI1	Photo sensor driving transistor output pin	
22	V_{CC}	Logic system power supply connection pin	
10	VM2	Motor power supply connection pin	
21	VM1	Motor power supply connection pin	
23	SGND	Signal ground	
12	PGND2	Power ground	
19	PGND1	Power ground	

Logic input specifications

• Common channels 1 to 4
ch1 : IN1 to IN2, OUT1 to OUT2
ch2 : IN3 to IN4, OUT3 to OUT4
ch3 : IN5 to IN6, OUT5 to OUT6
ch4 : IN7 to IN8, OUT7 to OUT8

Input		Output		Operation mode
IN1	IN2	OUT1	OUT2	
L	L	OFF	OFF	Standby
H	L	H	L	CW (forward)
L	H	L	H	CCW (reverse)
H	H	L	L	Brake

• Current limit control timing chart



(Forward) (Reverse) (Brake)

• Photo sensor driving transistor
When thermal shutdown and V_{CC} low-voltage cut circuits are activated, OUT1 through OUT8 are turned OFF under control of the internal circuit. But the output (PI1) of photo sensor driving transistor continues operation.

Input	Photo sensor driving
INA	PI1
L	OFF
H	ON

- SANYO Semiconductor Co.,Ltd. assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein.
- Regarding monolithic semiconductors, if you should intend to use this IC continuously under high temperature, high current, high voltage, or drastic temperature change, even if it is used within the range of absolute maximum ratings or operating conditions, there is a possibility of decrease reliability. Please contact us for a confirmation.
- SANYO Semiconductor Co.,Ltd. strives to supply high-quality high-reliability products, however, any and all semiconductor products fail or malfunction with some probability. It is possible that these probabilistic failures or malfunction could give rise to accidents or events that could endanger human lives, trouble that could give rise to smoke or fire, or accidents that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO Semiconductor Co.,Ltd. products described or contained herein are controlled under any of applicable local export control laws and regulations, such products may require the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written consent of SANYO Semiconductor Co.,Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO Semiconductor Co.,Ltd. product that you intend to use.
- Upon using the technical information or products described herein, neither warranty nor license shall be granted with regard to intellectual property rights or any other rights of SANYO Semiconductor Co.,Ltd. or any third party. SANYO Semiconductor Co.,Ltd. shall not be liable for any claim or suits with regard to a third party's intellectual property rights which has resulted from the use of the technical information and products mentioned above.

This catalog provides information as of Jun, 2012. Specifications and information herein are subject to change without notice.