TOSHIBA CMOS Digital Integrated Circuit Silicon Monolithic

TC74VCXH16374FT

Low-Voltage 16-Bit D-Type Flip-Flop with Bushold

The TC74VCXH16374FT is a high-performance CMOS 16-bit D-type flip-flop. Designed for use in 1.8-V, 2.5-V or 3.3-V systems, it achieves high-speed operation while maintaining the CMOS low power dissipation.

This 16-bit D-type flip-flop is controlled by a clock input (CK) and an output enable input ($\overline{OE}$) which are common to each byte. It can be used as two 8-bit flip-flops or one 16-bit flip-flop. When the $\overline{OE}$ input is high, the outputs are in a high-impedance state.

The D data inputs include active bushold circuitry, eliminating the need for external pull-up resistors to hold unused or floating data inputs at a valid logic level.

All inputs are equipped with protection circuits against static discharge.



Weight: 0.25 g (typ.)

Features

- Low-voltage operation: V_{CC} = 1.8 to 3.6 V
- Bushold on data inputs eliminating the need for external pull-up/pull-down resistors
- High-speed operation: t_{pd} = 3.0 ns (max) (V_{CC} = 3.0 to 3.6 V)
  : t_{pd} = 3.9 ns (max) (V_{CC} = 2.3 to 2.7 V)
  : t_{pd} = 6.0 ns (max) (V_{CC} = 1.8 V)
- Output current: I_{OH}/I_{OL} = ±24 mA (min) (V_{CC} = 3.0 V)
  : I_{OH}/I_{OL} = ±18 mA (min) (V_{CC} = 2.3 V)
  : I_{OH}/I_{OL} = ±6 mA (min) (V_{CC} = 1.8 V)
- Latch-up performance: –300 mA
- ESD performance: Machine model ≥ ±200 V
  Human body model ≥ ±2000 V
- Package: TSSOP
- 3.6-V tolerant function and power-down protection control inputs and outputs

Pin Assignment (top view)



IEC Logic Symbol



Truth Table

Inputs			Outputs
$1\overline{OE}$	1CK	1D1-1D8	1Q1-1Q8
H	X	X	Z
L	↓	X	Qn
L	↑	L	L
L	↑	H	H

Inputs			Outputs
$2\overline{OE}$	2CK	2D1-2D8	2Q1-2Q8
H	X	X	Z
L	↓	X	Qn
L	↑	L	L
L	↑	H	H

X: Don't care

Z: High impedance

Qn: No change

System Diagram



Absolute Maximum Ratings (Note 1)

Characteristics		Symbol	Rating	Unit
Power supply voltage		V_{CC}	−0.5 to 4.6	V
DC input voltage	($\overline{OE}$, CK)	V_{IN}	−0.5 to 4.6	V
	(An)		−0.5 to V_{CC} + 0.5	
DC output voltage		V_{OUT}	−0.5 to 4.6 (Note 2)	V
			−0.5 to V_{CC} + 0.5 (Note 3)	
Input diode current		I_{IK}	−50	mA
Output diode current		I_{OK}	±50 (Note 4)	mA
Output current		I_{OUT}	±50	mA
Power dissipation		P_D	400	mW
DC V_{CC}/ground current per supply pin		I_{CC}/I_{GND}	±100	mA
Storage temperature		T_{stg}	−65 to 150	°C

Note 1: Exceeding any of the absolute maximum ratings, even briefly, lead to deterioration in IC performance or even destruction.
Using continuously under heavy loads (e.g. the application of high temperature/current/voltage and the significant change in temperature, etc.) may cause this product to decrease in the reliability significantly even if the operating conditions (i.e. operating temperature/current/voltage, etc.) are within the absolute maximum ratings and the operating ranges.
Please design the appropriate reliability upon reviewing the Toshiba Semiconductor Reliability Handbook (“Handling Precautions”/“Derating Concept and Methods”) and individual reliability data (i.e. reliability test report and estimated failure rate, etc).

Note 2: OFF state

Note 3: High or low state. I_{OUT} absolute maximum rating must be observed.

Note 4: $V_{OUT} < GND$, $V_{OUT} > V_{CC}$

Operating Ranges (Note 1) (Note 2)

Characteristics		Symbol	Rating	Unit
Power supply voltage		V_{CC}	1.8 to 3.6	V
			1.2 to 3.6 (Note 3)	
Input voltage	($\overline{OE}$, CK)	V_{IN}	−0.3 to 3.6	V
	(An)		0 to V_{CC}	
Output voltage		V_{OUT}	0 to 3.6 (Note 4)	V
			0 to V_{CC} (Note 5)	
Output current		I_{OH}/I_{OL}	±24 (Note 6)	mA
			±18 (Note 7)	
			±6 (Note 8)	
Operating temperature		T_{opr}	−40 to 85	°C
Input rise and fall time		dt/dv	0 to 10 (Note 9)	ns/V

Note 1: The operating ranges must be maintained to ensure the normal operation of the device. Unused inputs must be tied to either VCC or GND.

Note 2: Floating or unused control inputs must be held high or low.

Note 3: Data retention

Note 4: OFF state

Note 5: High or low state

Note 6: V_{CC} = 3.0 to 3.6 V

Note 7: V_{CC} = 2.3 to 2.7 V

Note 8: V_{CC} = 1.8 V

Note 9: V_{IN} = 0.8 to 2.0 V, V_{CC} = 3.0 V

Electrical Characteristics

DC Characteristics (Ta = –40 to 85°C, 2.7 V < V_{CC} ≦ 3.6 V)

Characteristics		Symbol	Test Condition		V_{CC} (V)	Min	Max	Unit
Input voltage	H-level	V_{IH}	—		2.7 to 3.6	2.0	—	V
	L-level	V_{IL}	—		2.7 to 3.6	—	0.8	
Output voltage	H-level	V_{OH}	V_{IN} = V_{IH} or V_{IL}	I_{OH} = –100 μA	2.7 to 3.6	V_{CC} – 0.2	—	V
				I_{OH} = –12 mA	2.7	2.2	—	
				I_{OH} = –18 mA	3.0	2.4	—	
				I_{OH} = –24 mA	3.0	2.2	—	
	L-level	V_{OL}	V_{IN} = V_{IH} or V_{IL}	I_{OL} = 100 μA	2.7 to 3.6	—	0.2	
				I_{OL} = 12 mA	2.7	—	0.4	
				I_{OL} = 18 mA	3.0	—	0.4	
				I_{OL} = 24 mA	3.0	—	0.55	
Input leakage current	($\overline{OE}$, CK)	I_{IN}	V_{IN} = 0 to 3.6 V		2.7 to 3.6	—	±5.0	μA
	(An)		V_{IN} = V_{CC} or GND		2.7 to 3.6	—	±5.0	
Bushold input minimum drive hold current		$I_{I (HOLD)}$	V_{IN} = 0.8 V		3.0	75	—	μA
			V_{IN} = 2.0 V		3.0	–75	—	
Bushold input over-drive current to change state		$I_{I (OD)}$	(Note 1)		3.6	—	450	μA
			(Note 2)		3.6	—	–450	
3-state output OFF state current		I_{OZ}	V_{IN} = V_{IH} or V_{IL} V_{OUT} = 0 to 3.6 V		2.7 to 3.6	—	±10.0	μA
Power-off leakage current		I_{OFF}	V_{OUT} = 0 to 3.6 V		0	—	10.0	μA
Quiescent supply current		I_{CC}	V_{IN} = V_{CC} or GND		2.7 to 3.6	—	20.0	μA
			V_{CC} ≦ V_{OUT} ≦ 3.6 V	(Note 3)	2.7 to 3.6	—	±20.0	
Increase in I_{CC} per input		ΔI_{CC}	V_{IH} = V_{CC} – 0.6 V		2.7 to 3.6	—	750	μA

Note 1: An external driver must source at least the specified current to switch LOW-to-HIGH.

Note 2: An external driver must sink at least the specified current to switch HIGH-to-LOW.

Note 3: Outputs high impedance only.

DC Characteristics (Ta = −40 to 85°C, 2.3 V ≦ V_{CC} ≦ 2.7 V)

Characteristics		Symbol	Test Condition		V_{CC} (V)	Min	Max	Unit
Input voltage	H-level	V_{IH}	—		2.3 to 2.7	1.6	—	V
	L-level	V_{IL}	—		2.3 to 2.7	—	0.7	
Output voltage	H-level	V_{OH}	V_{IN} = V_{IH} or V_{IL}	I_{OH} = −100 μA	2.3 to 2.7	V_{CC} − 0.2	—	V
				I_{OH} = −6 mA	2.3	2.0	—	
				I_{OH} = −12 mA	2.3	1.8	—	
				I_{OH} = −18 mA	2.3	1.7	—	
	L-level	V_{OL}	V_{IN} = V_{IH} or V_{IL}	I_{OL} = 100 μA	2.3 to 2.7	—	0.2	
				I_{OL} = 12 mA	2.3	—	0.4	
				I_{OL} = 18 mA	2.3	—	0.6	
Input leakage current	($\overline{OE}$, CK)	I_{IN}	V_{IN} = 0 to 3.6 V		2.3 to 2.7	—	±5.0	μA
	(An)		V_{IN} = V_{CC} or GND		2.3 to 2.7	—	±5.0	
Bushold input minimum drive hold current		$I_{I (HOLD)}$	V_{IN} = 0.7 V		2.3	45	—	μA
			V_{IN} = 1.6 V		2.3	−45	—	
Bushold input over-drive current to change state		$I_{I (OD)}$	(Note 1)		2.7	—	300	μA
			(Note 2)		2.7	—	−300	
3-state output OFF state current		I_{OZ}	V_{IN} = V_{IH} or V_{IL} V_{OUT} = 0 to 3.6 V		2.3 to 2.7	—	±10.0	μA
Power-off leakage current		I_{OFF}	V_{OUT} = 0 to 3.6 V		0	—	10.0	μA
Quiescent supply current		I_{CC}	V_{IN} = V_{CC} or GND		2.3 to 2.7	—	20.0	μA
			V_{CC} ≦ V_{OUT} ≦ 3.6 V	(Note 3)	2.3 to 2.7	—	±20.0	

Note 1: An external driver must source at least the specified current to switch LOW-to-HIGH.

Note 2: An external driver must sink at least the specified current to switch HIGH-to-LOW.

Note 3: Outputs high impedance only.

DC Characteristics (Ta = −40 to 85°C, 1.8 V ≦ V_{CC} < 2.3 V)

Characteristics		Symbol	Test Condition		V_{CC} (V)	Min	Max	Unit
Input voltage	H-level	V_{IH}	—		1.8 to 2.3	0.7 × V_{CC}	—	V
	L-level	V_{IL}	—		1.8 to 2.3	—	0.2 × V_{CC}	
Output voltage	H-level	V_{OH}	V_{IN} = V_{IH} or V_{IL}	I_{OH} = −100 μA	1.8	V_{CC} − 0.2	—	V
				I_{OH} = −6 mA	1.8	1.4	—	
	L-level	V_{OL}	V_{IN} = V_{IH} or V_{IL}	I_{OL} = 100 μA	1.8	—	0.2	
				I_{OL} = 6 mA	1.8	—	0.3	
Input leakage current	($\overline{OE}$, CK)	I_{IN}	V_{IN} = 0 to 3.6 V		1.8	—	±5.0	μA
	(An)		V_{IN} = V_{CC} or GND		1.8	—	±5.0	
Bushold input minimum drive hold current		$I_{I (HOLD)}$	V_{IN} = 0.36 V		1.8	25	—	μA
			V_{IN} = 1.26 V		1.8	−25	—	
Bushold input over-drive current to change state		$I_{I (OD)}$	(Note 1)		1.8	—	200	μA
			(Note 2)		1.8	—	−200	
3-state output OFF state current		I_{OZ}	V_{IN} = V_{IH} or V_{IL} V_{OUT} = 0 to 3.6 V		1.8	—	±10.0	μA
Power-off leakage current		I_{OFF}	V_{OUT} = 0 to 3.6 V		0	—	10.0	μA
Quiescent supply current		I_{CC}	V_{IN} = V_{CC} or GND		1.8	—	20.0	μA
			V_{CC} ≦ V_{OUT} ≦ 3.6 V	(Note 3)	1.8	—	±20.0	

Note 1: An external driver must source at least the specified current to switch LOW-to-HIGH.

Note 2: An external driver must sink at least the specified current to switch HIGH-to-LOW.

Note 3: Outputs high impedance only.

AC Characteristics (Ta = −40 to 85°C, input: $t_r = t_f = 2.0$ ns, $C_L = 30$ pF, $R_L = 500\ \Omega$) (Note 1)

Characteristics	Symbol	Test Condition	V_{CC} (V)	Min	Max	Unit
Maximum clock frequency	f_{max}	Figure 1, Figure 2	1.8	125	—	MHz
			2.5 ± 0.2	200	—	
			3.3 ± 0.3	250	—	
Propagation delay time (CK-Q)	t_{pLH} t_{pHL}	Figure 1, Figure 2	1.8	1.5	6.0	ns
			2.5 ± 0.2	1.0	3.9	
			3.3 ± 0.3	0.8	3.0	
3-state output enable time	t_{pZL} t_{pZH}	Figure 1, Figure 3	1.8	1.5	7.0	ns
			2.5 ± 0.2	1.0	4.6	
			3.3 ± 0.3	0.8	3.5	
3-state output disable time	t_{pLZ} t_{pHZ}	Figure 1, Figure 3	1.8	1.5	5.0	ns
			2.5 ± 0.2	1.0	3.8	
			3.3 ± 0.3	0.8	3.5	
Minimum pulse width (CK)	$t_{w\ (H)}$ $t_{w\ (L)}$	Figure 1, Figure 2	1.8	3.0	—	ns
			2.5 ± 0.2	1.5	—	
			3.3 ± 0.3	1.5	—	
Minimum setup time	t_s	Figure 1, Figure 2	1.8	2.5	—	ns
			2.5 ± 0.2	1.5	—	
			3.3 ± 0.3	1.5	—	
Minimum hold time	t_h	Figure 1, Figure 2	1.8	1.0	—	ns
			2.5 ± 0.2	1.0	—	
			3.3 ± 0.3	1.0	—	
Output to output skew	t_{osLH} t_{osHL}	(Note 2)	1.8	—	0.5	ns
			2.5 ± 0.2	—	0.5	
			3.3 ± 0.3	—	0.5	

Note 1: For $C_L = 50$ pF, add approximately 300 ps to the AC maximum specification.

Note 2: Parameter guaranteed by design.
($t_{osLH} = |t_{pLHm} - t_{pLHn}|$, $t_{osHL} = |t_{pHLm} - t_{pHLn}|$)

Dynamic Switching Characteristics

(Ta = 25°C, Input: $t_r = t_f = 2.0$ ns, $C_L = 30$ pF, $R_L = 500\ \Omega$)

Characteristics	Symbol	Test Condition	V_{CC} (V)	Typ.	Unit
Quiet output maximum dynamic V_{OL}	V_{OLP}	V_{IH} = 1.8 V, V_{IL} = 0 V (Note)	1.8	0.25	V
		V_{IH} = 2.5 V, V_{IL} = 0 V (Note)	2.5	0.6	
		V_{IH} = 3.3 V, V_{IL} = 0 V (Note)	3.3	0.8	
Quiet output minimum dynamic V_{OL}	V_{OLV}	V_{IH} = 1.8 V, V_{IL} = 0 V (Note)	1.8	−0.25	V
		V_{IH} = 2.5 V, V_{IL} = 0 V (Note)	2.5	−0.6	
		V_{IH} = 3.3 V, V_{IL} = 0 V (Note)	3.3	−0.8	
Quiet output minimum dynamic V_{OH}	V_{OHV}	V_{IH} = 1.8 V, V_{IL} = 0 V (Note)	1.8	1.5	V
		V_{IH} = 2.5 V, V_{IL} = 0 V (Note)	2.5	1.9	
		V_{IH} = 3.3 V, V_{IL} = 0 V (Note)	3.3	2.2	

Note: Parameter guaranteed by design.

Capacitive Characteristics (Ta = 25°C)

Characteristics	Symbol	Test Condition	V_{CC} (V)	Typ.	Unit
Input capacitance	C_{IN}	—	1.8, 2.5, 3.3	6	pF
Output capacitance	C_O	—	1.8, 2.5, 3.3	7	pF
Power dissipation capacitance	C_{PD}	f_{IN} = 10 MHz (Note)	1.8, 2.5, 3.3	20	pF

Note: C_{PD} is defined as the value of the internal equivalent capacitance which is calculated from the operating current consumption without load.
Average operating current can be obtained by the equation:

$I_{CC\ (opr)} = C_{PD} \cdot V_{CC} \cdot f_{IN} + I_{CC}/16$ (per bit)

AC Test Circuit



Parameter	Switch	
t_{pLH}, t_{pHL}	Open	
t_{pLZ}, t_{pZL}	6.0 V $V_{CC} \times 2$	@V_{CC} = 3.3 ± 0.3 V @V_{CC} = 2.5 ± 0.2 V @V_{CC} = 1.8 V
t_{pHZ}, t_{pZH}	GND	

Figure 1

AC Waveform



Figure 2 t_{pLH}, t_{pHL}, t_w, t_s, t_h



Figure 3 t_{pLZ}, t_{pHZ}, t_{pZL}, t_{pZH}

Symbol	V_{CC}		
	3.3 ± 0.3 V	2.5 ± 0.2 V	1.8 V
V_{IH}	2.7 V	V_{CC}	V_{CC}
V_M	1.5 V	$V_{CC}/2$	$V_{CC}/2$
V_X	V_{OL} + 0.3 V	V_{OL} + 0.15 V	V_{OL} + 0.15 V
V_Y	V_{OH} − 0.3 V	V_{OH} − 0.15 V	V_{OH} − 0.15 V

Package Dimensions

TSSOP48-P-0061-0.50A Unit: mm



Weight: 0.25 g (typ.)

RESTRICTIONS ON PRODUCT USE

20070701-EN GENERAL

- The information contained herein is subject to change without notice.
- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
  In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the “Handling Guide for Semiconductor Devices,” or “TOSHIBA Semiconductor Reliability Handbook” etc.
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.).These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury (“Unintended Usage”). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in his document shall be made at the customer’s own risk.
- The products described in this document shall not be used or embedded to any downstream products of which manufacture, use and/or sale are prohibited under any applicable laws and regulations.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patents or other rights of TOSHIBA or the third parties.
- Please contact your sales representative for product-by-product details in this document regarding RoHS compatibility. Please use these products in this document in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances. Toshiba assumes no liability for damage or losses occurring as a result of noncompliance with applicable laws and regulations.