
Medium power transistor (30V, 1.0A)

2SC5730

●**Features**

1) High speed switching. (Tf : Typ. : 35ns at I_C = 1.0A)
2) Low saturation voltage, typically
   (Typ. : 150mV at I_C = 500mA, I_B = 50mA)
3) Strong discharge power for inductive load and
   capacitance load.
4) Complements the 2SA2048

●**External dimensions** (Units : mm)



●**Applications**

Small signal low frequency amplifier
High speed switching

●**Structure**

NPN Silicon epitaxial planar transistor

●**Packaging specifications**

Type	Package	Taping
	Code	TL
	Basic ordering unit (pieces)	3000
2SC5730		○

●**Absolute maximum ratings** (Ta=25°C)

Parameter	Symbol	Limits	Unit
Collector-base voltage	V_{CBO}	30	V
Collector-emitter voltage	V_{CEO}	30	V
Emitter-base voltage	V_{EBO}	6	V
Collector current	I_C	1	A
	I_{CP}	2	A *1
Power dissipation	P_C	500	mW *2
Junction temperature	Tj	150	°C
Range of storage temperature	Tstg	−55~+150	°C

*1 Pw=10ms
*2 Each terminal mounted on a recommended land.

●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector–base breakdown voltage	BV_{CBO}	30	–	–	V	I_C=100μA
Collector–emitter breakdown voltage	BV_{CEO}	30	–	–	V	I_C=1mA
Emitter–base breakdown voltage	BV_{EBO}	6	–	–	V	I_E=100μA
Collector cut-off current	I_{CBO}	–	–	1.0	μA	V_{CB}=20V
Emitter cut-off current	I_{EBO}	–	–	1.0	μA	V_{EB}=4V
Collector–emitter staturation voltage	$V_{CE(sat)}$	–	150	300	mV	I_C=500mA, I_B=50mA
DC current gain	h_{FE}	120	–	390	–	V_{CE}=2V, I_C=100mA
Transition frequency	fT	–	270	–	MHz	V_{CE}=10V, I_E= –100mA, f=10MHz*1
Collector output capacitance	Cob	–	10	–	pF	V_{CB}=10V, I_E=0mA,*2 f=1MHz
Turn-on time	Ton	–	30	–	ns	I_C=1A, I_{B1}=0.1A I_{B2}= –0.1A $V_{CC}\simeq$ 25V
Storage time	Tstg	–	120	–	ns	
Fall time	Tf	–	35	–	ns	

*1 Non repetitive pulse
*2 See switching charactaristics measurement cicuits

●h_{FE} RANK

Q	R
120-270	180-390

●Electrical characteristic curves




Fig.1 Safe operating area




Fig.2 Switching Time




Fig.3 DC current gain vs. collector current




Fig.4 DC current gain vs. collector current




Fig.5 Collector-emitter saturation voltage vs. collector current




Fig.6 Collector-emitter saturation voltage vs. collector current




Fig.7 Base-emitter saturation voltage vs. collector current




Fig.8 Ground emitter propagation characteristics




Fig.9 Transition frequency





Fig.10 Collector output capacitance

●Switching characteristics measurement circuits



Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document use silicon as a basic material.
  Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).
Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.
In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.