TOSHIBA CMOS Digital Integrated Circuit Silicon Monolithic

# TC74VHC125F,TC74VHC125FN,TC74VHC125FT,TC74VHC125FK
# TC74VHC126F,TC74VHC126FN,TC74VHC126FT,TC74VHC126FK

TC74VHC125F/FN/FT/FK Quad Bus Buffer

TC74VHC126F/FN/FT/FK Quad Bus Buffer

Note: xxxFN (JEDEC SOP) is not available in Japan.

The TC74VHC125/126 are high speed CMOS QUAD BUS BUFFERs fabricated with silicon gate $C^2MOS$ technology.

They achieve the high speed operation similar to equivalent Bipolar Shottky TTL while maintaining the CMOS low power dissipation.

The TC74VHC125 requires the 3-state control input $\overline{G}$ to be set high to place the output into the high impedance state, whereas the TC74VHC126 requires the control input G to be set low to place the output into high impedance.


An input protection circuit ensures that 0 to 5.5 V can be applied to the input pins without regard to the supply voltage. This device can be used to interface 5 V to 3 V systems and two supply systems such as battery back up.

This circuit prevents device destruction due to mismatched supply and input voltages.

## Features


- High speed: $t_{pd}$ = 3.8 ns (typ.) at $V_{CC}$ = 5 V
- Low power dissipation: $I_{CC}$ = 4 μA (max) at Ta = 25°C
- High noise immunity: $V_{NIH} = V_{NIL}$ = 28% $V_{CC}$ (min)
- Power down protection is provided on all inputs.
- Balanced propagation delays: $t_{pLH} \simeq t_{pHL}$
- Wide operating voltage range: $V_{CC\ (opr)}$ = 2 to 5.5 V
- Low noise: $V_{OLP}$ = 0.8 V (max)
- Pin and function compatible with 74ALS125/126

TC74VHC125F, TC74VHC126F




SOP14-P-300-1.27A

TC74VHC125FN, TC74VHC126FN




SOL14-P-150-1.27

TC74VHC125FT, TC74VHC126FT



TSSOP14-P-0044-0.65A

TC74VHC125FK, TC74VHC126FK





VSSOP14-P-0030-0.50

Weight


| | |
|---|---|
| SOP14-P-300-1.27A | : 0.18 g (typ.) |
| SOL14-P-150-1.27 | : 0.12 g (typ.) |
| TSSOP14-P-0044-0.65A | : 0.06 g (typ.) |
| VSSOP14-P-0030-0.50 | : 0.02 g (typ.) |


## Pin Assignment




## IEC Logic Symbol




## Truth Table

### TC74VHC125

| Inputs | | Output |
|---|---|---|
| $\overline{G}$ | A | Y |
| H | X | Z |
| L | L | L |
| L | H | H |

X: Don’t care

Z: High impedance

### TC74VHC126

| Inputs | | Output |
|---|---|---|
| G | A | Y |
| L | X | Z |
| H | L | L |
| H | H | H |

X: Don’t care

Z: High impedance

## Absolute Maximum Ratings (Note)

| Characteristics | Symbol | Rating | Unit |
|---|---|---|---|
| Supply voltage range | $V_{CC}$ | −0.5 to 7.0 | V |
| DC input voltage | $V_{IN}$ | −0.5 to 7.0 | V |
| DC output voltage | $V_{OUT}$ | −0.5 to $V_{CC}$ + 0.5 | V |
| Input diode current | $I_{IK}$ | −20 | mA |
| Output diode current | $I_{OK}$ | ±20 | mA |
| DC output current | $I_{OUT}$ | ±25 | mA |
| DC $V_{CC}$/ground current | $I_{CC}$ | ±50 | mA |
| Power dissipation | $P_D$ | 180 | mW |
| Storage temperature | $T_{stg}$ | −65 to 150 | °C |

Note: Exceeding any of the absolute maximum ratings, even briefly, lead to deterioration in IC performance or even destruction.
Using continuously under heavy loads (e.g. the application of high temperature/current/voltage and the significant change in temperature, etc.) may cause this product to decrease in the reliability significantly even if the operating conditions (i.e. operating temperature/current/voltage, etc.) are within the absolute maximum ratings and the operating ranges.
Please design the appropriate reliability upon reviewing the Toshiba Semiconductor Reliability Handbook (“Handling Precautions”/“Derating Concept and Methods”) and individual reliability data (i.e. reliability test report and estimated failure rate, etc).

## Operating Ranges (Note)

| Characteristics | Symbol | Rating | Unit |
|---|---|---|---|
| Supply voltage | $V_{CC}$ | 2.0 to 5.5 | V |
| Input voltage | $V_{IN}$ | 0 to 5.5 | V |
| Output voltage | $V_{OUT}$ | 0 to $V_{CC}$ | V |
| Operating temperature | $T_{opr}$ | −40 to 85 | °C |
| Input rise and fall time | dt/dv | 0 to 100 ($V_{CC}$ = 3.3 ± 0.3 V)<br>0 to 20 ($V_{CC}$ = 5 ± 0.5 V) | ns/V |

Note: The operating ranges must be maintained to ensure the normal operation of the device.
Unused inputs must be tied to either VCC or GND.

## Electrical Characteristics

### DC Characteristics

| Characteristics | Symbol | Test Condition | | $V_{CC}$ (V) | Ta = 25°C Min | Typ. | Max | Ta = −40 to 85°C Min | Max | Unit |
|---|---|---|---|---|---|---|---|---|---|---|
| High-level input voltage | $V_{IH}$ | — | | 2.0 | 1.50 | — | — | 1.50 | — | V |
| | | | | 3.0 to 5.5 | $V_{CC}$ × 0.7 | — | — | $V_{CC}$ × 0.7 | — | |
| Low-level input voltage | $V_{IL}$ | — | | 2.0 | — | — | 0.50 | — | 0.50 | V |
| | | | | 3.0 to 5.5 | — | — | $V_{CC}$ × 0.3 | — | $V_{CC}$ × 0.3 | |
| High-level output voltage | $V_{OH}$ | $V_{IN}$ = $V_{IH}$ or $V_{IL}$ | $I_{OH}$ = −50 μA | 2.0 | 1.9 | 2.0 | — | 1.9 | — | V |
| | | | | 3.0 | 2.9 | 3.0 | — | 2.9 | — | |
| | | | | 4.5 | 4.4 | 4.5 | — | 4.4 | — | |
| | | | $I_{OH}$ = −4 mA | 3.0 | 2.58 | — | — | 2.48 | — | |
| | | | $I_{OH}$ = −8 mA | 4.5 | 3.94 | — | — | 3.80 | — | |
| Low-level output voltage | $V_{OL}$ | $V_{IN}$ = $V_{IH}$ or $V_{IL}$ | $I_{OL}$ = 50 μA | 2.0 | — | 0.0 | 0.1 | — | 0.1 | V |
| | | | | 3.0 | — | 0.0 | 0.1 | — | 0.1 | |
| | | | | 4.5 | — | 0.0 | 0.1 | — | 0.1 | |
| | | | $I_{OL}$ = 4 mA | 3.0 | — | — | 0.36 | — | 0.44 | |
| | | | $I_{OL}$ = 8 mA | 4.5 | — | — | 0.36 | — | 0.44 | |
| 3-state output off-state current | $I_{OZ}$ | $V_{IN}$ = $V_{IH}$ or $V_{IL}$<br>$V_{OUT}$ = $V_{CC}$ or GND | | 5.5 | — | — | ±0.25 | — | ±2.50 | μA |
| Input leakage current | $I_{IN}$ | $V_{IN}$ = 5.5 V or GND | | 0 to 5.5 | — | — | ±0.1 | — | ±1.0 | μA |
| Quiescent supply current | $I_{CC}$ | $V_{IN}$ = $V_{CC}$ or GND | | 5.5 | — | — | 4.0 | — | 40.0 | μA |

## AC Characteristics (input: $t_r = t_f = 3$ ns)

| Characteristics | Symbol | Test Condition | | | Ta = 25°C | | | Ta = −40 to 85°C | | Unit |
|---|---|---|---|---|---|---|---|---|---|---|
| | | | $V_{CC}$ (V) | $C_L$ (pF) | Min | Typ. | Max | Min | Max | |
| Propagation delay time | $t_{pLH}$ $t_{pHL}$ | — | 3.3 ± 0.3 | 15 | — | 5.6 | 8.0 | 1.0 | 9.5 | ns |
| | | | | 50 | — | 8.1 | 11.5 | 1.0 | 13.0 | |
| | | | 5.0 ± 0.5 | 15 | — | 3.8 | 5.5 | 1.0 | 6.5 | |
| | | | | 50 | — | 5.3 | 7.5 | 1.0 | 8.5 | |
| Output enable time | $t_{pZL}$ $t_{pZH}$ | $R_L$ = 1 kΩ | 3.3 ± 0.3 | 15 | — | 5.4 | 8.0 | 1.0 | 9.5 | ns |
| | | | | 50 | — | 7.9 | 11.5 | 1.0 | 13.0 | |
| | | | 5.0 ± 0.5 | 15 | — | 3.6 | 5.1 | 1.0 | 6.0 | |
| | | | | 50 | — | 5.1 | 7.1 | 1.0 | 8.0 | |
| Output disable time | $t_{pLZ}$ $t_{pHZ}$ | $R_L$ = 1 kΩ | 3.3 ± 0.3 | 50 | — | 9.5 | 13.2 | 1.0 | 15.0 | ns |
| | | | 5.0 ± 0.5 | 50 | — | 6.1 | 8.8 | 1.0 | 10.0 | |
| Output to output skew | $t_{osLH}$ $t_{osHL}$ | (Note 1) | 3.3 ± 0.3 | 50 | — | — | 1.5 | — | 1.5 | ns |
| | | | 5.0 ± 0.5 | 50 | — | — | 1.0 | — | 1.0 | |
| Input capacitance | $C_{IN}$ | — | | | — | 4 | 10 | — | 10 | pF |
| Output capacitance | $C_{OUT}$ | — | | | — | 6 | — | — | — | pF |
| Power dissipation capacitance (Note 2) | $C_{PD}$ | TC74VHC125 | | | — | 14 | — | — | — | pF |
| | | TC74VHC126 | | | — | 15 | — | — | — | |

Note 1: Parameter guaranteed by design.

$t_{osLH} = |t_{pLHm} - t_{pLHn}|$, $t_{osHL} = |t_{pHLm} - t_{pHLn}|$

Note 2: $C_{PD}$ is defined as the value of the internal equivalent capacitance which is calculated from the operating current consumption without load.


Average operating current can be obtained by the equation:

$I_{CC\ (opr)} = C_{PD} \cdot V_{CC} \cdot f_{IN} + I_{CC}/4$ (per gate)

## Noise Characteristics (input: $t_r = t_f = 3$ ns)


| Characteristics | Symbol | Test Condition | Ta = 25°C | | | Unit |
|---|---|---|---|---|---|---|
| | | | $V_{CC}$ (V) | Typ. | Limit | |
| Quiet output maximum dynamic $V_{OL}$ | $V_{OLP}$ | $C_L$ = 50 pF | 5.0 | 0.3 | 0.8 | V |
| Quiet output minimum dynamic $V_{OL}$ | $V_{OLV}$ | $C_L$ = 50 pF | 5.0 | −0.3 | −0.8 | V |
| Minimum high level dynamic input voltage | $V_{IHD}$ | $C_L$ = 50 pF | 5.0 | — | 3.5 | V |
| Maximum low level dynamic input voltage | $V_{ILD}$ | $C_L$ = 50 pF | 5.0 | — | 1.5 | V |

**Input Equivalent Circuit**



## Package Dimensions


SOP14-P-300-1.27A Unit: mm




Weight: 0.18 g (typ.)

**Package Dimensions (Note)**

SOL14-P-150-1.27 Unit : mm





Note: This package is not available in Japan.

Weight: 0.12 g (typ.)

## Package Dimensions


TSSOP14-P-0044-0.65A Unit: mm




Weight: 0.06 g (typ.)

## Package Dimensions

VSSOP14-P-0030-0.50 Unit: mm




Weight: 0.02 g (typ.)

## RESTRICTIONS ON PRODUCT USE

20070701-EN GENERAL

- The information contained herein is subject to change without notice.
- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
  In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the “Handling Guide for Semiconductor Devices,” or “TOSHIBA Semiconductor Reliability Handbook” etc.
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.).These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury (“Unintended Usage”). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in his document shall be made at the customer’s own risk.
- The products described in this document shall not be used or embedded to any downstream products of which manufacture, use and/or sale are prohibited under any applicable laws and regulations.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patents or other rights of TOSHIBA or the third parties.
- Please contact your sales representative for product-by-product details in this document regarding RoHS compatibility. Please use these products in this document in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances. Toshiba assumes no liability for damage or losses occurring as a result of noncompliance with applicable laws and regulations.