COP820CJ,COP840CJ,COP880C,COP884BC, COP888CF,COP888CL,COP888EK,COP888FH, COP888GW,COP8ACC5,COP8AME9,COP8CBE9, COP8CBR9,COP8CCE9,COP8CCR9,COP8CDR9, COP8SAA7,COP8SAC7,COP8SBR9,COP8SCR9, COP8SDR9,COP8SGE5,COP8SGE7,COP8SGG5, COP8SGH5,COP8SGK5,COP8SGR5,COP8SGR7, COP912C

AN-329 Implementing an 8-Bit Buffer in COPS

Literature Number: SNOA581

Implementing an 8-Bit Buffer in COPS™

National Semiconductor
Application Note 329
David Pointer
April 1983

Sometimes a COP microcontroller must input and/or output 8-bit data; for instance, when handling ASCII data. In some applications, the processor must also provide temporary storage for 8-bit data before it is output. The COP instruction set and RAM structure lend themselves very nicely to providing a 32 digit, 8-bit buffer for a solution to these applications.

Such a large buffer is possible using a COP440 or a COP444L. The other members of the COP400 family with half as much RAM as these two would provide a 16 digit 8-bit buffer using the techniques described in this example.


Four adjacent RAM registers (16 digits each) are required. Referring to *Figure 1*, registers 4, 5, 6, and 7 are used for the buffer. Each RAM location contains 4 bits, so 2 locations will be used to store a byte of data. But these RAM locations are not adjacent to each other. You will note that the MSD of digit number 0A hex is in RAM location (4, A) while the LSD of the same digit is in RAM location (6, A).

The 2 RAM locations CHARM and CHARL are used for temporary storage of an 8-bit value.

In addition, 4 RAM locations are used for buffer pointers: those labelled IPM and IPL are the MSD and LSD of the input pointer, and those labelled OPM and OPL are the MSD and LSD of the output pointer. Each pointer's function is to store an 8-bit counter whose value ranges from 00 hex thru 1F hex. The input pointer's value is used for storing the temporary storage buffer contents into the digit with the same number. For example, if the input pointer equals 14 hex, then the contents of CHARM would be stored in RAM location (5, 4) and the contents of CHARL would be stored in RAM location (7, 4). The output pointer's value is used for retrieving a digit from the buffer and putting it in CHARM and CHARL. For instance, if the output pointer equals 05 hex, then the contents of RAM location (4, 5) would be transferred to CHARM and the contents of RAM location (6, 5) would be transferred to CHARL.

A simple example of one possible application of the buffer is flowcharted in *Figure 2.* In this example, data is input to CHARM and CHARL, then stored in the buffer. An output device (a printer) is checked to see if it is ready to receive data. If it is, data is brought out of the buffer and put in CHARM and CHARL for output to the printer.

Pages 3 and 4 contain a listing of the subroutines needed to perform the data transfers in the 32-digit, 8-bit buffer.




TL/DD/5181–1

FIGURE 1. 8-Bit Buffer RAM Map

COPS™ is a trademark of National Semiconductor Corporation.

©1995 National Semiconductor Corporation TL/DD/5181 RRD-B30M105/Printed in U. S. A.



TL/DD/5181–2

FIGURE 2. Buffer Example Flowchart

```
COP CROSS ASSEMBLER    PAGE:  1
BUFFER

    1            ;************************************
    2            ;***                                ***
    3            ;***  8-BIT RAM BUFFER SUBROUTINES  ***
    4            ;***                                ***
    5            ;************************************
    6            ;THESE ARE SUBROUTINES FOR IMPLEMENTING A 32 BYTE
    7            ;BUFFER IN A COP440 OR COP444L RAM  9/3/82
    8     01BC   .CHIP 444
    9            .TITLE BUFFER
   10     002D   CHARM   =       2,13            ;TEMPORARY STORAGE BUFFER MSD
   11     002C   CHARL   =       2,12            ;TEMPORARY STORAGE BUFFER LSD
   12     002F   IPM     =       2,15            ;INPUT POINTER MSD
   13     002E   IPL     =       2,14            ;INPUT POINTER LSD
   14     003F   OPM     =       3,15            ;OUTPUT POINTER MSD
   15     003E   OPL     =       3,14            ;OUTPUT POINTER LSD
   16 000 00             CLRA
   17     0080   .PAGE 2
   18            ;MTOC IS A SUBROUTINE THAT TRANSFERS M(OPM) AND M(OPL) TO
   19            ;CHARM AND CHARL
   20 080 233E   MTOC:    LDD     OPL             ;LOAD LSD OUTPUT POINTER
   21 082 50              CAB                     ;WHICH IS BD
   22 083 233F            LDD     OPM              ;LOAD MSB OUTPUT POINTER FOR B
   23 085 54              AISC    4                ;MAKE BR EQUAL 4 OR 5
   24 086 12              XABR
   25 087 25              LD      2               ;LOAD M(OPM), MAKE BR = 6 OR 7
   26 088 23AD            XAD     CHARM           ;M(OPM) TO CHARM
   27 08A 05              LD                       ;LOAD M(OPL)
   28 08B 23AC            XAD     CHARL           ;M(OPL) TO CHARL
   29 08D 48              RET
   30            ;
   31            ;
   32            ;CTOM IS A SUBROUTINE THAT TRANSFERS CHARM AND CHARL TO
   33            ;M(IPM) AND M(IPL)
   34 08E 232E   CTOM:    LDD     IPL             ;LOAD LSD INPUT POINTER
   35 090 50              CAB                     ;WHICH IS BD
   36 091 232F            LDD     IPM             ;LOAD MSD INPUT POINTER FOR BR
   37 093 54              AISC    4               ;MAKE BR = 4 OR 5
   38 094 12              XABR
   39 095 232D            LDD     CHARM           ;LOAD MSD TEMP STORAGE
   40 097 26              X       2               ;TO M(OPM), MAKE BR = 6 OR 7
   41 098 232C            LDD     CHARL           ;LOAD LSD TEMP STORAGE
   42 09A 06              X                       ;TO M(OPL)
   43 09B 48              RET
   44            ;
   45            ;
```

```
COP CROSS ASSEMBLER    PAGE:  2
BUFFER

   46            .FORM
   47            ;INCREMENTS INPUT POINT OR OUTPUT POINTER, ROLLS OVER
   48            ;AT 1F HEX
   49 09C 2D     INCIP:  LBI     IPL             ;POINT TO LSD OF POINTER
   50 09D 3D     INCOP:  LBI     OPL
   51 09E 22             SC                      ;C=1 FOR INCREMENT
   52 09F 00             CLRA
   53 0A0 30             ASC                     ;INCREMENT RAM VALUE
   54 0A1 44             NOP                     ;NEGATES SKIP CONDITION
   55 0A2 04             XIS                     ;STORE AND POINT TO (X,F)
   56 0A3 00             CLRA
   57 0A4 30             ASC                     ;PROPAGATE CARRY, IF ANY, TO MS
   58 0A5 44             NOP
   59 0A6 06             X                       ;STORE
   60 0A7 45             RMB     1               ;ROLL OVER AT X'1F
   61 0A8 48             RET
   62            ;
   63            ;
   64            .END


COP CROSS ASSEMBLER    PAGE:  3
BUFFER

CHARL  002C     CHARM  002D     CTOM   008E *   INCIP  009C *
INCOP  009D *   IPL    002E     IPM    002F     MTOC   0080 *
OPL    003E     OPM    003F
NO ERROR LINES
   42  ROM WORDS USED
COP   444  ASSEMBLY
SOURCE CHECKSUM = C6A5
INPUT FILE    6:RBUFFC. SRC  VN:    5
```

LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform, when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

National Semiconductor Corporation
1111 West Bardin Road
Arlington, TX 76017
Tel: 1(800) 272-9959
Fax: 1(800) 737-7018

National Semiconductor Europe
Fax: (+49) 0-180-530 85 86
Email: cnjwge@tevm2.nsc.com
Deutsch Tel: (+49) 0-180-530 85 85
English Tel: (+49) 0-180-532 78 32
Français Tel: (+49) 0-180-532 93 58
Italiano Tel: (+49) 0-180-534 16 80

National Semiconductor Hong Kong Ltd.
13th Floor, Straight Block,
Ocean Centre, 5 Canton Rd.
Tsimshatsui, Kowloon
Hong Kong
Tel: (852) 2737-1600
Fax: (852) 2736-9960

National Semiconductor Japan Ltd.
Tel: 81-043-299-2309
Fax: 81-043-299-2408

National does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and National reserves the right at any time without notice to change said circuitry and specifications.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		**Applications**	
Audio	www.ti.com/audio	Communications and Telecom	www.ti.com/communications
Amplifiers	amplifier.ti.com	Computers and Peripherals	www.ti.com/computers
Data Converters	dataconverter.ti.com	Consumer Electronics	www.ti.com/consumer-apps
DLP® Products	www.dlp.com	Energy and Lighting	www.ti.com/energy
DSP	dsp.ti.com	Industrial	www.ti.com/industrial
Clocks and Timers	www.ti.com/clocks	Medical	www.ti.com/medical
Interface	interface.ti.com	Security	www.ti.com/security
Logic	logic.ti.com	Space, Avionics and Defense	www.ti.com/space-avionics-defense
Power Mgmt	power.ti.com	Transportation and Automotive	www.ti.com/automotive
Microcontrollers	microcontroller.ti.com	Video and Imaging	www.ti.com/video
RFID	www.ti-rfid.com		
OMAP Mobile Processors	www.ti.com/omap		
Wireless Connectivity	www.ti.com/wirelessconnectivity		
	TI E2E Community Home Page		e2e.ti.com

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2011, Texas Instruments Incorporated