E91207R

Surface Mount Glass Passivated Single Phase Bridge Rectifier

Reverse Voltage 1000V Output Current 2.0A



RoHS COMPLIANT

Features

- Glass passivated fast recovery bridge rectifiers
- Ideal for automated placement
- Very low profile - max height 1.2 mm
- High surge current capability
- Moisture sensitivity: level 1, per J-STD-020
- High temperature soldering guaranteed: 260℃/10 seconds
- Low forward voltage drop



case: E91

Mechanical Data

- Case:E91,Molding compound meets UL 94V-0 flammability rating
- Terminals:Matte tin plated leads,solderable per MIl-STD-750 Method 2026,J-STD-002 and JESD22-B102

Typical Applications

General purpose use in ac-to-dc bridge full wave rectification for TV,Monitor,SMPS,Adapter, Printer,Audio equipment,and Home Applications application

Maximum Ratings (TA = 25 °C unless otherwise noted)

Parameter	Symbol	E91207R	Unit
Maximum repetitive peak reverse voltage	VRRM	1000	V
Maximum RMS voltage	VRMS	700	V
Maximum DC blocking voltage	VDC	1000	V
Maximum average output rectified current	Io(AV)	2.0	A
Peak forward surge current 8.3 ms single half sine-wave superimposed on rated load	IFSM	85	A
Rating for fusing (t≤8.3ms)	I^2t	30	A^2s
Operating junction and storage temperature range	TJ, TSTG	150	°C

Electrical Characteristics (TA = 25 °C unless otherwise noted)

Parameter	Test Conditions	Symbol	E91207R	Unit
Maximum instantaneous forward voltage	IF=1A	V_F	1.1	Volts
	IF=2A		1.3	
Maximum DC reverse current at rated DC blocking voltage	TA=25℃	I_R	5.0	μA
	TA=125℃		100	
Typical reverse recovery time	I_F=0.5A,I_R=1.0A, I_{rr}=0.25A	t_{rr}	250	nS
Typical junction capacitance	4.0 V, 1 MHz	C_J	22	pF

Thermal Characteristics (Ta=25℃ unless otherwixe noted)				
Parameter	**Test Conditions**	**Symbol**	**E91207R**	**Unit**
Typical thermal resistance	juntion to ambient[1)]	$R_{\theta JA}$	45	℃/W
	juntion to case[1)]	$R_{\theta JC}$	12.6	
	juntion to ambient[2)]	$R_{\theta JA}$	29.8	
	juntion to case[2)]	$R_{\theta JC}$	8.4	

Note:1), The thermal resistance from junction to ambient and case, mounted on glass epoxy FR-4 P.C.B with recommended copper pads

2), The thermal resistance from junction to ambient and case, mounted on glass epoxy FR-4 P.C.B with 13*13mm copper pads

Ratings and Characteristics Curves

(TA = 25℃ unless otherwise noted)



Figure 1.Forward Current Derating Curve



Figure 2.Maximum Non-Repetitive Peak Forward Surge Current



Figure 3. Typical Instantaneous Forward Characteristics



Figure 4. Typical Reverse Characteristics

Package Outline Dimensions



Mounting Pad layout,unit:mm



(Unit:mm)

Dim	Min	Nom.	Max	Dim	Min	Nom.	Max
A	1.10	1.17	1.20	L3	5.7	5.9	6.1
C	0.20	0.25	0.35	L4	0.6	0.80	1
D	8.3	8.4	8.6	L5	1.4	1.6	1.8
HE	10.0	10.2	10.4	P1	3.0 REF		
E	9.1	9.30	9.5	P2	7.4 REF		
E1	5.28 REF			P3	3.1 REF		
L1	1.4	1.60	1.80	P4	3.68 REF		
L2	1.0	1.2	1.4				

Disclaimers

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page.
(http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.