Ordering number : EN8177B

SANYO Semiconductors
DATA SHEET

An ON Semiconductor Company

Monolithic Linear IC

LA4631 — For Audio Applications 5W 2-Channel AF Power Amplifier

Overview

The LA4631 (5W×2 channels) is a single-ended power amplifier that has a pin arrangement similar to the LA4632 BTL power amplifier (10W×2 channels). The LA4631's pin compatibility makes it possible to share a common printed circuit board among a series of end products differentiated by power rank. (Note that the LA4632 is provided in an SIP-12H package, and that it is necessary to provide a hole for the LA4631 pin 13 if the same printed circuit board is to be shared. Note also that certain external components differ.)

Functions

- 2-channel power amplifier for audio applications

Specifications

Maximum Ratings at Ta = 25°C

Parameter	Symbol	Conditions	Ratings	Unit
Maximum supply voltage	V_{CC} max	With no input signal	24	V
Maximum output current	I_O peak	Per channel	2	A
Allowable power dissipation	Pd max	With an infinitely large heat sink	15	W
Maximum junction temperature	Tj max		150	°C
Operating temperature	Topr		-20 to +75	°C
Storage temperature	Tstg		-40 to +150	°C

Operating Conditions at Ta = 25°C

Parameter	Symbol	Conditions	Ratings	Unit
Recommended supply voltage	V_{CC}		14	V
Recommended load resistance range	R_L op		4	Ω
Allowable operating supply voltage range	V_{CC} op		5.5 to 22	V

*: V_{CC}, R_L, and the output level must be set for the size of the heat sink used so that the Pd max range is not exceeded.

■ Any and all SANYO Semiconductor Co.,Ltd. products described or contained herein are, with regard to "standard application", intended for the use as general electronics equipment (home appliances, AV equipment, communication device, office equipment, industrial equipment etc.). The products mentioned herein shall not be intended for use for any "special application" (medical equipment whose purpose is to sustain life, aerospace instrument, nuclear control device, burning appliances, transportation machine, traffic signal system, safety equipment etc.) that shall require extremely high level of reliability and can directly threaten human lives in case of failure or malfunction of the product or may cause harm to human bodies, nor shall they grant any guarantee thereof. If you should intend to use our products for applications outside the standard applications of our customer who is considering such use and/or outside the scope of our intended standard applications, please consult with us prior to the intended use. If there is no consultation or inquiry before the intended use, our customer shall be solely responsible for the use.

■ Specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.


Electrical Characteristics at Ta = 25°C, V_{CC} = 14V, R_L = 4Ω, f = 1kHz, Rg = 600Ω


Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Standby current	Ist	VSTB = 0V		1	10	μA
Quiescent current drain	I_{CCO}	Rg = 0, VSTB = 5V	18	35	80	mA
Standby pin applied voltage	Vst	The pin 5 voltage such that the amplifier is on	1.5		5	V
Output power	P_O	THD = 10%	4	5		W
Total harmonic distortion	THD	V_O = 1W		0.15	0.4	%
Voltage gain	VG	V_O = 0dBm	33	35	37	dB
Output noise voltage (rms)	V_{NO}	Rg = 0, BPF = 20Hz to 20kHz		0.05	0.25	mVrms
Supply voltage rejection ratio	SVRR	Rg = 0, f_R = 100Hz, V_{CC}R = 0dBm	50	60		dB
Channel separation	CHsep	Rg = 10kΩ, V_O = 0dBm	45	55		dB
Input resistance	Ri		20	30	40	kΩ

Package Dimensions


unit : mm (typ)

3107B






Block Diagram



Application Circuit Example



Top view

External Components and Usage Notes

C1, C2 : These are input coupling capacitors; we recommend a value of 1μF or lower. The LA4631 input pin potential is about 1.4V, and the polarity must be considered due to the DC potential of the circuits connected to the LA4631 front end. The amplifier's startup time (the time from the point power is first applied until the point an output is generated) will change proportionally with the values of these input capacitors. (When 1μF capacitors are used, the startup time will be about 0.2 seconds.)

C3 : This capacitor is used as a ripple filter. We recommend a value of 100μF. Amplifier impulse noise when turned off (when the standby pin goes low) may be made worse if a value under 100μF is used. The pin 1 voltage is about $1/2V_{CC}$. A DC mute function can be applied if pin 1 is connected to ground through a 300 to 500Ω resistor. Note that the muting activation voltage will be too low if a resistor value of 750Ω or higher is used.


C4 : This is an impulse noise prevention capacitor. The recommended value is 4.7μF. If a value of 2.2μF or lower is used for C4, impulse noise when the amplifier is turned off (when the standby pin goes low) may be made worse. Also, if a value of 10μF or higher is used, an "incomplete muting" phenomenon may occur when the amplifier is turned off (when the standby pin goes low).

C5 : Power supply capacitor. This capacitor should be located as close as possible to the IC (to minimize increases in the power supply line impedance) to achieve stable amplifier operation.

C6, C7 : Output capacitors. These capacitors influence the amplifiers low band frequency characteristics. ($fc = 1/2\pi Cout \times R_L$)
fc = low band cutoff frequency, Cout = C6, C7


• Caution


Although the LA4631 is basically pin compatible with the LA4632, there are certain differences in the external components and the way the devices are used.





- The amplifier can be turned on or off by controlling the high/low state of pin 5.
- The amplifier is turned on by applying a voltage of 1.5V or higher or an influx current of 800μA or higher. (If a 5V level is applied directly to pin 5, the pin 5 influx current will be about 4.5mA.)
- If a voltage, Vx, that exceeds 5V will be applied, insert a current limiter resistor (Rx) so that the influx current does not exceed 4.5mA. (See the formula below.)
  Rx = (Vx – 5V)/4.5mA
- When pin 5 is controlled by a microcontroller, to set up a pin 5 influx current (Ix) optimal for the drive capacity of the microcontroller, calculate Rx from the following formula as a first approximation and measure the influx current to verify that level.
  Rx = (Vx/Ix) – R1 (2kΩ)


*: When a voltage is applied to the standby pin (pin 5), refer to the above and insert a resistor (Rx) to limit the influx current if required.



ICCO – VCC
RL = 4Ω
Rg = 0
Quiescent current, ICCO – mA
Supply voltage, VCC – V



PO – VCC
Rg = 600Ω
fin = 1kHz
THD = 10%
RL = 4Ω
RL = 8Ω
Output power, PO – W
Supply voltage, VCC – V



THD – PO
VCC = 14V
RL = 4Ω
Rg = 600Ω
Filter : FLAT
f = 10kHz
f = 1kHz
f = 100Hz
Total harmonic distortion, THD – %
Output power, PO – W



THD – f
VCC = 14V
RL = 4Ω
Rg = 600Ω
PO = 1W
Filter : FLAT
Total harmonic distortion, THD – %
Frequency, f – Hz



Response – f
VCC = 14V
RL = 4Ω
Rg = 600Ω
VO = 0dBm
Response – dB
Frequency, f – Hz



PO – f
VCC = 14V
RL = 4Ω
Rg = 600Ω
THD = 10%
THD = 1%
Output power, PO – W
Frequency, f – Hz


CHsep – f
VCC = 14V
RL = 4Ω
Rg = 10kΩ
DIN AUDIO
CH2→1
CH1→2
Channel separation, CHsep – dB
Frequency, f – Hz


VNO – Rg
VCC = 14V
RL = 4Ω
DIN AUDIO
Output noise voltage, VNO – mVrms
Signal source resistance, Rg – Ω







- SANYO Semiconductor Co.,Ltd. assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein.
- SANYO Semiconductor Co.,Ltd. strives to supply high-quality high-reliability products, however, any and all semiconductor products fail or malfunction with some probability. It is possible that these probabilistic failures or malfunction could give rise to accidents or events that could endanger human lives, trouble that could give rise to smoke or fire, or accidents that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO Semiconductor Co.,Ltd. products described or contained herein are controlled under any of applicable local export control laws and regulations, such products may require the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written consent of SANYO Semiconductor Co.,Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO Semiconductor Co.,Ltd. product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production.
- Upon using the technical information or products described herein, neither warranty nor license shall be granted with regard to intellectual property rights or any other rights of SANYO Semiconductor Co.,Ltd. or any third party. SANYO Semiconductor Co.,Ltd. shall not be liable for any claim or suits with regard to a third party's intellctual property rights which has resulted from the use of the technical information and products mentioned above.

This catalog provides information as of June, 2009. Specifications and information herein are subject to change without notice.