


Data Sheet

HF Reader System Series 6000

S6500 Long Range Reader Module



Specifications:

Part number	RI-STU-650A
Operating Frequency	13.56MHz $\pm$ 7kHz
Supported Transponders	Tag-it HF, Tag-it HF-I, ISO 15693 compliant Transponders
Supply voltage	24V DC +5% / -1% (Noise Ripple: max. 20mV)
Power consumption	Max. 60W
Transmitter power	0.5W to 10W $\pm$ 1dB (adjustable by software in 0.25W steps) above 4W output power an additional heat sink 0.8K/W is necessary
Transmitter modulation	AM (10% - 30%) $\pm$ 6% or 100% (adjustable by software)
Antenna connection	Basic antenna (TX/RX) 1 x SMA female Complementary antenna (RX only):: 1 x SMA female
Antenna Impedance	50 Ohm at 13.56MHz
Receive channels	ASK 423.75kHz and FSK 423.75kHz / 484.29kHz for both antennas (adjustable by software)
Communication Interfaces	RS232 or RS485 (set by jumper)
Address setting for interface	Optional: - 3-position DIP switch (up to 8 addresses) - Software (up to 254 addresses)
Communication Parameters	Up to 115kBits, 8 data bits, even/odd/no parity
Communication Protocol	ISO Host Protocol
Memory	EEPROM 1kByte (for parameters; up to 10,000 write cycles) RAM 256 kByte (for data) Flash 512 kByte (for firmware; update via communication interface)
Outputs	2 opto-coupled: 24V DC / 30mA 1 relay: 24V DC / 60W
Inputs	2 opto-coupled: max. 24V DC / 20mA
Optical Indicators	5 LED's for status diagnostics
Synchronization	Protocol synchronization via I/O
Operating Temperature	-20°C to +65°C
Storage Temperature	-40°C to +85°C
Vibration	EN60068-2-6 (10Hz to 200Hz: 0.15mm/2g)
Dimensions (L x W x H)	160mm x 120mm x 67mm
Weight	650 g

For more information, contact the sales office or distributor nearest you. This contact information can be found on our web site at: <http://www.ti-rfid.com>

Texas Instruments reserves the right to change its products and services at any time without notice. TI provides customer assistance in various technical areas, but does not have full access to data concerning the uses and applications of customers products. Therefore, TI assumes no responsibility for customer product design or for infringement of patents and/or the rights of third parties, which may result from assistance provided by TI.