
High transition frequency (dual transistors)

EMX5 / UMX5N / IMX5

●Features

1) Two 2SC3838K chips in a EMT or UMT or SMT package.
2) High transition frequency. (f_T=3.2GHz)
3) Low output capacitance. (Cob=0.9pF)

●Inner circuits



●Absolute maximum ratings (Ta=25°C)

Parameter		Symbol	Limits	Unit	
Collector-base voltage		V_{CBO}	20	V	
Collector-emitter voltage		V_{CEO}	11	V	
Emitter-base voltage		V_{EBO}	3	V	
Collector current		I_C	50	mA	
Collector power dissipation	EMX5 / UMX5N	Pc	150(TOTAL)	mW	∗1
	IMX5		300(TOTAL)		∗2
Junction temperature		Tj	150	°C	
Storage temperature		Tstg	−55 to +150	°C	


∗1 120mW per element must not be exceeded.
∗2 200mW per element must not be exceeded.

●Package, marking, and packaging specifications

Type	EMX5	UMX5N	IMX5
Package	EMT6	UMT6	SMT6
Marking	X5	X5	X5
Code	T2R	TR	T108
Basic ordering unit (pieces)	8000	3000	3000


●Dimensions (Unit : mm)

EMX6




ROHM : EMT6 Each lead has same dimensions

UMX5N



ROHM : UMT6
EIAJ : SC-88 Each lead has same dimensions

IMX5



ROHM : SMT6
EIAJ : SC-74 Each lead has same dimensions

This product might cause chip aging and breakdown under the large electrified environment.
Please consider to design ESD protection circuit.

© 2010 ROHM Co., Ltd. All rights reserved.

●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage	BV_{CBO}	20	–	–	V	I_C=10μA
Collector-emitter breakdown voltage	BV_{CEO}	11	–	–	V	I_C=1mA
Emitter-base breakdown voltage	BV_{EBO}	3	–	–	V	I_E=10μA
Collector cutoff current	I_{CBO}	–	–	0.5	μA	V_{CB}=10V
Emitter cutoff current	I_{EBO}	–	–	0.5	μA	V_{EB}=2V
DC current transfer ratio	h_{FE}	56	–	120	–	V_{CE}/I_C=10V/5mA
Collector-emitter saturation voltage	$V_{CE(sat)}$	–	–	0.5	V	I_C/I_B=10mA/5mA
Transition frequency	f_T	1.4	3.2	–	GHz	V_{CE}/I_E=10V/–10mA, f=500MHz ＊
Output capacitance	Cob	–	0.9	1.55	pF	V_{CB}/f=10V/1MHz, I_E=0A

＊Transition frequency of the device.

●Electrical characteristics curves




Fig.1 DC current gain vs. collector current




Fig.2 Collector-emitter saturation voltage vs. collector current




Fig.3 Gain bandwidth product vs. emitter current




Fig.4 Capacitance vs. reverse bias voltage




Fig.5 Collector to base time constant vs. collector current characteristics




Fig.6 Noise factor vs. collector current characteristics

© 2010 ROHM Co., Ltd. All rights reserved.

Notes

No copying or reproduction of this document, in part or in whole, is permitted without the consent of ROHM Co.,Ltd.

The content specified herein is subject to change for improvement without notice.

The content specified herein is for the purpose of introducing ROHM's products (hereinafter "Products"). If you wish to use any such Product, please be sure to refer to the specifications, which can be obtained from ROHM upon request.

Examples of application circuits, circuit constants and any other information contained herein illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.

Great care was taken in ensuring the accuracy of the information specified in this document. However, should you incur any damage arising from any inaccuracy or misprint of such information, ROHM shall bear no responsibility for such damage.

The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM and other parties. ROHM shall bear no responsibility whatsoever for any dispute arising from the use of such technical information.

The Products specified in this document are intended to be used with general-use electronic equipment or devices (such as audio visual equipment, office-automation equipment, communication devices, electronic appliances and amusement devices).

The Products specified in this document are not designed to be radiation tolerant.

While ROHM always makes efforts to enhance the quality and reliability of its Products, a Product may fail or malfunction for a variety of reasons.

Please be sure to implement in your equipment using the Products safety measures to guard against the possibility of physical injury, fire or any other damage caused in the event of the failure of any Product, such as derating, redundancy, fire control and fail-safe designs. ROHM shall bear no responsibility whatsoever for your use of any Product outside of the prescribed scope or not in accordance with the instruction manual.

The Products are not designed or manufactured to be used with any equipment, device or system which requires an extremely high level of reliability the failure or malfunction of which may result in a direct threat to human life or create a risk of human injury (such as a medical instrument, transportation equipment, aerospace machinery, nuclear-reactor controller, fuel-controller or other safety device). ROHM shall bear no responsibility in any way for use of any of the Products for the above special purposes. If a Product is intended to be used for any such special purpose, please contact a ROHM sales representative before purchasing.

If you intend to export or ship overseas any Product or technology specified herein that may be controlled under the Foreign Exchange and the Foreign Trade Law, you will be required to obtain a license or permit under the Law.

ROHM SEMICONDUCTOR

Thank you for your accessing to ROHM product informations.
More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

http://www.rohm.com/contact/

© 2010 ROHM Co., Ltd. All rights reserved.