

#### **Features**

- · Glass passivated fast recovery rectifiers
- Ideal for automated placement
- Low forward voltage drop
- Low leakage current
- Moisture sensitivity: level 1, per J-STD-020
- Solder dip 260 °C, 10 s
- Low profile, typical thickness 1.0mm
- AEC-Q101 qualified

# ROHS COMPLIANT

eSGB (SMAF)

## **Typical Applications**

For use of general purpose rectification in lighting, cellular phone, portable device, power supplies, and other consumer applications.

Maximum Ratings (TA = 25 °C unless otherwise noted)									
Parameter	Symbol	LF1	LF2	LF3	LF4	LF5	LF6	LF7	Unit
Maximum repetitive peak reverse voltage	VRRM	50	100	200	400	600	800	1000	V
Maximum RMS voltage	VRMS	35	70	140	280	420	560	700	V
Maximum DC blocking voltage	VDC	50	100	200	400	600	800	1000	V
Maximum average forward rectified current	IF(AV)	1.0 A				А			
Peak forward surge current 8.3 ms single half sine-wave superimposed on rated load	IFSM	30 4			А				
Rating for fusing(t<8.3ms)	l <sup>2</sup> t	3.7 A <sup>2</sup>			A <sup>2</sup> sec				
Operating junction and storage temperature range	TJ, TSTG	- 55 to + 150 °C			°C				

Electrical Characteristics (TA = 25 °C unless otherwise noted)										
Parameter	Test Conditions	Symbol	LF1	LF2	LF3	LF4	LF5	LF6	LF7	Unit
Maximum instantaneous forward voltage	IF=1 A,TA=25℃	V <sub>F</sub>	1.3					V		
Maximum DC reverse current	um DC reverse current TA=25°C 5 d DC blocking voltage TA=125°C 50				μA					
at rated DC blocking voltage			50				μΛ			
Maximum reverse recovery I <sub>F</sub> =0.5A,I <sub>R</sub> =1.0A,		4	450				050 500			
time	I <sub>rr</sub> =0.25A	t <sub>rr</sub>	150			250	500		nS	
Typical junction capacitance	4.0 V, 1 MHz	CJ	11				pF			
$\mathbf{T}_{i}$ is a lather mean rest interval $(1)$	juntion to case	R <sub>θJC</sub>	45							°C/W
Typical thermal resistance <sup>1)</sup>	juntion to mount	R <sub>eJM</sub>	12						0,00	

Note:1), The thermal resistance from junction to case and mount, mounted on P.C.B with 8x8mm copper pads, 2 OZ, FR4 PCB



#### Ratings and Characteristics Curves




Figure 1. Forward Current Derating Curve




Figure 3. Typical Reverse Characteristics




Figure 2.Maximum Non-Repetitive Peak Forward Surge Current






Figure 4. Typical Instantaneous Forward Characteristics




### Package Outline Dimensions















## Packing Information

Packing quantities:

Reel size	Quantity/reel	Quantity/inner Box	Quantity/Carton
7"	ЗK	21K	84K
13"	10K	20K	180K

**Tape & Reel Specification** 





#### **Disclaimers**

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page.

(http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.