


ISDN S-BUS INPUT/OUTPUT TRANSFORMERS 7117-7121



Units matched to leading transceivers IC's.




IC MFG.	FILTRAN P/N	IC MFG.	FILTRAN P/N
AMD AM79C30A/79C32A	7121	NATIONAL TP3420/3421	7119
AT&T/LUCENT T7250/7256/7259 T7903	7120 7119	SGS THOMSON ST5420/5421	7119
MIETEC MTC-2072	7119	SIEMENS PEB 2080/2081/2085 PSB 2186 PEB 2084/2086	7119 7119 7119
MITEL MT8930	7119	YAMAHA 7405B	7119
MOTOROLA MC145474/145475 MC145574	7118 7120		



MECHANICAL AND SCHEMATIC (All dimensions in millimetres)

SUGGESTED PAD LAYOUT

SCHEMATIC



ELECTRICAL SPECIFICATION @ 25°C

Part Number	Turns Ratio (±2%)		L Pri (mH MIN)	L ₁ Sec (µH MAX)		C _{WV} (pF MAX)	CD Pri (pF MAX)		DCR Pri (Ω±25%)		DCR Sec (Ω±25%)	
	A	B		A	B		A	B	A	B	A	B
7117	1:1	1:2	22	5	15	100	42	80	2.4	2.3	2.4	4.0
7118	1:1	1:1	22	5	5	100	42	42	2.4	2.4	2.4	2.4
7119	1:2	1:2	22	15	15	100	80	80	2.5	2.5	4.3	4.3
7120	1:2.5	1:2.5	22	8-40	8-40	100	110	110	2.5	2.5	5.8	5.8
7121	1:2	1:2	22	11	11	100	180	180	2.4	2.4	4.4	4.4

ISSUE: A 08/01 7117 - 7121