BB301C

Built in Biasing Circuit MOS FET IC
VHF RF Amplifier

REJ03G0823-0300
(Previous ADE-208-507A)
Rev.3.00
Aug.10.2005

Features

- Built in Biasing Circuit; To reduce using parts cost & PC board space.
- Low noise characteristics;
  (NF = 1.3 dB typ. at f = 200 MHz)
- Withstanding to ESD;
  Built in ESD absorbing diode. Withstand up to 200V at C=200pF, Rs=0 conditions.
- Provide mini mold packages; CMPAK-4(SOT-343mod)

Outline

RENESAS Package code: PTSP0004ZA-A
(Package name: CMPAK-4)



1. Source
2. Gate1
3. Gate2
4. Drain

Notes : 1. Marking is “AW–”.
2. BB301C is individual type number of RENESAS BBFET.

Not recommend for new design

Absolute Maximum Ratings

(Ta = 25°C)

Item	Symbol	Ratings	Unit
Drain to source voltage	V_{DS}	6	V
Gate1 to source voltage	V_{G1S}	+6 –0	V
Gate2 to source voltage	V_{G2S}	±6	V
Drain current	I_D	25	mA
Channel power dissipation	Pch	100	mW
Channel temperature	Tch	150	°C
Storage temperature	Tstg	–55 to +150	°C

Electrical Characteristics

(Ta = 25°C)

Item	Symbol	Min	Typ	Max	Unit	Test conditions
Drain to source breakdown voltage	$V_{(BR)DSS}$	6	—	—	V	I_D = 200 µA, V_{G1S} = V_{G2S} = 0
Gate1 to source breakdown voltage	$V_{(BR)G1SS}$	+6	—	—	V	I_{G1} = +10 µA, V_{G2S} = V_{DS} = 0
Gate2 to source breakdown voltage	$V_{(BR)G2SS}$	±6	—	—	V	I_{G2} = ±10 µA, V_{G1S} = V_{DS} = 0
Gate1 to source cutoff current	I_{G1SS}	—	—	+100	nA	V_{G1S} = +5 V, V_{G2S} = V_{DS} = 0
Gate2 to source cutoff current	I_{G2SS}	—	—	±100	nA	V_{G2S} = ±5 V, V_{G1S} = V_{DS} = 0
Gate1 to source cutoff voltage	$V_{G1S(off)}$	0.4	—	1.0	V	V_{DS} = 5 V, V_{G2S} = 4 V I_D = 100 µA
Gate2 to source cutoff voltage	$V_{G2S(off)}$	0.4	—	1.0	V	V_{DS} = 5 V, V_{G1S} = 5 V I_D = 100 µA
Drain current	$I_{D(op)}$	10	15	20	mA	V_{DS} = 5 V, V_{G1} = 5 V V_{G2S} = 4 V, R_G = 100 kΩ
Forward transfer admittance	$\|y_{fs}\|$	15	20	—	mS	V_{DS} = 5 V, V_{G1} = 5 V, V_{G2S} =4 V R_G = 100 kΩ, f = 1 kHz
Input capacitance	Ciss	2.2	3.0	3.9	pF	V_{DS} = 5 V, V_{G1} = 5 V V_{G2S} =4 V, R_G = 100 kΩ f = 1 MHz
Output capacitance	Coss	0.9	1.2	1.6	pF	
Reverse transfer capacitance	Crss	—	0.018	0.04	pF	
Power gain	PG	22	26	—	dB	V_{DS} = 5 V, V_{G1} = 5 V, V_{G2S} =4 VR_G = 100 kΩ, f = 200 MHz
Noise figure	NF	—	1.3	1.9	dB	

Not recommend for new design

Main Characteristics

Test Circuit for Operating Items ($I_{D(op)}$, |yfs|, Ciss, Coss, Crss, NF, PG)



Equivalent Circuit



Not recommend for new design

Application Circuit



Maximum Channel Power Dissipation Curve



Typical Output Characteristics



Drain Current vs. Gate2 to Source Voltage



Drain Current vs. Gate1 Voltage



Drain Current vs. Gate1 Voltege



Drain Current vs. Gate1 Voltege



Not recommend for new design

Forward Transfer Admittance vs. Gate1 Voltage



Forward Transfer Admittance vs. Gate1 Voltage



Forward Transfer Admittance vs. Gate1 Voltage



Power Gain vs. Gate Resistance



Noise Figure vs. Gate Resistance



Power Gain vs. Drain Current



Not recommend for new design

Noise Figure vs. Drain Current



Drain Current vs. Gate Resistance



Gain Reduction vs.
Gate2 to Source Voltage



Input Capacitance vs.
Gate2 to Source Voltage



Not recommend for new design

Package Dimensions

JEITA Package Code	RENESAS Code	Package Name	MASS[Typ.]
SC-82A	PTSP0004ZA-A	CMPAK-4(T) / CMPAK-4(T)V	0.006g



Reference Symbol	Dimension in Millimeters		
	Min	Nom	Max
A	0.8	—	1.1
A_1	0	—	0.1
A_2	0.8	0.9	1.0
A_3	—	0.25	—
b	0.25	0.32	0.4
b_1	0.35	0.42	0.5
b_2	—	0.3	—
b_3	—	0.4	—
c	0.1	0.13	0.15
c_1	—	0.11	—
D	1.8	2.0	2.2
E	1.15	1.25	1.35
e	—	0.65	—
e_2	—	0.6	—
H_E	1.8	2.1	2.4
L	0.3	—	0.7
L_1	0.1	—	0.5
L_P	0.2	—	0.6
x	—	—	0.05
y	—	—	0.05
b_4	—	—	0.45
b_5	—	—	0.55
e_1	—	1.5	—
l_1	—	—	0.9
Q	—	0.2	—

Not recommend for new design

Ordering Information

Part Name	Quantity	Shipping Container
BB301CAW-TL-E	3000	ϕ 178 mm Reel, 8 mm Emboss Taping

Note: For some grades, production may be terminated. Please contact the Renesas sales office to check the state of production before ordering the product.

Renesas Technology Corp. Sales Strategic Planning Div. Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan

Keep safety first in your circuit designs!
1. Renesas Technology Corp. puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage.
Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials
1. These materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corp. product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corp. or a third party.
2. Renesas Technology Corp. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.
3. All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corp. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor for the latest product information before purchasing a product listed herein.
The information described here may contain technical inaccuracies or typographical errors.
Renesas Technology Corp. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.
Please also pay attention to information published by Renesas Technology Corp. by various means, including the Renesas Technology Corp. Semiconductor home page (http://www.renesas.com).
4. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Renesas Technology Corp. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
5. Renesas Technology Corp. semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
6. The prior written approval of Renesas Technology Corp. is necessary to reprint or reproduce in whole or in part these materials.
7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.
Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
8. Please contact Renesas Technology Corp. for further details on these materials or the products contained therein.

Not recommend for new design

RENESAS SALES OFFICES

http://www.renesas.com

Refer to "**http://www.renesas.com/en/network**" for the latest and detailed information.

Renesas Technology America, Inc.
450 Holger Way, San Jose, CA 95134-1368, U.S.A
Tel: <1> (408) 382-7500, Fax: <1> (408) 382-7501

Renesas Technology Europe Limited
Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K.
Tel: <44> (1628) 585-100, Fax: <44> (1628) 585-900

Renesas Technology Hong Kong Ltd.
7th Floor, North Tower, World Finance Centre, Harbour City, 1 Canton Road, Tsimshatsui, Kowloon, Hong Kong
Tel: <852> 2265-6688, Fax: <852> 2730-6071

Renesas Technology Taiwan Co., Ltd.
10th Floor, No.99, Fushing North Road, Taipei, Taiwan
Tel: <886> (2) 2715-2888, Fax: <886> (2) 2713-2999

Renesas Technology (Shanghai) Co., Ltd.
Unit2607 Ruijing Building, No.205 Maoming Road (S), Shanghai 200020, China
Tel: <86> (21) 6472-1001, Fax: <86> (21) 6415-2952

Renesas Technology Singapore Pte. Ltd.
1 Harbour Front Avenue, #06-10, Keppel Bay Tower, Singapore 098632
Tel: <65> 6213-0200, Fax: <65> 6278-8001

Renesas Technology Korea Co., Ltd.
Kukje Center Bldg. 18th Fl., 191, 2-ka, Hangang-ro, Yongsan-ku, Seoul 140-702, Korea
Tel: <82> 2-796-3115, Fax: <82> 2-796-2145

Renesas Technology Malaysia Sdn. Bhd.
Unit 906, Block B, Menara Amcorp, Amcorp Trade Centre, No.18, Jalan Persiaran Barat, 46050 Petaling Jaya, Selangor Darul Ehsan, Malaysia
Tel: <603> 7955-9390, Fax: <603> 7955-9510

© 2005. Renesas Technology Corp., All rights reserved. Printed in Japan.

Colophon .3.0