

Evaluation Kit for **ADM1087** Sequencer

FEATURES

Full featured evaluation board for the **ADM1087** sequencer

3 LEDs indicate output sequence

Dedicated ENABLE/DISABLE switch

On-board test points to examine **ADM1087** operation

On-board expansion feature to add more **ADM1087** devices

EVALUATION KIT CONTENTS

ADM1087 evaluation board

GENERAL DESCRIPTION

The **ADM1087** evaluation board (EVAL-ADM1087EBZ) is a fully featured board for evaluating **ADM1087** sequencers.

The board is designed to power up with a 9 V input supply that can be turned on and off using a dedicated switch (Switch S1, ON/OFF). The two **ADM1087** devices on the board can be enabled and disabled using another switch (Switch S2, ENABLE/DISABLE). When enabled, the **ADM1087** devices on the board monitor a voltage rail and turn on the corresponding three **ADP3334** LDO devices in a sequence. LEDs on the board provide a direct visual indication of the sequencing of three different voltages: 3.3 V, 2.5 V, and 1.8 V.

Complete specifications for the **ADM1087** can be found in the **ADM1087** data sheet, available at www.analog.com, and should be consulted in conjunction with this user guide when using the evaluation board.

PHOTOGRAPH OF THE EVALUATION BOARD




Figure 1.

TABLE OF CONTENTS

Features	1	Evaluation Board Description	3
Evaluation Kit Contents.....	1	Evaluation Board Hardware.....	4
General Description	1	Evaluation Board Connector, Switch, LED Functions	4
Photograph of the Evaluation Board.....	1	Evaluation Board Schematic	5
Revision History	2	Bill of Materials.....	6

REVISION HISTORY

11/13—Revision 0: Initial Version

EVALUATION BOARD DESCRIPTION

The **EVAL-ADM1087EBZ** is designed to demonstrate the features of the **ADM1087** sequencer. A simplified block diagram of the evaluation board is shown in Figure 2.

Two **ADM1087** devices are used to sequence the outputs of three **ADP3334** LDO regulators. Separate capacitors on the CEXT pin of each **ADM1087** device determine the time delays between enabling the 3.3 V, 2.5 V, and 1.8 V supplies. The LDO regulators and **ADM1087** devices are connected in a cascade; therefore, the output of each regulator is dependent on the output of the previous device.

There are two switches included on the board:

- The S1 switch (ON/OFF) is used to power up or power down the board.
- The S2 switch (ENABLE/DISABLE) is used to enable or disable the **ADM1087** devices.

A 9 V battery supplies power to the board. The board functions as follows:

1. Place the S1 switch into the ON position to turn on the first **ADP3334** LDO regulator.
2. The **ADM1087** devices monitor the output of this regulator. When the output reaches 3.3 V, the red LED (D1) illuminates and the second **ADP3334** LDO regulator turns on.
3. The **ADM1087** devices monitor the output of this regulator. When the output reaches 2.5 V, the yellow LED (D2) illuminates and the third **ADP3334** LDO regulator turns on.
4. The **ADM1087** devices monitor the output of this regulator. When the output reaches 1.8 V, the green LED (D3) illuminates.




Figure 2. Simplified Block Diagram of **EVAL-ADM1087EBZ**

11837-002

EVALUATION BOARD HARDWARE

EVALUATION BOARD CONNECTOR, SWITCH, LED FUNCTIONS

Table 1. Connector Functions

Reference	Function
P1	Connects the positive and negative terminal of a 9 V battery.

Table 2. Switch Functions

Reference	Position	Function
S1	ON	Powers up the board.
	OFF	Powers down the board.
S2	ENABLE	Enables the ADM1087 devices.
	DISABLE	Disables the ADM1087 devices.

Table 3. LED Functions

Reference	LED Color	Function
D1	Red	Illuminates when the first ADP3334 LDO regulator output is 3.3 V.
D2	Yellow	Illuminates when the second ADP3334 LDO regulator output is 2.5 V.
D3	Green	Illuminates when the third ADP3334 LDO regulator output is 1.8 V.

EVALUATION BOARD SCHEMATIC




Figure 3. EVAL-ADM1087EBZ Schematic, Page 1

11837-003

BILL OF MATERIALS

Table 4. Bill of Materials for the [EVAL-ADM1087EBZ](#)

Name	Part Type	Value	Description	Stock Code
C1	Capacitor	1 μ F	16 V, Y5V, ceramic capacitor	FEC 318-8899
C2	Capacitor	1 μ F	16 V, Y5V, ceramic capacitor	FEC 318-8899
C3	Capacitor	1 μ F	16 V, Y5V, ceramic capacitor	FEC 318-8899
C4	Capacitor	1 μ F	16 V, Y5V, ceramic capacitor	FEC 318-8899
C5	Capacitor	1 μ F	16 V, Y5V, ceramic capacitor	FEC 318-8899
C6	Capacitor	1 μ F	16 V, Y5V, ceramic capacitor	FEC 318-8899
C7	Capacitor	100 nF	35 V through-hole tantalum capacitor	FEC 1100483
C8	Capacitor	100 nF	35 V through-hole tantalum capacitor	FEC 1100483
C9	Capacitor	1 μ F	16 V, Y5V, ceramic capacitor	FEC 318-8899
D1	LED		Red LED	FEC 114-2512
D2	LED		Yellow LED	FEC 114-2515
D3	LED		Green LED	FEC 114-2509
P1	BATT_PP3		Pair battery connectors	FEC 723-988
Q1	BC850B		General-purpose transistor	FEC 108-1239
Q2	BC850B		General-purpose transistor	FEC 108-1239
Q3	BC850B		General-purpose transistor	FEC 108-1239
R1	Resistor	75 k Ω	0.1 W resistor	FEC 933-3541
R2	Resistor	150 k Ω	0.1 W resistor	FEC 933-2626
R3	Resistor	3.9 k Ω	0.1 W resistor	FEC 933-3169
R4	Resistor	10 k Ω	0.1 W resistor	FEC 933-2391
R5	Resistor	91 k Ω	0.1 W resistor	FEC 933-3649
R6	Resistor	110 k Ω	0.1 W resistor	FEC 933-2464
R7	Resistor	3.9 k Ω	0.1 W resistor	FEC 933-3169
R8	Resistor	10 k Ω	0.1 W resistor	FEC 933-2391
R9	Resistor	150 k Ω	0.1 W resistor	FEC 933-2626
R10	Resistor	75 k Ω	0.1 W resistor	FEC 933-3541
R11	Resistor	3.9 k Ω	0.1 W resistor	FEC 933-3169
R12	Resistor	160 k Ω	0.1 W resistor	FEC 933-2685
R13	Resistor	51 k Ω	0.1 W resistor	FEC 933-3339
R14	Resistor	110 k Ω	0.1 W resistor	FEC 933-2464
R15	Resistor	51 k Ω	0.1 W resistor	FEC 933-3339
R16	Resistor	10 k Ω	0.1 W resistor	FEC 933-2391
R17	Resistor	10 k Ω	0.1 W resistor	FEC 933-2391
R18	Resistor	10 k Ω	0.1 W resistor	FEC 933-2391
S1	SW-SPDT-SLIDE		SPDT slide switch	FEC 112-3875
S2	SW-SPDT-SLIDE		SPDT slide switch	FEC 112-3875
T1	Test point		Test point	FEC 873-1144
T2	Test point		Test point	FEC 873-1144
T3	Test point		Test point	FEC 873-1144
T4	Test point		Test point	FEC 873-1144
T5	Test point		Test point	FEC 873-1144
T6	Test point		Test point	FEC 873-1144
T7	Test point		Test point	FEC 873-1144
U1	LDO regulator		High accuracy, low I_o , anyCAP® adjustable low dropout regulator in 8-lead MSOP	ADP3334ARMZ-REEL7
U2	LDO regulator		High accuracy, low I_o , anyCAP adjustable low dropout regulator in 8-lead MSOP	ADP3334ARMZ-REEL7
U3	LDO regulator		High accuracy, low I_o , anyCAP adjustable low dropout regulator in 8-lead MSOP	ADP3334ARMZ-REEL7
U4	Sequencer		Voltage Sequencer with Active Low, Open-Drain Enable Output in 6-lead SC70	ADM1087AKSZ-REEL7
U5	Sequencer		Voltage Sequencer with Active Low, Open-Drain Enable Output in 6-lead SC70	ADM1087AKSZ-REEL7

NOTES

NOTES

**ESD Caution**

ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

Legal Terms and Conditions

By using the evaluation board discussed herein (together with any tools, components documentation or support materials, the "Evaluation Board"), you are agreeing to be bound by the terms and conditions set forth below ("Agreement") unless you have purchased the Evaluation Board, in which case the Analog Devices Standard Terms and Conditions of Sale shall govern. Do not use the Evaluation Board until you have read and agreed to the Agreement. Your use of the Evaluation Board shall signify your acceptance of the Agreement. This Agreement is made by and between you ("Customer") and Analog Devices, Inc. ("ADI"), with its principal place of business at One Technology Way, Norwood, MA 02062, USA. Subject to the terms and conditions of the Agreement, ADI hereby grants to Customer a free, limited, personal, temporary, non-exclusive, non-sublicensable, non-transferable license to use the Evaluation Board FOR EVALUATION PURPOSES ONLY. Customer understands and agrees that the Evaluation Board is provided for the sole and exclusive purpose referenced above, and agrees not to use the Evaluation Board for any other purpose. Furthermore, the license granted is expressly made subject to the following additional limitations: Customer shall not (i) rent, lease, display, sell, transfer, assign, sublicense, or distribute the Evaluation Board; and (ii) permit any Third Party to access the Evaluation Board. As used herein, the term "Third Party" includes any entity other than ADI, Customer, their employees, affiliates and in-house consultants. The Evaluation Board is NOT sold to Customer; all rights not expressly granted herein, including ownership of the Evaluation Board, are reserved by ADI. **CONFIDENTIALITY.** This Agreement and the Evaluation Board shall all be considered the confidential and proprietary information of ADI. Customer may not disclose or transfer any portion of the Evaluation Board to any other party for any reason. Upon discontinuation of use of the Evaluation Board or termination of this Agreement, Customer agrees to promptly return the Evaluation Board to ADI. **ADDITIONAL RESTRICTIONS.** Customer may not disassemble, decompile or reverse engineer chips on the Evaluation Board. Customer shall inform ADI of any occurred damages or any modifications or alterations it makes to the Evaluation Board, including but not limited to soldering or any other activity that affects the material content of the Evaluation Board. Modifications to the Evaluation Board must comply with applicable law, including but not limited to the RoHS Directive. **TERMINATION.** ADI may terminate this Agreement at any time upon giving written notice to Customer. Customer agrees to return to ADI the Evaluation Board at that time. **LIMITATION OF LIABILITY.** THE EVALUATION BOARD PROVIDED HEREUNDER IS PROVIDED "AS IS" AND ADI MAKES NO WARRANTIES OR REPRESENTATIONS OF ANY KIND WITH RESPECT TO IT. ADI SPECIFICALLY DISCLAIMS ANY REPRESENTATIONS, ENDORSEMENTS, GUARANTEES, OR WARRANTIES, EXPRESS OR IMPLIED, RELATED TO THE EVALUATION BOARD INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTY OF MERCHANTABILITY, TITLE, FITNESS FOR A PARTICULAR PURPOSE OR NONINFRINGEMENT OF INTELLECTUAL PROPERTY RIGHTS. IN NO EVENT WILL ADI AND ITS LICENSORS BE LIABLE FOR ANY INCIDENTAL, SPECIAL, INDIRECT, OR CONSEQUENTIAL DAMAGES RESULTING FROM CUSTOMER'S POSSESSION OR USE OF THE EVALUATION BOARD, INCLUDING BUT NOT LIMITED TO LOST PROFITS, DELAY COSTS, LABOR COSTS OR LOSS OF GOODWILL. ADI'S TOTAL LIABILITY FROM ANY AND ALL CAUSES SHALL BE LIMITED TO THE AMOUNT OF ONE HUNDRED US DOLLARS (\$100.00). **EXPORT.** Customer agrees that it will not directly or indirectly export the Evaluation Board to another country, and that it will comply with all applicable United States federal laws and regulations relating to exports. **GOVERNING LAW.** This Agreement shall be governed by and construed in accordance with the substantive laws of the Commonwealth of Massachusetts (excluding conflict of law rules). Any legal action regarding this Agreement will be heard in the state or federal courts having jurisdiction in Suffolk County, Massachusetts, and Customer hereby submits to the personal jurisdiction and venue of such courts. The United Nations Convention on Contracts for the International Sale of Goods shall not apply to this Agreement and is expressly disclaimed.