

PLEASE CHECK WWW.MOLEX.COM FOR LATEST PART INFORMATION

**Part Number:** [03-09-6061](#)  
**Status:** **Active**  
**Overview:** [Standard .093" Pin and Socket Connectors](#)  
**Description:** 2.36mm Diameter Standard .093" Pin and Socket Receptacle Housing, 6 Circuits, Dual Row, Panel Mount, Black

**Documents:**  
[3D Model](#)  
[Drawing \(PDF\)](#)  
[Product Specification PS-02-09 \(PDF\)](#)  
[Product Specification PS-43660-9999 \(PDF\)](#)  
[Packaging Specification PK-1261-001 \(PDF\)](#)  
[RoHS Certificate of Compliance \(PDF\)](#)

**Agency Certification**

CSA LR19980  
UL E29179

**General**

Product Family Crimp Housings  
Series [1261](#)  
Application Power, Wire-to-Wire  
Comments 14.0A max. can be achieved when housing is used with 42477 or 42478 terminals  
Overview [Standard .093" Pin and Socket Connectors](#)  
Product Name Standard .093"  
UPC 800754232623

**Physical**

Circuits (maximum) 6  
Color - Resin Natural  
Flammability 94V-2  
Gender Receptacle  
Glow-Wire Compliant No  
Lock to Mating Part Yes  
Material - Resin Nylon  
Net Weight 3.109/g  
Number of Rows 2  
Packaging Type Bag  
Panel Mount Yes  
Pitch - Mating Interface 5.03mm  
Stackable No  
Temperature Range - Operating -40°C to +105°C

**Electrical**

Current - Maximum per Contact 11A

**Material Info**

Old Part Number 1261RBK

**Reference - Drawing Numbers**

Packaging Specification PK-1261-001  
Product Specification PS-02-09, PS-43660-9999  
Sales Drawing SD-1261-\*




image - Reference only

Series

**EU RoHS**  
**ELV and RoHS**  
**Compliant**  
**REACH SVHC**  
**Contains SVHC: No**  
**Low-Halogen Status**  
**Low-Halogen**

**China RoHS**



**Need more information on product environmental compliance?**  
Email [productcompliance@molex.com](mailto:productcompliance@molex.com)  
For a multiple part number RoHS Certificate of Compliance, [click here](#)  
Please visit the [Contact Us](#) section for any non-product compliance questions.

**Search Parts in this Series**  
[1261Series](#)

**Mates With**  
[03-09-2062](#) , [03-09-7062](#)

**Use With**  
[1189](#) Crimp Terminals, [1190](#) Crimp Terminals, [1380](#) Male Crimp Terminals, [1381](#) Female Crimp Terminals, [1433](#) Crimp Terminals, [1434](#) Male Crimp Terminals, [1973](#) , [2151](#) , [2273](#) , [2870](#) , [2871](#) , [4272](#) , [4550](#) , [6271](#)