

SPECIFICATION SHEET**JFW MODEL 50FHAO-XXX-100-4****FIXED ATTENUATOR**

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	DC-4000 MHz
Impedance	50 Ohms nominal
Attenuation Values	30 or 40 dB
VSWR	1.2:1 maximum DC-2000 MHz 1.4:1 maximum 2000-4000 MHz
Attenuation Accuracy	± 0.5 dB DC-2000 MHz ± 0.75 dB 2000-4000 MHz
RF Input Power	100 Watts average
Peak Power	1000 Watts
RF Connector	N or 4.3-10.0
Operating Temperature Range	-55°C to +100°C
Physical Size	See outline drawing 092-3164

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	09/05/2013		TRS 09/05/2013				
26007	12/14/2015	A	CLK 12/14/2015				