

Data sheet | Item number: 706-2400/202-100

System cable; for Siemens S7-400; 2x 8 digital outputs for higher voltages;
Length: 1 m; Conductor cross-section: 0.34 mm²

www.wago.com/706-2400/202-100



Picture differs from the item.

Data Notes

Note	If less than 3 channels used at the same time, the maximum current per wire 2 A and up to 5 A (amb. T 30 °C) or 3.5 A (amb. T 50 °C) on the power supply pins N/L. If more than 3 channels used at the same time, the maximum current per wire 0.75 A and up to 5 A (amb. T 30 °C) or 3.5 A (amb. T 50 °C) on the power supply pins N/L.
------	--

Electrical data

Inputs/outputs	2 x 8 digital outputs; for higher voltages
Operating voltage	≤ AC/DC 250 V
Current per wire (max.)	0.75 A

Connection data

Compatible PLC Modules	Siemens S7-400
Compatible PLC I/O Card Types	6ES7 422-1HH00-0AA0
Connection type (1)	System
Pole number 1	10
Pluggable connectors	WAGO 231 Series
Connection type 2	System
Pole number 2	10
Connector 2	WAGO 231 Series

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.



Connection type (3)	System
Pole number 3	10
Connector 3	WAGO 231 Series
Connection type (4)	System
Pole number (4)	10
Connector 4	WAGO 231 Series
Anschlussstyp 5	System
Pole number (5)	48
Connector 5	Siemens 6ES7-492-1BL00-0AA0
Cable type	LiYY
Wire cross-section	0.34 mm ²
Color code	per DIN VDE 47100

Physical data

Cable length	1 m
--------------	-----

Material data

Weight	717 g
--------	-------

Environmental requirements

Surrounding air temperature (operation)	-20 ... 50 °C
---	---------------

Commercial data

PU (SPU)	1 Stück
Packaging type	bag
Country of origin	FR
GTIN	4055143979856
Customs tariff number	85444290900

Downloads

Documentation

System Description

WAGO System Wiring, Selection Guide

This guide will help you select the appropriate interface modules and system cables for the controller you are using.

pdf
545.9 kB
[Download](#)

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.



Environmental Product Compliance

Compliance Search

Environmental Product Compliance 706-2400/202-100

URL

Download

System cable; for Siemens S7-400; 2x 8 digital outputs for higher voltages; Length: 1 m; Conductor cross-section: 0.34 mm²

Installation Notes

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG

Hansastr. 27

32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169

Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.