

TL-3/4 Bi-Pin Base (.050") Lens End




Part Number	Design Voltage	Amps	Spot Characteristic	Life Hours	Filament Type
CM7909	5.0	.12	None	40,000	C-2R
CM7910	5.0	.06	None	25,000	C-2R

TL-1 Wire Terminal Lens End




Part Number	Design Voltage	Amps	Spot Characteristic	Life Hours	Filament Type
CM1284	1.5	.08	None	16,000	C-2R
CM1415	5.0	.12	None	40,000	C-2R
CM1283	5.0	.06	None	25,000	C-2R
CM1413	5.0	.08	None	25,000	C-2R

TL-1 Sub-Midget Flange Base Lens End



Part Number	Design Voltage	Amps	Spot Characteristic	Life Hours	Filament Type
CM8-1285	1.5	.08	None	16,000	C-2R
CM3905	5.0	.06	None	25,000	C-2R
CM3906	5.0	.08	None	16,000	C-2R
CM8-1418	5.0	.12	None	4,000	C-2R

TL-1 Bi-Pin Base (.050") Lens End



Part Number	Design Voltage	Amps	Spot Characteristic	Life Hours	Filament Type
CM7908	1.5	.08	None	16,000	C-2R
CM7905	5.0	.06	None	25,000	C-2R
CM7906	5.0	.08	None	16,000	C-2R
CM7907	5.0	.12	None	40,000	C-2R

CML and Chicago Miniature Lamp are registered trademarks of Visual Communications Company, LLC.