PASTERNACK®
www.pasternack.com



# 75 Watts High Power WR-28 RF Load 26.5 GHz to 40 GHz

## TECHNICAL DATA SHEET PE6200

**75 Watts High Power WR-28 RF Load 26.5 GHz to 40 GHz**

### Configuration

| | |
|---|---|
| Connector | WR-28 |
| Heat Sink | Aluminum |
| Body Style | Straight |

### Electrical Specifications

| | |
|---|---|
| Frequency Range, GHz | 26.5 to 40 |
| Impedance, Ohms | 50 |
| Maximum VSWR | 1.25:1 |
| Maximum Input Power, Watts | 75 |

### Mechanical Specifications

**Size**

| | |
|---|---|
| Length, in [mm] | 4 [101.6] |
| Width/Dia., in [mm] | 1.5 [38.1] |
| Height, in [mm] | 0.9 [22.86] |
| Color | Black |

**Connector**

| | |
|---|---|
| Type | WR-28 |

### Compliance Certifications (visit www.Pasternack.com for current document)

| | |
|---|---|
| RoHS Compliant | Yes |

### Plotted and Other Data

| | |
|---|---|
| Notes: | Values at 25 °C, sea level |

75 Watts High Power WR-28 RF Load 26.5 GHz to 40 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in “SEARCH” on website) to obtain additional part information including price, inventory and certifications: 75 Watts High Power WR-28 RF Load 26.5 GHz to 40 GHz PE6200

URL: http://www.pasternack.com/75-watts-wr-28-rf-load-26.5-40-ghz-pe6200-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.


Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623
**Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451
Sales@Pasternack.com • Techsupport@Pasternack.com

ISO 9001 : 2008 Registered

© 2013 Pasternack Enterprises All Rights Reserved

# PE6200 CAD Drawing

75 Watts High Power WR-28 RF Load 26.5 GHz to 40 GHz




NOTES:
1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
3. DIMENSIONS ARE IN INCHES [mm].

| CAD FILE | 062113 | SCALE N/A | SIZE A | 2233 |
|---|---|---|---|---|

DWG TITLE **PE6200**

**FSCM NO. 53919**


PASTERNACK®
Pasternack Enterprises, Inc.
P.O. Box 16759 | Irvine | CA | 92623
**Phone:** (949) 261-1920 | **Fax:** (949) 261-7451
**Website:** www.pasternack.com | **E-Mail:** sales@pasternack.com


© 2013 Pasternack Enterprises All Rights Reserved