

Data sheet | Item number: 706-2500/603-100

System cable; for Siemens S7-1500; 4 analog inputs and 2 analog outputs, voltage; Length: 1 m; Conductor cross-section: 0.25 mm²



www.wago.com/706-2500/603-100



Data Notes

Note	When using more than 10 wires, the maximum current per wire must be reduced to 1 A.
------	---

Electrical data

Inputs/outputs	4 analog inputs and 2 analog outputs; voltage
Operating voltage	≤ AC/DC 35 V
Current per wire (max.)	2 A

Connection data

Compatible PLC Modules	Siemens S7-1500
Compatible PLC I/O Card Types	6ES7 534-7QE00-0AB0
Connection type (1)	System
Pole number 1	25
Pluggable connectors	D-sub female connector
Connection type 2	System
Pole number 2	40
Connector 2	Siemens 6ES7-592-1AM00-0XB0
Cable type	LIYCY
Wire cross-section	0.25 mm ²
Color code	per DIN VDE 47100

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.



Physical data

Cable length	1 m
--------------	-----

Material data

Weight	398 g
--------	-------

Environmental requirements

Surrounding air temperature (operation)	-20 ... 50 °C
---	---------------

Commercial data

PU (SPU)	1 Stück
----------	---------

Packaging type	bag
----------------	-----

GTIN	4055143595551
------	---------------

Downloads

Documentation

System Description

WAGO System Wiring, Selection Guide

This guide will help you select the appropriate interface modules and system cables for the controller you are using.

pdf
545.9 kB

[Download](#)

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 706-2500/603-100

System cable; for Siemens S7-1500; 4 analog inputs and 2 analog outputs, voltage; Length: 1 m; Conductor cross-section: 0.25 mm²

[URL](#)

[Download](#)

Installation Notes

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG

Hansastr. 27

32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169

Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.