

SPECIFICATION SHEET

JFW MODEL 50PD-647

8 WAY REACTIVE POWER DIVIDER/COMBINER

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	2-6 GHz
Impedance	50 Ohms nominal
VSWR	1.6:1 maximum < 1.4:1 typical
Insertion Loss (above 9 dB split)	1.9 dB maximum 0.5 dB typical @ 2 GHz 1.1 dB typical @ 6 GHz
Amplitude Tracking	± 0.8 dB
Phase Tracking	± 9°
Isolation	18 dB minimum
Matched Input Power	5 Watts average (divider) 0.5 Watts average (combiner)
Operating Temperature Range	-40°C to +85°C
RF Connector	SMA female
Physical Size	See outline drawing 092-5373

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	03/23/2007		TRS 03/23/2007				
14386	07/11/2007	A	TRS 07/11/2007				
14415	07/18/2007	B	TRS 07/18/2007				