



## Features:

- · Protections:Short circuit/Over load/Over voltage
- · Cooling by free air convection
- · LED indicator for power on
- 100% full load burn-in test
- All using 105  $^{\circ}$  long life electrolytic capacitors
- Withstand 300VAC surge input for 5 second
- High operating temperature up to 70℃
- · Withstand 5G vibration test
- High efficiency, long life and high reliability
- 3 years warranty

## **SPECIFICATION**



MODEL		RT-125A			RT-125B			RT-125C			RT-125D			
	OUTPUT NUMBER	CH1	CH2	CH3	CH1	CH2	CH3	CH1	CH2	CH3	CH1	CH2	CH3	
ОИТРИТ	DC VOLTAGE	5V	12V	-5V	5V	12V	-12V	5V	15V	-15V	5V	24V	12V	
	RATED CURRENT	12A	5.5A	1A	12A	5A	1A	10A	4.5A	1A	8A	3A	2A	
	CURRENT RANGE Note.6	2 ~ 15A	0.5 ~ 6A	0.1 ~ 1A	2 ~ 15A	0.5 ~ 6A	0.1 ~ 1A	2 ~ 15A	0.5 ~ 6A	0.1 ~ 1A	2 ~ 15A	0.4 ~ 4A	0.1 ~ 2A	
	RATED POWER Note.6	131W		132W		132.5W			136W					
	RIPPLE & NOISE (max.) Note.2	80mVp-p   120mVp-p   80mVp-p		80mVp-p 120mVp-p 120mVp-p		80mVp-p   150mVp-p   150mVp-p			80mVp-p 150mVp-p 120mVp-					
	VOLTAGE ADJ. RANGE	CH1: 4.75 ~ 5.5V			CH1: 4.75	5~5.5V	5.5V		CH1: 4.75 ~ 5.5V		CH1: 4.75 ~ 5.5V			
	VOLTAGE TOLERANCE Note.3	±2.0%	+8,-3%	+6,-10%	±2.0%	+8,-3%	±6.0%	±2.0%	+8,-3%	±6.0%	±2.0%	±5.0%	±6.0%	
	LINE REGULATION Note.4	±0.5%	±1.0%	±1.0%	±0.5%	±1.0%	±1.0%	±0.5%	±1.0%	±1.0%	±0.5%	±1.0%	±1.0%	
	LOAD REGULATION Note.5	±1.0%	±3.0%	±6.0%	±1.0%	±3.0%	±6.0%	±1.0%	±3.0%	±6.0%	±1.0%	±3.0%	±6.0%	
	SETUP, RISE TIME	500ms, 20	00ms, 20ms/230VAC 1200ms, 30ms/115VAC at full load											
	HOLD TIME (Typ.)	36ms/230	VAC :	30ms/115V	AC at full load									
INPUT	VOLTAGE RANGE	88 ~ 132VAC / 176 ~ 264VAC selected by switch 248 ~ 373VDC(Withstand 300VAC surge for 5sec. Without decrease of the control of									hout damag	je)		
	FREQUENCY RANGE	47 ~ 63Hz	47 ~ 63Hz											
	EFFICIENCY(Typ.)	79%			80%			81%			82%			
	AC CURRENT (Typ.)	3A/115VA	AC 2A	/230VAC										
	INRUSH CURRENT (Typ.)	COLD START 40A/230VAC												
	LEAKAGE CURRENT	<2mA / 240VAC												
PROTECTION		110 ~ 150% rated output power												
	OVER LOAD	Protection type: Hiccup mode, recovers automatically after fault condition is removed												
	OVER VOLTAGE	CH1: 5.75 ~ 6.75V												
	OVER VOLTAGE	Protection type: Hiccup mode, recovers automatically after fault condition is removed												
ENVIRONMENT	WORKING TEMP.	-25 ~ +70	°C (Refer to	o output loa	d derating curve)									
	WORKING HUMIDITY	20 ~ 90%	20 ~ 90% RH non-condensing											
	STORAGE TEMP., HUMIDITY	-40 ~ +85	°C, 10 ~ 95	% RH										
	TEMP. COEFFICIENT	±0.03%/°	±0.03%/°C (0 ~ 50°C)on +5V output											
	VIBRATION	10 ~ 500H	10 ~ 500Hz, 5G 10min./1cycle, period for 60min. each along X, Y, Z axes											
SAFETY & EMC (Note 7)	SAFETY STANDARDS	UL60950-1, TUV EN60950-1 Approved												
	WITHSTAND VOLTAGE	I/P-O/P:3KVAC I/P-FG:1.5KVAC O/P-FG:0.5KVAC												
	ISOLATION RESISTANCE	I/P-O/P, I/P-FG, O/P-FG:100M Ohms/500VDC												
	EMI CONDUCTION & RADIATION	Compliance to EN55022 (CISPR22) Class B												
	HARMONIC CURRENT	Compliance to EN61000-3-2,-3												
	EMS IMMUNITY	Complian	Compliance to EN61000-4-2,3,4,5,6,8,11; ENV50204, EN61000-6-2 (EN50082-2) heavy industry level, criteria A											
OTHERS	MTBF		209.3Khrs min. MIL-HDBK-217F (25℃)											
	DIMENSION		199*98*38mm (L*W*H)											
	PACKING		0.7Kg; 20pcs/14Kg/0.8CUFT											
NOTE	Ripple & noise are measure     Tolerance : includes set up     Line regulation is measured	ameters NOT specially mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature.  & noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor.  nce: includes set up tolerance, line regulation and load regulation.  egulation is measured from low line to high line at rated load.  equilation is measured from 20% to 100% rated load, and other output at 60% rated load.												

- Load regulation is measured from 20% to 100% rated load, and other output at 60% rated load.
- 6. Each output can work within current range. But total output power can't exceed rated output power.
- 7. The power supply is considered a component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets
- 8. Length of set up time is measured at cold first start. Turning ON/OFF the power supply very quickly may lead to increase of the set up time.



