Product data sheet
Characteristics

HU361RBGL
SW NOT FUSIBLE HD 30A NEMA3R/ GROUND LUG

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Product	Single Throw Safety Switch
Line Rated Current	30 A
Certifications	UL listed file E2875
Enclosure Rating	NEMA 3R galvannealed steel
Factory Installed Neutral	None
Disconnect Type	Non-fusible disconnect
Mounting Type	Surface
Number of Poles	3
Duty Rating	Heavy duty
System Voltage	600 V AC/DC
Wire Size	AWG 14...AWG 6 (copper) AWG 12...AWG 6 (aluminium)
Wire Size	4.86 in

Complementary

Width	7.55 in
Height	14.88 in
Tightening torque	40 lbf.in for 8.367 mm² (AWG 8) 35 lbf.in for 2.06...5.261 mm² (AWG 14...AWG 10) 45 lbf.in for 13.3 mm² (AWG 6)

Ordering and shipping details

Category	00160 - DE1 MISC
Discount Schedule	DE1
GTIN	00785901693505
Nbr. of units in pkg.	1
Package weight(Lbs)	11
Returnability	N
Country of origin	US

Offer Sustainability

Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 1313 - Schneider Electric declaration of conformity Schneider Electric declaration of conformity
REACh	Reference not containing SVHC above the threshold
Product environmental profile	Available
Product end of life instructions	Need no specific recycling operations
California proposition 65	WARNING: This product can expose you to chemicals including:
- - - - - - - Substance 1	Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
- - - - - - - More information	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein.
This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications.
It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof.
Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.