

Data sheet | Item number: 706-2500/501-100

System cable; for Siemens S7-1500; 4 analog outputs (voltage); Length: 1 m;
Conductor cross-section: 0.25 mm²



www.wago.com/706-2500/501-100



Data Notes

Note	When using more than 10 wires, the maximum current per wire must be reduced to 1 A.
------	---

Electrical data

Inputs/outputs	4 analog outputs; voltage
Operating voltage	≤ AC/DC 35 V
Current per wire (max.)	2 A

Connection data

Compatible PLC Modules	Siemens S7-1500
Compatible PLC I/O Card Types	6ES7 532-5HD00-0AB0 6ES7 532-5ND00-0AB0
Connection type (1)	System
Pole number 1	15
Pluggable connectors	D-sub female connector
Connection type 2	System
Pole number 2	40
Connector 2	Siemens 6ES7-592-1BM00-0XB0
Cable type	LIYCY
Wire cross-section	0.25 mm ²

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.



Color code	per DIN VDE 47100
------------	-------------------

Physical data

Cable length	1 m
--------------	-----

Material data

Weight	274 g
--------	-------

Environmental requirements

Surrounding air temperature (operation)	-20 ... 50 °C
---	---------------

Commercial data

PU (SPU)	1 Stück
Packaging type	bag
Country of origin	FR
GTIN	4055143979924
Customs tariff number	85444290900

Downloads**Documentation****System Description**

WAGO System Wiring, Selection Guide This guide will help you select the appropriate interface modules and system cables for the controller you are using.	pdf 545.9 kB	Download
--	-----------------	----------

Environmental Product Compliance**Compliance Search**

Environmental Product Compliance 706-2500/501-100 System cable; for Siemens S7-1500; 4 analog outputs (voltage); Length: 1 m; Conductor cross-section: 0.25 mm ²	URL	Download
---	-----	----------

Installation Notes

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.