

Replacement - Tube Guitar Power (290 Series)



TUBE GUITAR AMPLIFIER - POWER TRANSFORMERS

- Designed for drop in replacement of original tube guitar amplifier power supply transformers.
- Physically, parts were designed to look similar to original factory units (where possible).
- For individual photos of each part - visit our website: www.hammondmfg.com

| Part No. | Primary | Amplifier Manufacturer | Amplifier Model Names | Equivalent To Mfg's Part Number |
|-------------------------------|----------------------------------|------------------------|---|---------------------------------|
| 290AX 290AEX | 120VAC 60 Hz. 240VAC 50 Hz. | Fender | Champ, Vibro Champ, Princeton, Princeton Reverb, Tweed Deluxe | 125P1B & 022772 |
| 290BX 290BEX | 120VAC 60 Hz. 240VAC 50 Hz. | Fender | Deluxe, Deluxe Reverb | 125P23D & 041316 |
| 290CX 290CEX | 120VAC 60 Hz. 240VAC 50 Hz. | Fender | Vibrolux, Vibrolux Reverb, Tremolux | 125P26A & 022723 |
| 290DX 290DEX | 120VAC 60 Hz. 240VAC 50 Hz. | Fender | Super Reverb, Pro Reverb, Bandmaster Reverb, Tweed Bassman | 125P5D & 022798 |
| 290EX 290EEX | 120VAC 60 Hz. 240VAC 50 Hz. | Fender | Bassman, Concert, Pro | 125P7D & 022814 |
| 290FX 290FEX | 120VAC 60 Hz. 240VAC 50 Hz. | Fender | Twin Reverb, Dual Showman, Bassman 100 | 125P34A & 022756 |
| 290GX | 120/220/240VAC 50/60 Hz. | Marshall | JCM 800, JMP - 50 Watt | - |
| 290HX | 120/220/240VAC 50/60 Hz. | Marshall | JCM 800, JMP - 100 Watt | - |
| 290KX | 120/240VAC 50/60 Hz. | Marshall | JCM 900 - 50 Watt | - |
| 290JX | 120/240VAC 50/60 Hz. | Marshall | JCM 900 - 100 Watt | - |
| 290LX | 120/240VAC 50/60 Hz. | Marshall | JTM 45 | - |
| 290PX | 120/240VAC 50/60 Hz. | VOX | AC15 | - |
| 290NX | 100/120/220/230/240VAC 50/60 Hz. | VOX | AC30 Vintage | - |
| 290MX | 120/240VAC 50/60 Hz. | VOX | AC30 Reissue | - |

DISCLAIMER: Hammond Mfg. is not affiliated with Fender Musical Instruments Corp., Marshall Amplification, Yorkville/Traynor or VOX Amplification companies. Amplifier model names Bandmaster Reverb, Bassman, Bassman 100, Champ, Vibro Champ, Concert, Deluxe, Deluxe Reverb, Dual Showman, Princeton, Princeton Reverb, Pro, Pro Reverb, Super Reverb, Tremolux, Tweed Bassman, Tweed Deluxe, Twin Reverb, Vibrolux & Vibrolux Reverb are all trademarks of Fender Musical Instruments Corp.

Guitar Amp

EUROPE

Basingstoke, UK 01256 812812

AUSTRALIA

Queenstown, Australia 61-8-8240-2244

www.hammondmfg.com



CANADA

Guelph, Ontario (519) 822-2960
St. Laurent, Quebec (514) 343-9010

USA

Cheektowaga, NY (716) 630-7030



Replacement - Tube Guitar Chokes (194 Series)



TUBE GUITAR AMPLIFIER - POWER TRANSFORMERS

- Designed for drop in replacement of original tube guitar amplifier power supply chokes.
- Physically, parts were designed to look similar to original factory units (where possible).
- For individual photos of each part - visit our website: www.hammondmfg.com

| Part No. | Inductance (Henrys) | Amplifier Manufacturer | Amplifier Model Names | Equivalent To Mfg's Part Number |
|-------------|---------------------|------------------------|--|---------------------------------|
| 194A | 4 | Fender | Deluxe, Deluxe Reverb, Vibrolux, Vibrolux Reverb | 125C3A & 022707 |
| 194B | 4 | Fender | Bandmaster, Dual Showman, Pro Reverb, Twin Super | 125C1A & 022699 |
| 194C | 40 | Marshall | JCM 800 | - |
| 194D | 5 | VOX | AC30 reissue | - |
| 194E | 30 | VOX | AC30 vintage | - |

DISCLAIMER: Hammond Mfg. is not affiliated with Fender Musical Instruments Corp., Marshall Amplification or VOX Amplification companies. Amplifier model names Bandmaster, Deluxe, Deluxe Reverb, Dual Showman, Pro Reverb, Twin Super, Vibrolux & Vibrolux Reverb are all trademarks of Fender Musical Instruments Corp.

Guitar Amp



CANADA

Guelph, Ontario (519) 822-2960
St. Laurent, Quebec (514) 343-9010

USA

Cheektowaga, NY (716) 630-7030

www.hammondmfg.com



EUROPE

Basingstoke, UK 01256 812812

AUSTRALIA

Queenstown, Australia 61-8-8240-2244