

## Data sheet | Item number: 706-3033/600-300

System cable; for Schneider Modicon TM3; 6 analog inputs or outputs;  
Length: 3 m; Conductor cross-section: 0.25 mm<sup>2</sup>



[www.wago.com/706-3033/600-300](http://www.wago.com/706-3033/600-300)



### Data Notes

Note	When using more than 10 wires, the maximum current per wire must be reduced to 1 A.
------	---

### Electrical data

Inputs/outputs	6 analog inputs or outputs
Operating voltage	≤ AC/DC 35 V
Current per wire (max.)	2 A

### Connection data

Compatible PLC Modules	Schneider Modicon TM3
Compatible PLC I/O Card Types	TM3 AM6(G)
Connection type (1)	System
Pole number 1	25
Pluggable connectors	D-sub female connector
Connection type 2	System
Pole number 2	20
Connector 2	TM3 AM6(G)
Cable type	LiYCY
Wire cross-section	0.25 mm <sup>2</sup>

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG  
Hansastr. 27  
32423 Minden  
Phone: +49571 887-0 | Fax: +49571 887-169  
Email: [info.de@wago.com](mailto:info.de@wago.com) | Web: [www.wago.com](http://www.wago.com)

Do you have any questions about our products?  
We are always happy to take your call at +49 (571) 887-44222.



Color code per DIN VDE 47100

---

### Physical data

Cable length 3 m

---

### Material data

Weight 410 g

---

### Environmental requirements

Surrounding air temperature (operation) -20 ... 50 °C

---

### Commercial data

PU (SPU) 1 Stück

---

Packaging type bag

---

GTIN 4055143257626

---

Customs tariff number 85444290900

---

### Downloads

#### Documentation

##### System Description

WAGO System Wiring, Selection Guide

pdf Download  
545.9 kB

This guide will help you select the appropriate interface modules and system cables for the controller you are using.

---

### Environmental Product Compliance

#### Compliance Search

Environmental Product Compliance 706-3033/600-300

URL Download

System cable; for Schneider Modicon TM3; 6 analog inputs or outputs; Length: 3 m; Conductor cross-section: 0.25 mm<sup>2</sup>

---

### Installation Notes

Subject to changes. Please also observe the further product documentation!

---

WAGO GmbH & Co. KG

Hansastr. 27

32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169

Email: [info.de@wago.com](mailto:info.de@wago.com) | Web: [www.wago.com](http://www.wago.com)

Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.