

**SPECIFICATION SHEET**  
**JFW MODEL 50PD-134**  
**3 WAY RESISTIVE POWER DIVIDER**

JFW Industries, Inc.  
 Phone: 317-887-1340  
 sales@jfwindustries.com  
 www.jfwindustries.com

Frequency Range	DC-2000 MHz
Impedance	50 Ohms nominal
VSWR	1.2:1 maximum to 500 MHz 1.3:1 maximum to 1000 MHz 1.4:1 maximum to 2000 MHz
Insertion Loss	9.5 dB ± 0.5 dB
Amplitude Tracking	± 0.4 dB
RF Input Power	2 Watts average @ 25°C 100 Watts peak (1 microsecond)
Operating Temperature Range	-40°C to +85°C
RF Connector	N or BNC female
Physical Size	See outline drawing 092-2328 (N)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	06/15/1995			9999	11/17/2002	C	SL 11/27/2002
866	10/28/1997	A					
961	02/05/1998	B					