## Product data sheet Characteristics

# 70S2-05-C-10-M

Relay, SE Relays, solid state, SPST, 10A, 24... 280VAC, 6...30/32VDC Uc, triac, printed circuit board or panel, solder term



#### Main

TTIONIT		<u> </u>
Range	Legacy	i g
Product Type	Solid state relay	
Maximum output current	10 A AC	
Mounting Support	Printed circuit boards Panel mounting	
Network Number of Phases	1 phase	
Output Voltage	24280 V AC	±

### Complementary

Holding Current	50 mA
Input Current Limits	610 mA at 630 V DC typical
Switch Function	SPST
Contacts Type and Composition	NO
Protection Type	Reverse polarity 3 V DC control
Connections Terminals	solder terminal
Switching Voltage	1 V DC tripping
Switching Device	Triac output Zero voltage switching
Maximum Peak Voltage	600 V
Surge Current	110 A 1 cycle 32 A 60 cycles
Must Release Voltage	1 V
Voltage Drop	<1.6 V on-state AC
Thermal Resistance	3.3 °C/W
Leakage Current	6 mA at off-state
DV/Dt	300 V/ms off-state at maximum rated voltage
Response Time	8.33 ms (turn-on, turn-off)
Dielectric Strength	3000 V between input and output 3000 V between terminals and chassis
Height	0.88 in (22.25 mm)

Width	1.03 in (26.2 mm)	
Depth	1.23 in (31.2 mm)	
Product Weight	1.23 oz (35 g)	
Environment		
Product Certifications	UL Recognized CSA CE	
Ambient Air Temperature for Operation	-40185 °F (-4085 °C)	
Ambient Air Temperature for Storage	-40257 °F (-40125 °C)	
Ordering and shipping details GTIN	03606481107558	
Offer Sustainability		
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov	
REACh Regulation	REACh Declaration	
REACh free of SVHC	Yes	
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) EU RoHS Declaration	
Mercury free	Yes	
RoHS exemption information	Yes	
China RoHS Regulation	China RoHS declaration	
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.	

### Connections and Wiring Diagrams

