

# BGSA143GL10

## Low Resistance Antenna Tuning Switch

### Features

- Designed for high-linearity antenna tuning switching and RF tuning applications
- Ultra low  $R_{ON}$  resistance of  $1.15 \Omega$  at each port in ON state
- Low  $C_{OFF}$  capacitance of 140 fF at each port in OFF state
- High RF operating peak voltage handling of 42 V in OFF state
- Resonance-Stopper Antenna Tuning
- Low harmonic generation
- 3 GPIO pins control interface
- No RF parameter change within supply voltage range
- Small form factor  $1.1 \times 1.5 \text{ mm}^2$  (MSL1, 260°C per JEDEC J-STD-020)
- RoHS and WEEE compliant package




### Description

BGSA143GL10 is a small and versatile Single-Pole Quad Throw (SP4T) RF switch optimized for low  $C_{OFF}$  as well as low  $R_{ON}$  enabling applications up to 6.0GHz. GPIO digital control lines offer the possibility to adopt SP4T, SPDT along with SPST topology for an optimum flexibility in RF Front-end designs.

BGSA143GL10 is ideal for high Q tuning applications. This single supply chip integrates on-chip CMOS logic control. It can be driven by 2 or 3 CMOS or TTL compatible control input signals. Due to its high RF voltage ruggedness and OFF RF ports reflective short feature, it is suited for switching any reactive devices such as inductors and capacitors in RF matching circuits without significant losses, also mitigating or even eradicating unwanted parasitic RF resonances.

**Block diagram and ordering information**



**Figure 1** BGSA143GL10 Block diagram

**Table 1** Ordering Information

Type	Package	Marking
BGSA143GL10	TSLP-10	AB



WEEE Compliant Package



Halogen-Free PB Free



RoHS

**Trademarks**

All referenced product or service names and trademarks are the property of their respective owners.

**Edition 2019-10-16**  
**Published by**  
**Infineon Technologies AG**  
**81726 München, Germany**

© 2019 Infineon Technologies AG.  
 All Rights Reserved.

**Do you have a question about this document?**  
**Email: [erratum@infineon.com](mailto:erratum@infineon.com)**

**Document reference**  
**ifx1**

**IMPORTANT NOTICE**

The information given in this document shall in no event be regarded as a guarantee of conditions or characteristics ("Beschaffenheitsgarantie").

With respect to any examples, hints or any typical values stated herein and/or any information regarding the application of the product, Infineon Technologies hereby disclaims any and all warranties and liabilities of any kind, including without limitation warranties of non-infringement of intellectual property rights of any third party.

In addition, any information given in this document is subject to customer's compliance with its obligations stated in this document and any applicable legal requirements, norms and standards concerning customer's products and any use of the product of Infineon Technologies in customer's applications.

The data contained in this document is exclusively intended for technically trained staff. It is the responsibility of customer's technical departments to evaluate the suitability of the product for the intended application and the completeness of the product information given in this document with respect to such application.

For further information on the product, technology, delivery terms and conditions and prices please contact your nearest Infineon Technologies office ([www.infineon.com](http://www.infineon.com)).

**WARNINGS**

Due to technical requirements products may contain dangerous substances. For information on the types in question please contact your nearest Infineon Technologies office.

Except as otherwise explicitly approved by Infineon Technologies in a written document signed by authorized representatives of Infineon Technologies, Infineon Technologies' products may not be used in any applications where a failure of the product or any consequences of the use thereof can reasonably be expected to result in personal injury.