## CC-DEVPACK-DEBUG Revision 1.3.0

	Quantity Part Reference	Value	Description	Manufacturer
02-03063	5 C1 C2 C3 C12 C15	10nF	CAPACITOR, CERAMIC X7R, 10nF, 25V, -10%/+10%, -55DEGC/+125DEGC, 0402, SMD	MANUFACTURER
02-03049	4 C4 C5 C16 C20	100nF	CAPACITOR, CERAMIC X7R, 100nF, 10V, -10%/+10%, -55DEGC/+125DEGC, 0402, SMD	MANUFACTURER
02-03066	3 C6 C8 C11	1uF	CAPACITOR, CERAMIC X5R, 1uF, 10V, -10%/+10%, -55DEGC/+85DEGC, 0402, SMD	MANUFACTURER
2-04475	2 C7 C10	0.1uF	CAPACITOR, CERAMIC X5R, 0.1uF, 10V, -15%/+15%, -55DEGC/+85DEGC, 0402, SMD	MURATA
2-04476	3 C9 C17 C19	2.2uF	CAPACITOR, CERAMIC X5R, 2.2uF, 6.3V, -10%/+10%, -55DEGC/+85DEGC, 0402, SMD	MURATA
02-03030	2 C13 C14	12pF	CAPACITOR, CERAMIC COG/NP0, 12pF, 50V, -5%/+5%, -55DEGC/+125DEGC, 0402, SMD	MANUFACTURER
2-06059	1 C18	15pF	CAPACITOR, CERAMIC, 15pF, 50V, -5%/+5%, -55DEGC/+125DEGC, 0201, SMD	MURATA
15-01169	1 CR1	LS L296-P2Q2-1	OPTO, LED, SUPER RED COLOR, 630nm, 1.8V TO 2.3V, 0.06A, 0603, SMD	OSRAM
15-01023	1 CR2	LPL296-J2L2-25	OPTO, LED, GREEN COLOR, 562nm, 0.02A, 0.08W, 0603, SMD	OSRAM
14-06172	1 CR3	TPD4E004DRY	DIODE, PROTECTION, ESD ARRAY, 4 CHANNEL, 6V TO 8V, -40DEGC/+85DEGC, SON6, SMD	TEXAS INSTRUME
19-00300	6 FIDU1 FIDU2 FIDU3 FIDU4 FIDU5 FIDU6	FIDU_1.27mm	FIDUCIAL MARK, ROUND 1.27MM	
06-03032	2 J1 J4	LSS-110-01-F-DV-A-TR	CONNECTOR, HEADER, HI-SPEED SOCKET, FEMALE, STRAIGHT, 2 ROWS,20 PINS, PITCH 0.635mm, SMD	SAMTEC
06-03704	1 J2	BB02-CN102-KB8-000000	CONNECTOR, B2B, FEMALE, STRAIGHT, 2 ROWS, 10 PINS, PITCH 1.27mm, PTH	GRADCONN
06-03288	1 J3	47491-0001	CONNECTOR, MICRO-USB, 1 ROW, 5 PINS, PITCH 0.65mm, SMD	MOLEX
19-00452	1 P1	TC2050-IDC-NL	NON COMPONENT, CONNECTOR CABLE, PLUG OF NAILS, 10 PINS, 2 ROWS, SMD	
06-02153	1 P2	DNM	CONNECTOR, HEADER, MALE, STRAIGHT, 2 ROWS, 20 PINS, PITCH 1.27mm, PTH	SAMTEC
06-04790	3 P3 P4 P5	DNM	CONNECTOR, HEADER, MALE, RIGHT ANGLE, 1 ROW, 4 PINS, PITCH 2mm, SMD	SHENZHEN NS-TE
1-12937	1 R1	750k	RESISTOR, THICK FILM, 750k, -1%/+1%, 0.063W, 50V, -55DEGC/+155DEGC, 0402, SMD	MANUFACTURER
1-11629	1 R2	51	RESISTOR, THICK FILM, 51, -5%/+5%, 0.063W, 50V, -55DEGC/+155DEGC, 0402, SMD	MANUFACTURER
01-11684	1 R3	10k	RESISTOR, THICK FILM, 10k, -5%/+5%, 0.063W, 50V, -55DEGC/+155DEGC, 0402, SMD	MANUFACTURER
01-11660	5 R4 R10 R11 R12 R17	1k	RESISTOR, THICK FILM, 1k, -5%/+5%, 0.063W, 50V, -55DEGC/+155DEGC, 0402, SMD	MANUFACTURER
01-12780	1 R6	33k	RESISTOR, THICK FILM, 33k, -1%/+1%, 0.063W, 50V, -55DEGC/+155DEGC, 0402, SMD	MANUFACTURER
1-11587	1 R7	DNM	RESISTOR, DO NOT MOUNT, 0402, SMD	MANUFACTURER
1-11656	1 R8	680	RESISTOR, THICK FILM, 680, -5%/+5%, 0.063W, 50V, -55DEGC/+155DEGC, 0402, SMD	MANUFACTURER
01-12503	1 R9	120	RESISTOR, THICK FILM, 120, -1%/+1%, 0.063W, 50V, -55DEGC/+155DEGC, 0402, SMD	MANUFACTURER
1-12894	1 R13	330k	RESISTOR, THICK FILM, 330k, -1%/+1%, 0.063W, 50V, -55DEGC/+155DEGC, 0402, SMD	MANUFACTURER
01-12873	1 R14	220k	RESISTOR, THICK FILM, 220k, -1%/+1%, 0.063W, 50V, -55DEGC/+155DEGC, 0402, SMD	MANUFACTURER
1-12495	1 R15	100	RESISTOR, THICK FILM, 100, -1%/+1%, 0.063W, 50V, -55DEGC/+155DEGC, 0402, SMD	MANUFACTURER
1-02472	1 R16	DNM	RESISTOR, DO NOT MOUNT, 0402, SMD	DO NOT MOUNT
01-12687	1 R18	4.87k	RESISTOR, THICK FILM, 4.87k, -1%/+1%, 0.063W, 50V, -55DEGC/+155DEGC, 0402, SMD	MANUFACTURER
01-16574	1 R19	0	RESISTOR, JUMPER, 3 PORTS, -55DEGC/+155DEGC, 0402, SMD	KOA SPEER
01-04213	1 R20	51k	RESISTOR, THICK FILM, 51K, -5%/+5%, 0.05W, 30V, -55DEGC/+155DEGC, 0201, SMD	VISHAY
01-03904	1 R21	30.1k	RESISTOR, THICK FILM, 30K1, -1%/+1%, 0.05W, 30V, -55DEGC/+155DEGC, 0201, SMD	VISHAY
01-11636	1 R22	100	RESISTOR, THICK FILM, 100, -5%/+5%, 0.063W, 50V, -55DEGC/+155DEGC, 0402, SMD	MANUFACTURER
08-00290	1 SW1	TL3700AF160Q	SWITCH, TACT, 0.02A@15V, 0.02A, 15V, SMD	E-SWITCH
13-00433	1 TP1	DNM	MECHANIC, OTHER, TEST PIN, PCB, SMD	HARWIN
18-29511	1 U1	TM4C1294NCPDTT3R	IC, MICROPROCESSOR, TIVA C SERIES MICROCONTROLLER, ARM CRTEX-M4, 2.97V TO 3.63V, TQFP128, SMD	TEXAS INSTRUME
18-29530	1 U2	TPS79601DR	IC, ANALOG, ULTRALOW-NOISE, HIGH PSRR, FAST, RF, 1A LOW-DROPOUT LINEAR REGULATORS, VIN:2.7V TO 5.5V, VOUT:1.2V TO 5.5V, SON8, SMD	TEXAS INSTRUME
18-29558	1 U3	LM4040B25IDCK		TEXAS INSTRUME
12-00745				NIHON DEMPA K
	= :=			
	1-12687 1-16574 1-04213 1-03904 1-11636 8-00290 3-00433 8-29511 8-29530 8-29558	1.12687 1 R18 1-16574 1 R19 1-16574 1 R20 1-04213 1 R20 1-03904 1 R21 1-11636 1 R22 8-00290 1 SW1 3-00433 1 TP1 8-29551 1 U1 8-29550 1 U2 8-29550 1 U3	1.12687 1 R18 4.87k 1.16574 1 R19 0 1.16574 1 R19 0 1.04213 1 R20 51k 1.043904 1 R21 30.1k 1.1636 1 R22 100 8.00290 1 SW1 113700AF160Q 3.00433 1 TP1 DNM 8.29551 1 U1 TMAC1294NCPDTT3R 8.29550 1 U2 TP579601DR 8.29550 1 U3 LM400825IDCK	1.12687

Manufacturer	MPN	PCB Package	Max Oper Temp	NOTE Status	RoHS Status
MANUFACTURER SELECTION	CAPACITOR_0402_10nF_X7R_M_+/-10%_25V	0402	+125DEGC	PREFERRED	ROHS_COMPLIANT
MANUFACTURER SELECTION	CAPACITOR_0402_100nF_X7R_M_+/-10%_10V	0402	+125DEGC	PREFERRED	ROHS_COMPLIANT
MANUFACTURER SELECTION	CAPACITOR_0402_1uF_X5R_I_+/-10%_10V	0402	+85DEGC	PREFERRED	ROHS COMPLIANT
MURATA	GRM155R61A104KA01D	0402	+85DEGC	PREFERRED	ROHS_COMPLIANT
MURATA	GRM155R60J225KE95D	0402	+85DEGC	PREFERRED	ROHS COMPLIANT
MANUFACTURER SELECTION	CAPACITOR_0402_12pF_C0G/NP0_M_+/-5%_50V	0402	+125DEGC	PREFERRED	ROHS_COMPLIANT
MURATA	GRM0332C1H150JA01D	0201	+125DEGC	PREFERRED	ROHS_COMPLIANT
OSRAM	LS L296-P2Q2-1	0603	+100DEGC	PREFERRED	ROHS COMPLIANT
OSRAM	LP L296-J2L2-25	0603	+100DEGC	NOT_PREFERRED	ROHS_COMPLIANT
TEXAS INSTRUMENTS	TPD4E004DRYR	SON6	+85DEGC	PREFERRED	ROHS_COMPLIANT
SAMTEC	LSS-110-01-F-DV-A-TR		+125DEGC	PREFERRED	ROHS_COMPLIANT
GRADCONN	BB02-CN102-KB8-000000		+105DEGC	PREFERRED	ROHS_COMPLIANT
MOLEX	47491-0001		+85DEGC	PREFERRED	ROHS_COMPLIANT
SAMTEC	FTS-110-02-L-D		+125DEGC	PREFERRED	ROHS_COMPLIANT
SHENZHEN NS-TECH	1125R-SMT-4P		+85DEGC	PREFERRED	PART NOT KNOWN
MANUFACTURER SELECTION	RESISTOR_0402_750k_+/-1%_50V_0.063W_M_+/-100PPM	0402	+155DEGC	PREFERRED	ROHS_COMPLIANT
MANUFACTURER SELECTION	RESISTOR_0402_51_+/-5%_50V_0.063W_M_+/-200PPM	0402	+155DEGC	PREFERRED	ROHS_COMPLIANT
MANUFACTURER SELECTION	RESISTOR_0402_10k_+/-5%_50V_0.063W_M_+/-200PPM	0402	+155DEGC	PREFERRED	ROHS_COMPLIANT
MANUFACTURER SELECTION	RESISTOR_0402_1k_+/-5%_50V_0.063W_M_+/-200ppm	0402	+155DEGC	PREFERRED	ROHS_COMPLIANT
MANUFACTURER SELECTION	RESISTOR_0402_33k_+/-1%_50V_0.063W_M_+/-100PPM	0402	+155DEGC	PREFERRED	ROHS_COMPLIANT
MANUFACTURER SELECTION	DNM	0402	N/A	PREFERRED	PART NOT KNOWN
MANUFACTURER SELECTION	RESISTOR_0402_680_+/-5%_50V_0.063W_M_+/-200PPM	0402	+155DEGC	PREFERRED	ROHS_COMPLIANT
MANUFACTURER SELECTION	RESISTOR_0402_120_+/-1%_50V_0.063W_M_+/-100PPM	0402	+155DEGC	PREFERRED	ROHS_COMPLIANT
MANUFACTURER SELECTION	RESISTOR_0402_330k_+/-1%_50V_0.063W_M_+/-100PPM	0402	+155DEGC	PREFERRED	ROHS_COMPLIANT
MANUFACTURER SELECTION	RESISTOR_0402_220k_+/-1%_50V_0.063W_M_+/-100PPM	0402	+155DEGC	PREFERRED	ROHS_COMPLIANT
MANUFACTURER SELECTION	RESISTOR_0402_100_+/-1%_50V_0.063W_M_+/-100PPM	0402	+155DEGC	PREFERRED	ROHS_COMPLIANT
DO NOT MOUNT	DNM	0402	N/A	PREFERRED	PART NOT KNOWN
MANUFACTURER SELECTION	RESISTOR_0402_4.87k_+/-1%_50V_0.063W_M_+/-100ppm	0402	+155DEGC	PREFERRED	ROHS_COMPLIANT
KOA SPEER	RK73Z1ETTPL	0402	+155DEGC	PREFERRED	ROHS_COMPLIANT
VISHAY	CRCW020151K0JNED	0201	+155DEGC	PREFERRED	ROHS_COMPLIANT
VISHAY	CRCW020130K1FKED	0201	+155DEGC	PREFERRED	ROHS_COMPLIANT
MANUFACTURER SELECTION	RESISTOR_0402_100_+/-5%_50V_0.063W_M_+/-200ppm	0402	+155DEGC	PREFERRED	ROHS_COMPLIANT
E-SWITCH	TL3700AF160Q		+85DEGC	PREFERRED	ROHS_COMPLIANT
HARWIN	S1751-06			PREFERRED	LEADED
TEXAS INSTRUMENTS	TM4C1294NCPDTT3R	TQFP128	+85DEGC	PREFERRED	ROHS_COMPLIANT
TEXAS INSTRUMENTS	TPS79601DRBR	SON8	+125DEGC	PREFERRED	ROHS_COMPLIANT
TEXAS INSTRUMENTS	LM4040B25IDCKR	SC70-5	+85DEGC	PREFERRED	ROHS_COMPLIANT
NIHON DEMPA KOGYO	NX3225GA-16.000M-STD-CRG-1		+85DEGC	PREFERRED	ROHS_COMPLIANT

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have *not* been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

## Products Applications

logic.ti.com

Audio www.ti.com/audio Automotive and Transportation www.ti.com/automotive **Amplifiers** amplifier.ti.com Communications and Telecom www.ti.com/communications **Data Converters** dataconverter.ti.com Computers and Peripherals www.ti.com/computers **DLP® Products** www.dlp.com Consumer Electronics www.ti.com/consumer-apps DSP dsp.ti.com **Energy and Lighting** www.ti.com/energy Clocks and Timers www.ti.com/clocks Industrial www.ti.com/industrial Interface interface.ti.com Medical www.ti.com/medical

Power Mgmt power.ti.com Space, Avionics and Defense www.ti.com/space-avionics-defense

Security

www.ti.com/security

Microcontrollers microcontroller.ti.com Video and Imaging www.ti.com/video

RFID www.ti-rfid.com

Logic

OMAP Applications Processors www.ti.com/omap TI E2E Community e2e.ti.com

Wireless Connectivity www.ti.com/wirelessconnectivity