# ACPM-9413 LTE Band 13 MIPI ET/APT PA 2.0 mm × 2.5 mm Power Amplifier Module

**Product Brief** 



The ACPM-9413 is a fully matched 10-pin surface mount power amplifier module developed for LTE Band 13. The 2 mm × 2.5 mm form-factor package is self contained, and it incorporates 50-ohm input and output matching networks.

The ACPM-9413 features CoolPAM circuit technology that supports two power modes—low and high. The CoolPAM is a stage bypass technology that enhances PAE (power added efficiency) at low power range.

The power amplifier is manufactured on an advanced InGaP HBT (hetero-junction bipolar transistor) MMIC (microwave monolithic integrated circuit) technology that offers state-of-the-art reliability, temperature stability, and ruggedness.

#### Features

- Thin package (0.93 mm typical)
- Excellent linearity in envelope tracking mode and average power tracking mode
- MIPI RFFE interface
- Two-mode power
- Quiescent current control for high power mode and low power mode
- Ten-pin surface mounting package
- Internal 50-ohm matching networks for both RF input and output
- Separate drive and output VCC supplies
- Low bypass capacitance
- Green Lead-free and RoHS compliant

#### **Applications**

Band 13 LTE


### **Ordering Information**

Part Number	Number of Devices	Container
ACPM-9413-TR1	1,000	178 mm (7 in.) tape/reel




# Package Dimensions

The dimensions are in millimeters.



# **Marking Specification**



- Date Code
- ZZ Assembly Lot Identification
- 9413 Device Code

#### **Pin Description**

Pin # Name		Description	
1	VCC1	DC supply voltage, connect to the RF stages' collector to which APT is applied (0.5V~3.5V)	
2	RFIN	RF input	
3	Vbat	DC supply voltage, connect to the bias circuitry with a fixed voltage (higher than 3.0V)	
4	Vio	RFFE enable	
5	Sdta	RFFE data	
6	Sclk	RFFE clock	
7	GND	Ground	
8	SEL	RFFE duplicate device select	
9	RFOUT	RF output	
10	VCC2	DC supply voltage, connect to the RF stages' collector to which APT is applied (0.5V~3.5V)	

For product information and a complete list of distributors, please go to our web site: www.avagotech.com

Avago, Avago Technologies, and the A logo are trademarks of Avago Technologies in the United States and other countries. All other brand and product names may be trademarks of their respective companies.

Data subject to change. Copyright © 2015 Avago Technologies. All Rights Reserved.

AV02-4860EN - 2015-03-24



